

Control Commands

Model No. PT-RQ35K
PT-RZ34K
PT-SRQ35KC
PT-SRZ34C



- Please refer to the Operating Instructions for the serial command format, limitations, connection and other details.
- シリアルコマンドのフォーマット、制限事項、接続方法およびその他詳細につきましては、各モデルの取扱説明書をご覧ください。
- 有关串行控制命令的格式、限制事项、连接方法以及其他详情、请参阅各机型的使用说明书。

Panasonic

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		RQ35K SERIES	RZ34K SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K SRQ35KC	RZ34K SRZ34KC	
BASIC OPERATIO N REMOTE CONTROL	POWER	ON		PON	QPW	001		✓	✓
		OFF (STANDBY)		POF		000		✓	✓
	INPUT SELECT	DVI		IIS: DVI	QIN	DVI		✓	✓
		HDMI1		IIS: HD1		HD1		✓	✓
		SD1		IIS: SD1		SD1		✓	✓
		DIGITAL LINK		IIS: DL1		DL1		✓	✓
	INPUT SELECT (DIGITAL LINK)	COMPUTER1		IIS: DL1: PC1	QIN	DL1: PC1		✓	✓
		COMPUTER2		IIS: DL1: PC2		DL1: PC2		✓	✓
		VIDEO		IIS: DL1: VID		DL1: VID		✓	✓
		HDMI1		IIS: DL1: HD1		DL1: HD1		✓	✓
		HDMI2		IIS: DL1: HD2		DL1: HD2		✓	✓
		S-VIDEO		IIS: DL1: SVD		DL1: SVD		✓	✓
	INPUT SELECT (SLOT)	SLOT1 : SD1		IIS: AU1, SD1	QIN	AU1, SD1		✓	✓
		SLOT1 : SD12		IIS: AU1, SD2		AU1, SD2		✓	✓
		SLOT1 : SD13		IIS: AU1, SD3		AU1, SD3		✓	✓
		SLOT1 : SD14		IIS: AU1, SD4		AU1, SD4		✓	✓
		SLOT2 : SD1		IIS: AU2, SD1		AU2, SD1		✓	✓
		SLOT2 : SD12		IIS: AU2, SD2		AU2, SD2		✓	✓
		SLOT2 : SD13		IIS: AU2, SD3		AU2, SD3		✓	✓
		SLOT2 : SD14		IIS: AU2, SD4		AU2, SD4		✓	✓
		SLOT1 : HDMI1		IIS: AU1, HD1		AU1, HD1		✓	✓
		SLOT1 : HDMI2		IIS: AU1, HD2		AU1, HD2		✓	✓
		SLOT2 : HDMI3		IIS: AU2, HD3		AU2, HD3		✓	✓
		SLOT2 : HDMI4		IIS: AU2, HD4		AU2, HD4		✓	✓
		SLOT1 : DVI1		IIS: AU1, DV1		AU1, DV1		✓	✓
		SLOT1 : DVI2		IIS: AU1, DV2		AU1, DV2		✓	✓
		SLOT2 : DVI3		IIS: AU2, DV3		AU2, DV3		✓	✓
		SLOT2 : DVI4		IIS: AU2, DV4		AU2, DV4		✓	✓
		SLOT1 : DisplayPort1		IIS: AU1, DP1		AU1, DP1		✓	✓
		SLOT1 : DisplayPort2		IIS: AU1, DP2		AU1, DP2		✓	✓
		SLOT2 : DisplayPort3		IIS: AU2, DP3		AU2, DP3		✓	✓
		SLOT2 : DisplayPort4		IIS: AU2, DP4		AU2, DP4		✓	✓
		SLOT1 : 12G SDI OPT1		IIS: AU1, OP1		AU1, OP1		✓	✓
		SLOT1 : 12G SDI OPT2		IIS: AU1, OP2		AU1, OP2		✓	✓
		SLOT2 : 12G SDI OPT1		IIS: AU2, OP1		AU2, OP1		✓	✓
		SLOT2 : 12G SDI OPT2		IIS: AU2, OP2		AU2, OP2		✓	✓
	FREEZE	OFF		OFZ: 0	QFZ	0		✓	✓
		ON		OFZ: 1		1		✓	✓
	MENU KEY			OMN				✓	✓
	ENTER KEY			OEN				✓	✓
	UP KEY			OCU				✓	✓
	DOWN KEY			OCD				✓	✓
	LEFT KEY			OCL				✓	✓
	RIGHT KEY			OCR				✓	✓
	DEFAULT KEY			OST				✓	✓
	AUTO SETUP KEY			OAS				✓	✓
	SHUTTER	OFF		OSH: 0	QSH	0		✓	✓
		ON		OSH: 1		1		✓	✓
	SHUTTER(Toggle)	OFF		OSH	QSH	0		✓	✓
		ON				1		✓	✓
FUNCTION KEY			FC1				✓	✓	
SYSTEM SELCTOR KEY			OSL				✓	✓	
ASPECT KEY			VS1				✓	✓	
NUMERIC KEY	0		ONK: 0				✓	✓	
	1		ONK: 1				✓	✓	
	2		ONK: 2				✓	✓	
	3		ONK: 3				✓	✓	
	4		ONK: 4				✓	✓	
	5		ONK: 5				✓	✓	
	6		ONK: 6				✓	✓	
	7		ONK: 7				✓	✓	
	8		ONK: 8				✓	✓	
	9		ONK: 9				✓	✓	
LENS HOME POSITION	EXECUTE		VXX: LNSI 1=+00001				✓	✓	
ACTIVE FOCUS OPTIMIZER-ACTIVE FOCUS	OFF		VXX: AFOI 1=+00000	QVX: AFOI 1	AFOI 1=+00000		✓	✓	
	ON		VXX: AFOI 1=+00001		AFOI 1=+00001		✓	✓	
ACTIVE FOCUS OPTIMIZER-FOCUS OFFSET BRIGHT	-00299		VXX: FOBI 1=- 00299	QVX: FOBI 1	FOBI 1=- 00299	-299	✓	-299	
	+00299		VXX: FOBI 1=+00299		FOBI 1=+00299	+299	✓	+299	
ACTIVE FOCUS OPTIMIZER-FOCUS OFFSET DARK	-00299		VXX: FODI 1=- 00299	QVX: FODI 1	FODI 1=- 00299	-299	✓	-299	
	+00299		VXX: FODI 1=+00299		FODI 1=+00299	+299	✓	+299	
ACTIVE FOCUS OPTIMIZER-INITILIZE	EXECUTE		VXX: FOI 1=+00001				✓	✓	
LENS SHIFT-HORIZONTAL	SLOW+		VXX: LNSI 2=+00000				✓	✓	
	SLOW-		VXX: LNSI 2=+00001				✓	✓	
	NORMAL+		VXX: LNSI 2=+00100				✓	✓	
	NORMAL-		VXX: LNSI 2=+00101				✓	✓	
	FAST+		VXX: LNSI 2=+00200				✓	✓	
	FAST-		VXX: LNSI 2=+00201				✓	✓	
LENS SHIFT-VERTICAL	SLOW+		VXX: LNSI 3=+00000				✓	✓	
	SLOW-		VXX: LNSI 3=+00001				✓	✓	
	NORMAL+		VXX: LNSI 3=+00100				✓	✓	
	NORMAL-		VXX: LNSI 3=+00101				✓	✓	
	FAST+		VXX: LNSI 3=+00200				✓	✓	
	FAST-		VXX: LNSI 3=+00201				✓	✓	
LENS FOCUS	SLOW+		VXX: LNSI 4=+00000				✓	✓	
	SLOW-		VXX: LNSI 4=+00001				✓	✓	
	NORMAL+		VXX: LNSI 4=+00100				✓	✓	
	NORMAL-		VXX: LNSI 4=+00101				✓	✓	
	FAST+		VXX: LNSI 4=+00200				✓	✓	
	FAST-		VXX: LNSI 4=+00201				✓	✓	
LENS ZOOM	SLOW+		VXX: LNSI 5=+00000				✓	✓	
	SLOW-		VXX: LNSI 5=+00001				✓	✓	
	NORMAL+		VXX: LNSI 5=+00100				✓	✓	
	NORMAL-		VXX: LNSI 5=+00101				✓	✓	
	FAST+		VXX: LNSI 5=+00200				✓	✓	
	FAST-		VXX: LNSI 5=+00201				✓	✓	
LENS POSITION HORIZONTAL	-02480		VXX: LNSI 7=- 02480	QVX: LNSI 7	LNSI 7=- 02480		✓	✓	
	+02480		VXX: LNSI 7=+02480		LNSI 7=+02480		✓	✓	
LENS POSITION VERTICAL	-03200		VXX: LNSI 8=- 03200	QVX: LNSI 8	LNSI 8=- 03200		✓	✓	
	+03200		VXX: LNSI 8=+03200		LNSI 8=+03200		✓	✓	
LENS POSITION FOCUS	+00000		VXX: LNSI 9=+00000	QVX: LNSI 9	LNSI 9=+00000		✓	✓	
	+02560		VXX: LNSI 9=+02560		LNSI 9=+02560		✓	✓	
LENS POSITION H/V	-02480/-03200		VXX: LNSSB=- 02480- 03200	QVX: LNSSB	LNSSB=- 02480- 03200		✓	✓	
	+02480/+03200		VXX: LNSSB=+02480+03200		LNSSB=+02480+03200		✓	✓	
LENS POSITION H/V FOCUS	-02480/-03200/+00000		VXX: LNSSC=- 02480- 03200+00000	QVX: LNSSC	LNSSC=- 02480- 03200+00000		✓	✓	
	+02480/+03200/+02560		VXX: LNSSC=+02480+03200+02560		LNSSC=+02480+03200+02560		✓	✓	
STATUS KEY			STS				✓	✓	
LENS FOCUS KEY			OLF				✓	✓	
LENS SHIFT KEY			OLH				✓	✓	
LENS ZOOM KEY			OLZ				✓	✓	
DIGITAL LINK KEY			DLK				✓	✓	
INPUT MENU KEY			IPT				✓	✓	
SELF DIAGNOSIS				QVX: ERRS1	ERRS1=*****		✓	✓	
				QVX: ERRS2	ERRS2=*****		✓	✓	
PICTURE MODE	DYNAMIC		VPM: DYN	QPM	DYN		✓	✓	
	NATURAL		VPM: NAT		NAT		✓	✓	
	STANDARD		VPM: STD		STD		✓	✓	
	CINEMA		VPM: CIN		CIN		✓	✓	
	GRAPHIC		VPM: GRA		GRA		✓	✓	
	DICOM SIM.		VPM: DIC		DIC		✓	✓	
	USER		VPM: USR		USR		✓	✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		RQ35K SERIES	RZ34K SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K SRQ35KC	RZ34K SRZ34KC	
PICTURE	PICTURE MODE-NAME SETTING USER	PICTUREMODE		VXX: NCGS0=PICTUREMODE	QVX: NCGS0	NCGS0=PICTUREMODE		✓	✓
	PICTURE MODE-NAME CLEAR USER	PICTUREMODE		VXX: NCLI 0=+00000				✓	✓
	CONTRAST	+1 +63		VCN: 001 VCN: 063	QVR	001 063		✓	✓
	BRIGHTNESS	+1 +63		VBR: 001 VBR: 063	QVB	001 063		✓	✓
	COLOR	+1 +63		VCO: 001 VCO: 063	QVC	001 063		✓	✓
	TINT	+1 +63		VTN: 001 VTN: 063	QVT	001 063		✓	✓
	SHARPNESS	0 15		VSR: 000 VSR: 015	QVS	000 015		✓	✓
	COLOR TEMPERATURE	USER1(USER) USER2 DEFAULT 3200K 3300K 9200K 9300K 9400K 12900K 13000K		OTE: 04 OTE: 09 OTE: 10 OTE: 3200 OTE: 3300 OTE: 9200 OTE: 9300 OTE: 9400 OTE: 12900 OTE: 13000	QTE	4 9 10 3200 3300 9200 9300 9400 12900 13000		✓	✓
	COLOR TEMP-NAME SETTING USER1	COLORTEMP1		VXX: NCGS1=COLORTEMP1	QVX: NCGS1	NCGS1=COLORTEMP1		✓	✓
	COLOR TEMP-NAME SETTING USER2	COLORTEMP2		VXX: NCGS3=COLORTEMP2	QVX: NCGS3	NCGS3=COLORTEMP2		✓	✓
	COLOR TEMP-NAME CLEAR USER1	COLORTEMP1		VXX: NCLI 1=+00000				✓	✓
	COLOR TEMP-NAME CLEAR USER2	COLORTEMP2		VXX: NCLI 3=+00000				✓	✓
	WHITE BALANCE LOW-RED	-127 +127		VOR: 001 VOR: 255	QOR	001 255		✓	✓
	WHITE BALANCE LOW-GREEN	-127 +127		VOG: 001 VOG: 255	QOG	001 255		✓	✓
	WHITE BALANCE LOW-BLUE	-127 +127		VOB: 001 VOB: 255	QOB	001 255		✓	✓
	WHITE BALANCE HIGH-RED	0 +255		VHR: 000 VHR: 255	QHR	000 255		✓	✓
	WHITE BALANCE HIGH-GREEN	0 +255		VHG: 000 VHG: 255	QHG	000 255		✓	✓
	WHITE BALANCE HIGH-BLUE	0 +255		VHB: 000 VHB: 255	QHB	000 255		✓	✓
	GAMMA	1.0 1.8 2.0 2.1 2.2 2.3 2.4 2.5 2.6 2.7 2.8 USER1 USER2 DICOM HDR HLG HDR ST2048-500 HDR ST2048-1000 DEFAULT		VGA: 1. 0 VGA: 1. 8 VGA: 2. 0 VGA: 2. 1 VGA: 2. 2 VGA: 2. 3 VGA: 2. 4 VGA: 2. 5 VGA: 2. 6 VGA: 2. 7 VGA: 2. 8 VGA: US1 VGA: US2 VGA: DI C VGA: HD1 VGA: HD2 VGA: HD3 VGA: DEF	QGA	1. 0 1. 8 2. 0 2. 1 2. 2 2. 3 2. 4 2. 5 2. 6 2. 7 2. 8 US1 US2 DI C HD1 HD2 HD3 DEF		✓	✓
	GAMMA-HDR HLG SYSTEM GAMMA	min. max.	(0.1step)	VXX: HLGS1=+1. 00 VXX: HLGS1=+1. 62	QVX: HLGS1	HLGS1=1. 00 HLGS1=1. 62		✓	✓
	GAMMA-NAME SETTING USER1	GAMMAUSER1		VXX: NCGS2=GAMMAUSER1	QVX: NCGS2	NCGS2=GAMMAUSER1		✓	✓
	GAMMA-NAME SETTING USER2	GAMMAUSER2		VXX: NCGS4=GAMMAUSER2	QVX: NCGS4	NCGS4=GAMMAUSER2		✓	✓
	GAMMA-NAME CLEAR USER1	GAMMAUSER1		VXX: NCLI 2=+00000				✓	✓
	GAMMA-NAME CLEAR USER2	GAMMAUSER2		VXX: NCLI 4=+00000				✓	✓
	DAYLIGHT VIEW FRONT INSTALL	OFF AUTO(1) ON(2) ON(3) 4 5 6		VXX: DLVI 0=+00000 VXX: DLVI 0=+00001 VXX: DLVI 0=+00002 VXX: DLVI 0=+00003 VXX: DLVI 0=+00004 VXX: DLVI 0=+00005 VXX: DLVI 0=+00006	QVX: DLVI 0	DLVI 0=+00000 DLVI 0=+00001 DLVI 0=+00002 DLVI 0=+00003 DLVI 0=+00004 DLVI 0=+00005 DLVI 0=+00006		✓	✓
	NOISE REDUCTION	OFF 1 2 3 4 5 6		VNS: 0 VNS: 1 VNS: 2 VNS: 3 VNS: 4 VNS: 5 VNS: 6	QNS	0 1 2 3 4 5 6		✓	✓
	DYNAMIC CONTRAST/IRIS	OFF 1 2 3 USER		OAI: 0 OAI: 1 OAI: 2 OAI: 3 OAI: 4	QAI	0 1 2 3 4		✓	✓
	DYNAMIC CONTRAST/AUTO IRIS (AUTO CONTRAST)	OFF 1 255		OAI: A000 OAI: A001 OAI: A255	QAI: A	000 001 255		✓	✓
	DYNAMIC CONTRAST (BRIGHT SIGNAL LEVEL)	6% 50%		VXX: DYCI 1=+00006 VXX: DYCI 1=+00050	QVX: DYCI 1	00006 00050		✓	✓
	DYNAMIC CONTRAST (LIGHTS OUT TIMER)	DISABLE 0.0s 10.0s		VXX: DYCS2=OFF VXX: DYCS2=0. 0 VXX: DYCS2=10. 0	QVX: DYCS2	OFF 0. 0 10. 0		✓	✓
	DYNAMIC CONTRAST (LIGHTS OUT SIGNAL LEVEL)	0 5		VXX: DYCI 3=+00000 VXX: DYCI 3=+00005	QVX: DYCI 3	00000 00005		✓	✓
	DYNAMIC CONTRAST (LIGHTS OUT FADE-IN)	0.0s(OFF) 0.5s 1.0s 1.5s 2.0s 2.5s 3.0s 3.5s 4.0s 5.0s 7.0s 10.0s		VXX: DYCS4=0. 0 VXX: DYCS4=0. 5 VXX: DYCS4=1. 0 VXX: DYCS4=1. 5 VXX: DYCS4=2. 0 VXX: DYCS4=2. 5 VXX: DYCS4=3. 0 VXX: DYCS4=3. 5 VXX: DYCS4=4. 0 VXX: DYCS4=5. 0 VXX: DYCS4=7. 0 VXX: DYCS4=10. 0	QVX: DYCS4	DYCS4=0. 0 DYCS4=0. 5 DYCS4=1. 0 DYCS4=1. 5 DYCS4=2. 0 DYCS4=2. 5 DYCS4=3. 0 DYCS4=3. 5 DYCS4=4. 0 DYCS4=5. 0 DYCS4=7. 0 DYCS4=10. 0		✓	✓
	DYNAMIC CONTRAST (LIGHTS OUT FADE-OUT)	0.0s(OFF) 0.5s 1.0s 1.5s 2.0s 2.5s 3.0s 3.5s 4.0s 5.0s 7.0s 10.0s		VXX: DYCS5=0. 0 VXX: DYCS5=0. 5 VXX: DYCS5=1. 0 VXX: DYCS5=1. 5 VXX: DYCS5=2. 0 VXX: DYCS5=2. 5 VXX: DYCS5=3. 0 VXX: DYCS5=3. 5 VXX: DYCS5=4. 0 VXX: DYCS5=5. 0 VXX: DYCS5=7. 0 VXX: DYCS5=10. 0	QVX: DYCS5	DYCS5=0. 0 DYCS5=0. 5 DYCS5=1. 0 DYCS5=1. 5 DYCS5=2. 0 DYCS5=2. 5 DYCS5=3. 0 DYCS5=3. 5 DYCS5=4. 0 DYCS5=5. 0 DYCS5=7. 0 DYCS5=10. 0		✓	✓
	DYNAMIC CONTRAST/MANUAL IRIS (MANUAL INTENSITY)	OFF 1 255		OAI: M000 OAI: M001 OAI: M255	QAI: M	000 001 255		✓	✓
	DYNAMIC CONTRAST (DYNAMIC GAMMA)	OFF 1 2		OAI: D0 OAI: D1 OAI: D2	QAI: D	0 1 2		✓	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ35K SERIES	RZ34K SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K SRQ35KC	RZ34K SRZ34KC
POSITION	COLOR SPACE	3		OAI: D3		3	✓	✓
		NATIVE		VXX: CSPI 1=+00000	QVX: CSPI 1	CSPI 1=+00000	✓	✓
		ITU-709		VXX: CSPI 1=+00001		CSPI 1=+00001	✓	✓
		DCI-P3		VXX: CSPI 1=+00002		CSPI 1=+00002	✓	✓
	SYSTEM SELECTOR RGB(VGA/480P)	ITU2020		VXX: CSPI 1=+00003		CSPI 1=+00003	✓	✓
		VGA60		ORF: 0	QRF	0	✓	✓
		480P(YCbCr)		ORF: 1		1	✓	✓
	SYSTEM SELECTOR RGB(Other)/DVI/SLOT-DVI	480p(RGB)		ORF: 3		3	✓	✓
		RGB		ORF: 0	QRF	0	✓	✓
	SYSTEM SELECTOR HDMI/DIGITAL LINK/SLOT-HDMI	YPbPr		ORF: 1		1	✓	✓
RGB			ORF: 0	QRF	0	✓	✓	
GEOMETRY	SYSTEM SELECTOR HDMI/DIGITAL LINK/SLOT-HDMI	YPbPr		ORF: 1		1	✓	✓
		AUTO		ORF: 2		2	✓	✓
		OFF		VXX: GMMI 0=+00000	QVX: GMMI 0	GMMI 0=+00000	✓	✓
		KEYSTONE		VXX: GMMI 0=+00001		GMMI 0=+00001	✓	✓
		CURVED		VXX: GMMI 0=+00002		GMMI 0=+00002	✓	✓
		PC-1		VXX: GMMI 0=+00003		GMMI 0=+00003	✓	✓
	GEOMETRY-KEYSTONE- LENS THROW RATIO	PC-2		VXX: GMMI 0=+00004		GMMI 0=+00004	✓	✓
		PC-3		VXX: GMMI 0=+00005		GMMI 0=+00005	✓	✓
		CORNER-CORRECTION		VXX: GMMI 0=+00010		GMMI 0=+00010	✓	✓
		0.7	0.1 step	VXX: GMKSO=+00. 7	QVX: GMKSO	GMKSO=+00. 7	✓	✓
GEOMETRY-KEYSTONE- VERTICAL BALANCE	16.5		VXX: GMKSO=+16. 5		GMKSO=+16. 5	✓	✓	
	-60		VXX: GMKI 4=- 00060	QVX: GMKI 4	GMKI 4=- 00060	✓	✓	
GEOMETRY-KEYSTONE- HORIZONTAL BALANCE	+60		VXX: GMKI 4=+00060		GMKI 4=+00060	✓	✓	
	-30		VXX: GMKI 7=- 00030	QVX: GMKI 7	GMKI 7=- 00030	✓	✓	
GEOMETRY-KEYSTONE- VERTICAL KEYSTONE	+30		VXX: GMKI 7=+00030		GMKI 7=+00030	✓	✓	
	-40.0 (-45.0)*	0.2 step	VXX: GMKS8=- 40. 0	QVX: GMKS8	GMKS8=- 40. 0	✓	✓	
GEOMETRY-KEYSTONE- HORIZONTAL KEYSTONE	+40.0 (+45.0)*		VXX: GMKS8=+40. 0		GMKS8=+40. 0	✓	✓	
	-15.0 (-40.0)*	0.2 step	VXX: GMKS9=- 15. 0	QVX: GMKS9	GMKS9=- 15. 0	✓	✓	
GEOMETRY-CURVED-LENS THROU RATIO	+15.0 (+40.0)*		VXX: GMKS9=+15. 0		GMKS9=+15. 0	✓	✓	
	0.7	0.1 step	VXX: GMCSO=+00. 7	QVX: GMCSO	GMCSO=+00. 7	✓	✓	
GEOMETRY-CURVED- VERTICAL ARC	16.5		VXX: GMCSO=+16. 5		GMCSO=+16. 5	✓	✓	
	-50 (-100)*		VXX: GMCI 3=- 00050	QVX: GMCI 3	GMCI 3=- 00050	✓	✓	
GEOMETRY-CURVED- HORIZONTAL ARC	+50 (+100)*		VXX: GMCI 3=+00050		GMCI 3=+00050	✓	✓	
	-50 (-100)*		VXX: GMCI 7=- 00050	QVX: GMCI 7	GMCI 7=- 00050	✓	✓	
GEOMETRY-CURVED- VERTICAL BALANCE	+50 (+100)*		VXX: GMCI 7=+00050		GMCI 7=+00050	✓	✓	
	-60		VXX: GMCI 2=- 00060	QVX: GMCI 2	GMCI 2=- 00060	✓	✓	
GEOMETRY-CURVED- HORIZONTAL BALANCE	+60		VXX: GMCI 2=+00060		GMCI 2=+00060	✓	✓	
	-30		VXX: GMCI 6=- 00030	QVX: GMCI 6	GMCI 6=- 00030	✓	✓	
GEOMETRY-CURVED- VERTICAL KEYSTONE	+30		VXX: GMCI 6=+00030		GMCI 6=+00030	✓	✓	
	-40.0 (-45.0)*	0.2 step	VXX: GMCS8=- 40. 0	QVX: GMCS8	GMCS8=- 40. 0	✓	✓	
GEOMETRY-CURVED- HORIZONTAL KEYSTONE	+40.0 (+45.0)*		VXX: GMCS8=+40. 0		GMCS8=+40. 0	✓	✓	
	-15.0 (-40.0)*	0.2 step	VXX: GMCS9=- 15. 0	QVX: GMCS9	GMCS9=- 15. 0	✓	✓	
GEOMETRY-CURVED- MAINTAIN ASPECT RATIO	+15.0 (+40.0)*		VXX: GMCS9=+15. 0		GMCS9=+15. 0	✓	✓	
	OFF		VXX: GMCI A=+00000	QVX: GMCI A	GMCI A=+00000	✓	✓	
GEOMETRY-CORNER CORRECTION-UPPER LEFT(V)	ON		VXX: GMCI A=+00001		GMCI A=+00001	✓	✓	
	min.		VXX: GMFI 1=+00000	QVX: GMFI 1	GMFI 1=+00000	0	0	
GEOMETRY-CORNER CORRECTION-UPPER RIGHT(V)	max.		VXX: GMFI 1=+00300		GMFI 1=+00300	+300	+300	
	min.		VXX: GMFI 2=+00000	QVX: GMFI 2	GMFI 2=+00000	0	0	
GEOMETRY-CORNER CORRECTION-LOWER LEFT(V)	max.		VXX: GMFI 2=+00300		GMFI 2=+00300	+300	+300	
	min.		VXX: GMFI 3=- 00300	QVX: GMFI 3	GMFI 3=- 00300	-300	-300	
GEOMETRY-CORNER CORRECTION-LOWER RIGHT(V)	max.		VXX: GMFI 3=+00000		GMFI 3=+00000	0	0	
	min.		VXX: GMFI 4=- 00300	QVX: GMFI 4	GMFI 4=- 00300	-300	-300	
GEOMETRY-CORNER CORRECTION-LINEARITY(V)	max.		VXX: GMFI 4=+00000		GMFI 4=+00000	0	0	
	min.		VXX: GMFI 5=- 00127	QVX: GMFI 5	GMFI 5=- 00127	-127	-127	
GEOMETRY-CORNER CORRECTION-UPPER LEFT(H)	max.		VXX: GMFI 5=+00127		GMFI 5=+00127	+127	+127	
	min.		VXX: GMFI 6=+00000	QVX: GMFI 6	GMFI 6=+00000	0	0	
GEOMETRY-CORNER CORRECTION-UPPER RIGHT(H)	max.		VXX: GMFI 6=+00480		GMFI 6=+00480	+480	+480	
	min.		VXX: GMFI 7=- 00480	QVX: GMFI 7	GMFI 7=- 00480	-480	-480	
GEOMETRY-CORNER CORRECTION-LOWER LEFT(H)	max.		VXX: GMFI 7=+00000		GMFI 7=+00000	0	0	
	min.		VXX: GMFI 8=+00000	QVX: GMFI 8	GMFI 8=+00000	0	0	
GEOMETRY-CORNER CORRECTION-LOWER RIGHT(H)	max.		VXX: GMFI 8=+00480		GMFI 8=+00480	+480	+480	
	min.		VXX: GMFI 9=- 00480	QVX: GMFI 9	GMFI 9=- 00480	-480	-480	
GEOMETRY-CORNER CORRECTION-LINEARITY(H)	max.		VXX: GMFI 9=+00000		GMFI 9=+00000	0	0	
	min.		VXX: GMFI A=- 00127	QVX: GMFI A	GMFI A=- 00127	-127	-127	
GEOMETRY-CORNER/PINCUSHION- PINCUSHION UPPER	max.		VXX: GMFI A=+00127		GMFI A=+00127	+127	+127	
	min.		VXX: GMFI B=- 00100	QVX: GMFI B	GMFI B=- 00100	✓	✓	
GEOMETRY-CORNER/PINCUSHION- PINCUSHION LOWER	max.		VXX: GMFI B=+00100		GMFI B=+00100	✓	✓	
	min.		VXX: GMFI C=- 00100	QVX: GMFI C	GMFI C=- 00100	✓	✓	
GEOMETRY-CORNER/PINCUSHION- PINCUSHION LEFT	max.		VXX: GMFI C=+00100		GMFI C=+00100	✓	✓	
	min.		VXX: GMFI D=- 00100	QVX: GMFI D	GMFI D=- 00100	✓	✓	
GEOMETRY-CORNER/PINCUSHION- PINCUSHION RIGHT	max.		VXX: GMFI D=+00100		GMFI D=+00100	✓	✓	
	min.		VXX: GMFI E=- 00100	QVX: GMFI E	GMFI E=- 00100	✓	✓	
GEOMETRY-CORNER/PINCUSHION- LINEARITY	max.		VXX: GMFI E=+00100		GMFI E=+00100	✓	✓	
	min.		VXX: GMFI F=+00000	QVX: GMFI F	GMFI F=+00000	✓	✓	
GEOMETRY - FREE GRID (ON/OFF)	MANUAL		VXX: GMFI F=+00001		GMFI F=+00001	✓	✓	
	OFF		VXX: GMGI 1=+00000	QVX: GMGI 1	GMGI 1=+00000	✓	✓	
GEOMETRY - FREE GRID - INITIALIZE	ON		VXX: GMGI 1=+00001		GMGI 1=+00001	✓	✓	
	2x2		VXX: GMGI 2=+00001		GMGI 2=+00001	✓	✓	
GEOMETRY - FREE GRID - GRID RESOLUTION	3x3		VXX: GMGI 3=+00002	QVX: GMGI 3	GMGI 3=+00002	✓	✓	
	5x5		VXX: GMGI 3=+00003		GMGI 3=+00003	✓	✓	
	9x9		VXX: GMGI 3=+00005		GMGI 3=+00005	✓	✓	
	17x17		VXX: GMGI 3=+00009		GMGI 3=+00009	✓	✓	
	17x17		VXX: GMGI 3=+00017		GMGI 3=+00017	✓	✓	
GEOMETRY - FREE GRID - GRID COLOR	OFF		VXX: GMGI 4=+00000	QVX: GMGI 4	GMGI 4=+00000	✓	✓	
	WHITE		VXX: GMGI 4=+00001		GMGI 4=+00001	✓	✓	
	BLACK		VXX: GMGI 4=+00002		GMGI 4=+00002	✓	✓	
	RED		VXX: GMGI 4=+00003		GMGI 4=+00003	✓	✓	
	GREEN		VXX: GMGI 4=+00004		GMGI 4=+00004	✓	✓	
	BLUE		VXX: GMGI 4=+00005		GMGI 4=+00005	✓	✓	
	CYAN		VXX: GMGI 4=+00006		GMGI 4=+00006	✓	✓	
	MAGENTA		VXX: GMGI 4=+00007		GMGI 4=+00007	✓	✓	
	YELLOW		VXX: GMGI 4=+00008		GMGI 4=+00008	✓	✓	
GEOMETRY - FREE GRID - CONTROL POINTS	POINT		VXX: GMGI 5=+00000	QVX: GMGI 5	GMGI 5=+00000	✓	✓	
	HORIZONTAL LINE		VXX: GMGI 5=+00001		GMGI 5=+00001	✓	✓	
	VERTICAL LINE		VXX: GMGI 5=+00002		GMGI 5=+00002	✓	✓	
	1		VXX: GMGI 7=+00001	QVX: GMGI 7	GMGI 7=+00001	✓	✓	
GEOMETRY - FREE GRID - CONTROL POINTS COLOR	10		VXX: GMGI 7=+00010		GMGI 7=+00010	✓	✓	
	WHITE		VXX: GMGI 8=+00001	QVX: GMGI 8	GMGI 8=+00001	✓	✓	
	BLACK		VXX: GMGI 8=+00002		GMGI 8=+00002	✓	✓	
	RED		VXX: GMGI 8=+00003		GMGI 8=+00003	✓	✓	
	GREEN		VXX: GMGI 8=+00004		GMGI 8=+00004	✓	✓	
	BLUE		VXX: GMGI 8=+00005		GMGI 8=+00005	✓	✓	
	CYAN		VXX: GMGI 8=+00006		GMGI 8=+00006	✓	✓	
	MAGENTA		VXX: GMGI 8=+00007		GMGI 8=+00007	✓	✓	
YELLOW		VXX: GMGI 8=+00008		GMGI 8=+00008	✓	✓		
CONVERGENCE	OFF		VXX: CNVI 1=+00000	QVX: CNVI 1	CNVI 1=+00000	✓	✓	
	ON		VXX: CNVI 1=+00001		CNVI 1=+00001	✓	✓	
CONVERGENCE - UPPER LEFT VERTICAL			VXX: CNVS2=*: *****	QVX: CNVS2	CNVS2=*: *****	✓	✓	
			VXX: CNVS2=R: *****		CNVS2=R: *****	✓	✓	
			VXX: CNVS2=G: *****		CNVS2=G: *****	✓	✓	
			VXX: CNVS2=B: *****		CNVS2=B: *****	✓	✓	
			VXX: CNVS2=*: +00. 00		CNVS2=*: +00. 00	✓	✓	
CONVERGENCE - UPPER LEFT HORIZONTAL			VXX: CNVS2=*: +03. 75		CNVS2=*: +03. 75	✓	✓	
			VXX: CNVS3=*: *****	QVX: CNVS3	CNVS3=*: *****	✓	✓	
			VXX: CNVS3=R: *****		CNVS3=R: *****	✓	✓	
			VXX: CNVS3=G: *****		CNVS3=G: *****	✓	✓	
			VXX: CNVS3=B: *****		CNVS3=B: *****	✓	✓	
		VXX: CNVS3=*: +00. 00		CNVS3=*: +00. 00	✓	✓		
		VXX: CNVS3=*: +03. 75		CNVS3=*: +03. 75	✓	✓		

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ35K SERIES	RZ34K SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K SRQ35KC	RZ34K SRZ34KC
CONVERGENCE	CONVERGENCE - UPPER RIGHT VERTICAL			VXX: CNVS4=*: *****	QVX: CNVS4	CNVS4=*: *****	✓	✓
				VXX: CNVS4=R: *****		CNVS4=R: *****	✓	✓
				VXX: CNVS4=G: *****		CNVS4=G: *****	✓	✓
				VXX: CNVS4=B: *****		CNVS4=B: *****	✓	✓
				VXX: CNVS4=*: +00. 00		CNVS4=*: +00. 00	✓	✓
				VXX: CNVS4=*: +03. 75		CNVS4=*: +03. 75	✓	✓
	CONVERGENCE - UPPER RIGHT HORIZONTAL			VXX: CNVS5=*: *****	QVX: CNVS5	CNVS5=*: *****	✓	✓
				VXX: CNVS5=R: *****		CNVS5=R: *****	✓	✓
				VXX: CNVS5=G: *****		CNVS5=G: *****	✓	✓
				VXX: CNVS5=B: *****		CNVS5=B: *****	✓	✓
				VXX: CNVS5=*: - 03. 75		CNVS5=*: - 03. 75	✓	✓
				VXX: CNVS5=*: +00. 00		CNVS5=*: +00. 00	✓	✓
	CONVERGENCE - LOWER LEFT VERTICAL			VXX: CNVS6=*: *****	QVX: CNVS6	CNVS6=*: *****	✓	✓
				VXX: CNVS6=R: *****		CNVS6=R: *****	✓	✓
				VXX: CNVS6=G: *****		CNVS6=G: *****	✓	✓
				VXX: CNVS6=B: *****		CNVS6=B: *****	✓	✓
				VXX: CNVS6=*: +00. 00		CNVS6=*: +00. 00	✓	✓
				VXX: CNVS6=*: +03. 75		CNVS6=*: +03. 75	✓	✓
	CONVERGENCE - LOWER LEFT HORIZONTAL			VXX: CNVS7=*: *****	QVX: CNVS7	CNVS7=*: *****	✓	✓
				VXX: CNVS7=R: *****		CNVS7=R: *****	✓	✓
				VXX: CNVS7=G: *****		CNVS7=G: *****	✓	✓
				VXX: CNVS7=B: *****		CNVS7=B: *****	✓	✓
				VXX: CNVS7=*: - 03. 75		CNVS7=*: - 03. 75	✓	✓
				VXX: CNVS7=*: +00. 00		CNVS7=*: +00. 00	✓	✓
CONVERGENCE - LOWER RIGHT VERTICAL			VXX: CNVS8=*: *****	QVX: CNVS8	CNVS8=*: *****	✓	✓	
			VXX: CNVS8=R: *****		CNVS8=R: *****	✓	✓	
			VXX: CNVS8=G: *****		CNVS8=G: *****	✓	✓	
			VXX: CNVS8=B: *****		CNVS8=B: *****	✓	✓	
			VXX: CNVS8=*: - 03. 75		CNVS8=*: - 03. 75	✓	✓	
			VXX: CNVS8=*: +00. 00		CNVS8=*: +00. 00	✓	✓	
CONVERGENCE - LOWER RIGHT HORIZONTAL			VXX: CNVS9=*: *****	QVX: CNVS9	CNVS9=*: *****	✓	✓	
			VXX: CNVS9=R: *****		CNVS9=R: *****	✓	✓	
			VXX: CNVS9=G: *****		CNVS9=G: *****	✓	✓	
			VXX: CNVS9=B: *****		CNVS9=B: *****	✓	✓	
			VXX: CNVS9=*: - 03. 75		CNVS9=*: - 03. 75	✓	✓	
			VXX: CNVS9=*: +00. 00		CNVS9=*: +00. 00	✓	✓	
SHIFT-HORIZONTAL	0		VTH: 0000	QTH	0000	✓	✓	
	+4095		VTH: 4095		4095	✓	✓	
SHIFT-VERTICAL	0		VTV: 0000	QTV	0000	✓	✓	
	+4094		VTV: 4094		4094	✓	✓	
ASPECT	AUTO/VID AUTO/DEFAULT		VSE: 0	QSE	0	✓	✓	
	NORMAL(4:3)		VSE: 1		1	✓	✓	
	WIDE(16:9)		VSE: 2		2	✓	✓	
	NATIVE(through)		VSE: 5		5	✓	✓	
	FULL(HV FIT)		VSE: 6		6	✓	✓	
	H-FIT		VSE: 9		9	✓	✓	
	V-FIT		VSE: 10		10	✓	✓	
ZOOM-HORIZONTAL	50		OZH: 050	QZH	050	✓	✓	
	999		OZH: 999		999	✓	✓	
ZOOM-VERTICAL	50		OZV: 050	QZV	050	✓	✓	
	999		OZV: 999		999	✓	✓	
ZOOM-BOTH	50		OZO: 050	QZO	050	✓	✓	
	999		OZO: 999		999	✓	✓	
ZOOM-INTERLOCKED	OFF		OZS: 0	QZS	0	✓	✓	
	ON		OZS: 1		1	✓	✓	
ZOOM-MODE	INTERNAL		OZT: 0	QZT	0	✓	✓	
	FULL		OZT: 1		1	✓	✓	
DIGITAL CINEMA REALITY	AUTO		OPD: 0	QPD	0	✓	✓	
	OFF		OPD: 1		1	✓	✓	
	30p/25p FIXED		OPD: 2		2	✓	✓	
GRADATION SMOOTHER	OFF		VXX: GRSI 1=+00000	QVX: GRSI 1	GRSI 1=+00000	✓		
	1		VXX: GRSI 1=+00001		GRSI 1=+00001	✓		
	2		VXX: GRSI 1=+00002		GRSI 1=+00002	✓		
	3		VXX: GRSI 1=+00003		GRSI 1=+00003	✓		
BLANKING-UPPER	min.		DBU: 000	QLU	000	0	0	
	max.		DBU: 2398		2398	2398	1198	
BLANKING-LOWER	min.		DBB: 000	QLB	000	0	0	
	max.		DBB: 2398		2398	2398	1198	
BLANKING-RIGHT	min.		DBR: 000	QLR	000	0	0	
	max.		DBR: 3838		3838	3838	1918	
BLANKING-LEFT	min.		DBL: 000	QLL	000	0	0	
	max.		DBL: 3838		3838	3838	1918	
CUSTOM MASKING *	OFF		VXX: MSKI 1=+00000	QVX: MSKI 1	MSKI 1=+00000	✓	✓	
	PC-1		VXX: MSKI 1=+00001		MSKI 1=+00001	✓	✓	
	PC-2		VXX: MSKI 1=+00002		MSKI 1=+00002	✓	✓	
	PC-3		VXX: MSKI 1=+00003		MSKI 1=+00003	✓	✓	
EDGE BLENDING	OFF		VXX: EDBI 0=+00000	QVX: EDBI 0	EDBI 0=+00000	✓	✓	
	ON		VXX: EDBI 0=+00001		EDBI 0=+00001	✓	✓	
EDGE BLENDING-UPPER ON/OFF	OFF		VGU: 0	QGU	0	✓	✓	
	ON		VGU: 1		1	✓	✓	
EDGE BLENDING-LOWER ON/OFF	OFF		VGB: 0	QGB	0	✓	✓	
	ON		VGB: 1		1	✓	✓	
EDGE BLENDING-LEFT ON/OFF	OFF		VGL: 0	QGL	0	✓	✓	
	ON		VGL: 1		1	✓	✓	
EDGE BLENDING-RIGHT ON/OFF	OFF		VGR: 0	QGR	0	✓	✓	
	ON		VGR: 1		1	✓	✓	
EDGE BLENDING-START-UPPER	min.		VEU: 0000	QEU	0000	0	0	
	max.		VEU: 2272		2272	2272	1023	
EDGE BLENDING-START-LOWER	min.		VEB: 0000	QEB	0000	0	0	
	max.		VEB: 2272		2272	2272	1199	
EDGE BLENDING-START-LEFT	min.		VEL: 0000	QEL	0000	0	0	
	max.		VEL: 3712		3712	3712	1023	
EDGE BLENDING-START-RIGHT	min.		VER: 0000	QER	0000	0	0	
	max.		VER: 3712		3712	3712	1919	
EDGE BLENDING-WIDTH-UPPER	min.		VXX: EUWI 0=+00000	QVX: EUWI 0	EUWI 0=+00000	0	0	
	max.		VXX: EUWI 0=+02272		EUWI 0=+02272	2272	1023	
EDGE BLENDING-WIDTH-LOWER	min.		VXX: EBWI 0=+00000	QVX: EBWI 0	EBWI 0=+00000	0	0	
	max.		VXX: EBWI 0=+02272		EBWI 0=+02272	2272	1199	
EDGE BLENDING-WIDTH-LEFT	min.		VXX: ELWI 0=+00000	QVX: ELWI 0	ELWI 0=+00000	0	0	
	max.		VXX: ELWI 0=+03712		ELWI 0=+03712	3712	1023	
EDGE BLENDING-WIDTH-RIGHT	min.		VXX: ERWI 0=+00000	QVX: ERWI 0	ERWI 0=+00000	0	0	
	max.		VXX: ERWI 0=+03712		ERWI 0=+03712	3712	1919	
EDGE BLENDING-MARKER-ON/OFF	OFF		VGM: 0	QGM	0	✓	✓	
	ON		VGM: 1		1	✓	✓	
EDGE BLENDING-NON-OVERLAPPED BLACK LEVEL	0 (W,R,G,B)		VJI: 000, 000, 000, 000	QJI	000, 000, 000, 000	✓	✓	
	255 (W,R,G,B)		VJI: 255, 255, 255, 255		255, 255, 255, 255	✓	✓	
EDGE BLENDING-NON-OVERLAPPED BLACK LEVEL-	OFF		VXX: EBI I 1=+00000	QVX: EBI I 1	EBI I 1=+00000	✓	✓	
	ON		VXX: EBI I 1=+00001		EBI I 1=+00001	✓	✓	
EDGE BLENDING-BLACK BORDER LEVEL	0 (W,R,G,B)		VJO: 000, 000, 000, 000	QJO	000, 000, 000, 000	✓	✓	
	255 (W,R,G,B)		VJO: 255, 255, 255, 255		255, 255, 255, 255	✓	✓	
EDGE BLENDING-BLACK BORDER LEVEL-INTERLOCKED	OFF		VXX: EBI I 2=+00000	QVX: EBI I 2	EBI I 2=+00000	✓	✓	
	ON		VXX: EBI I 2=+00001		EBI I 2=+00001	✓	✓	
EDGE BLENDING-BLACK BORDER WIDTH-UPPER	min.		VJU: 0000	QJU	0000	0	0	
	max.		VJU: 2272		2272	2272	1023	
EDGE BLENDING-BLACK BORDER WIDTH-LOWER	min.		VJB: 0000	QJB	0000	0	0	
	max.		VJB: 2272		2272	2272	1199	
EDGE BLENDING-BLACK BORDER WIDTH-LEFT	min.		VJL: 0000	QJL	0000	0	0	
	max.		VJL: 3712		3712	3712	1023	
EDGE BLENDING-BLACK BORDER WIDTH-RIGHT	min.		VJR: 0000	QJR	0000	0	0	
	max.		VJR: 3712		3712	3712	1919	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		RQ35K SERIES	RZ34K SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K SRQ35KC	RZ34K SRZ34KC	
ADVANCED	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA -	OFF		VXX: EBFI 1+=00000	QVX: EBFI 1	EBFI 1+=00000	✓	✓	
	ON			VXX: EBFI 1+=00001		EBFI 1+=00001	✓	✓	
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA -	OFF		VXX: EBFI 2+=00000	QVX: EBFI 2	EBFI 2+=00000	✓	✓	
	ON			VXX: EBFI 2+=00001		EBFI 2+=00001	✓	✓	
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA -	OFF		VXX: EBFI 3+=00000	QVX: EBFI 3	EBFI 3+=00000	✓	✓	
	ON			VXX: EBFI 3+=00001		EBFI 3+=00001	✓	✓	
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA -	OFF		VXX: EBFI 4+=00000	QVX: EBFI 4	EBFI 4+=00000	✓	✓	
	ON			VXX: EBFI 4+=00001		EBFI 4+=00001	✓	✓	
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA -	2		VXX: EFPI 1+=00002	QVX: EFPI 1	EFPI 1+=00002	✓	✓	
	3			VXX: EFPI 1+=00003		EFPI 1+=00003	✓	✓	
	5			VXX: EFPI 1+=00005		EFPI 1+=00005	✓	✓	
	9			VXX: EFPI 1+=00009		EFPI 1+=00009	✓	✓	
	17			VXX: EFPI 1+=00017		EFPI 1+=00017	✓	✓	
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA -	2		VXX: EFPI 2+=00002	QVX: EFPI 2	EFPI 2+=00002	✓	✓	
	3			VXX: EFPI 2+=00003		EFPI 2+=00003	✓	✓	
	5			VXX: EFPI 2+=00005		EFPI 2+=00005	✓	✓	
	9			VXX: EFPI 2+=00009		EFPI 2+=00009	✓	✓	
	17			VXX: EFPI 2+=00017		EFPI 2+=00017	✓	✓	
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA -	2		VXX: EFPI 3+=00002	QVX: EFPI 3	EFPI 3+=00002	✓	✓	
	3			VXX: EFPI 3+=00003		EFPI 3+=00003	✓	✓	
	5			VXX: EFPI 3+=00005		EFPI 3+=00005	✓	✓	
	9			VXX: EFPI 3+=00009		EFPI 3+=00009	✓	✓	
	17			VXX: EFPI 3+=00017		EFPI 3+=00017	✓	✓	
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA -	2		VXX: EFPI 4+=00002	QVX: EFPI 4	EFPI 4+=00002	✓	✓	
	3			VXX: EFPI 4+=00003		EFPI 4+=00003	✓	✓	
	5			VXX: EFPI 4+=00005		EFPI 4+=00005	✓	✓	
	9			VXX: EFPI 4+=00009		EFPI 4+=00009	✓	✓	
	17			VXX: EFPI 4+=00017		EFPI 4+=00017	✓	✓	
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA -	EXECUTE		VXX: EFI I 1+=00001			✓	✓	
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA -	EXECUTE		VXX: EFI I 2+=00001			✓	✓	
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA -	EXECUTE		VXX: EFI I 3+=00001			✓	✓	
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA -	EXECUTE		VXX: EFI I 4+=00001			✓	✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-UPPER	0 (W,R,G,B)		VXX: EBBS0=000, 000, 000, 000	QVX: EBBS0	EBBS0=000, 000, 000, 000	✓	✓	
	255 (W,R,G,B)			VXX: EBBS0=255, 255, 255, 255		EBBS0=255, 255, 255, 255	✓	✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LOWER	0 (W,R,G,B)		VXX: EBBS1=000, 000, 000, 000	QVX: EBBS1	EBBS1=000, 000, 000, 000	✓	✓	
	255 (W,R,G,B)			VXX: EBBS1=255, 255, 255, 255		EBBS1=255, 255, 255, 255	✓	✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LEFT	0 (W,R,G,B)		VXX: EBBS2=000, 000, 000, 000	QVX: EBBS2	EBBS2=000, 000, 000, 000	✓	✓	
	255 (W,R,G,B)			VXX: EBBS2=255, 255, 255, 255		EBBS2=255, 255, 255, 255	✓	✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-RIGHT	0 (W,R,G,B)		VXX: EBBS3=000, 000, 000, 000	QVX: EBBS3	EBBS3=000, 000, 000, 000	✓	✓	
	255 (W,R,G,B)			VXX: EBBS3=255, 255, 255, 255		EBBS3=255, 255, 255, 255	✓	✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-UPPER	OFF		VXX: EBI I 3+=00000	QVX: EBI I 3	EBI I 3+=00000	✓	✓	
	ON			VXX: EBI I 3+=00001		EBI I 3+=00001	✓	✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LOWER	OFF		VXX: EBI I 4+=00000	QVX: EBI I 4	EBI I 4+=00000	✓	✓	
	ON			VXX: EBI I 4+=00001		EBI I 4+=00001	✓	✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LEFT INTERLOCKED	OFF		VXX: EBI I 5+=00000	QVX: EBI I 5	EBI I 5+=00000	✓	✓	
ON			VXX: EBI I 5+=00001		EBI I 5+=00001	✓	✓		
EDGE BLENDING-OVERLAPPED BLACK LEVEL-RIGHT	OFF		VXX: EBI I 6+=00000	QVX: EBI I 6	EBI I 6+=00000	✓	✓		
ON			VXX: EBI I 6+=00001		EBI I 6+=00001	✓	✓		
EDGE BLENDING-MODE	SOFTEDGE/BLACK LEVEL		VXX: EBMI 1+=00000	QVX: EBMI 1	EBMI 1+=00000	✓	✓		
BLACK LEVEL ONLY			VXX: EBMI 1+=00001		EBMI 1+=00001	✓	✓		
EDGE BLENDING-AUTO TESTPATTERN	OFF		VXX: EATI 1+=00000	QVX: EATI 1	EATI 1+=00000	✓	✓		
ON			VXX: EATI 1+=00001		EATI 1+=00001	✓	✓		
FRAME RESPONSE	NORMAL		VXX: FDYI 0+=00000	QVX: FDYI 0	FDYI 0+=00000	✓	✓		
FAST			VXX: FDYI 0+=00001		FDYI 0+=00001	✓	✓		
FIXED			VXX: FDYI 0+=00005		FDYI 0+=00005	✓	✓		
FRAME DELAY	0.00		VXX: FDYS1+=0. 00	QVX: FDYS1	FDYS1+=0. 00	✓	✓		
100.00			VXX: FDYS1+=100. 00		FDYS1+=100. 00	✓	✓		
FILM DETECTION	OFF		VXX: FDTI 1+=00000	QVX: FDTI 1	FDTI 1+=00000	✓	✓		
ON			VXX: FDTI 1+=00001		FDTI 1+=00001	✓	✓		
QUAD PIXEL DRIVE	OFF		VXX: QPDI 1+=00000	QVX: QPDI 1	QPDI 1+=00000	✓	✓		
ON			VXX: QPDI 1+=00001		QPDI 1+=00001	✓	✓		
RASTER POSITION-HORIZONTAL	-2048		VRH: 2952	QRH	2952	✓	✓		
+2047			VRH: 7047		7047	✓	✓		
RASTER POSITION-VERTICAL	-2048		VRV: 2952	QRV	2952	✓	✓		
+2047			VRV: 7047		7047	✓	✓		
DISPLAY LANGUAGE	LANGUAGE	English		OLG: ENG	QLG	ENG	✓	✓	
	German			OLG: DEU		DEU	✓	✓	
	French			OLG: FRA		FRA	✓	✓	
	Spanish			OLG: ESP		ESP	✓	✓	
	Italian			OLG: I TL		I TL	✓	✓	
	Japanese			OLG: JPN		JPN	✓	✓	
	Chinese			OLG: CHI		CHI	✓	✓	
	Russian			OLG: RUS		RUS	✓	✓	
	Korea			OLG: KOR		KOR	✓	✓	
	Portuguse			OLG: POR		POR	✓	✓	
	3D SETTINGS	3D SYSTEM SETTING	SINGLE		VXX: DSYI 1+=00000	QVX: DSYI 1	DSYI 1+=00000	✓	✓
		DUAL(LEFT)			VXX: DSYI 1+=00001		DSYI 1+=00001	✓	✓
DUAL(RIGHT)				VXX: DSYI 1+=00002		DSYI 1+=00002	✓	✓	
3D SYNC SETTING		OFF		VXX: DSNI 1+=00000	QVX: DSNI 1	DSNI 1+=00000	✓	✓	
1				VXX: DSNI 1+=00001		DSNI 1+=00001	✓	✓	
2				VXX: DSNI 1+=00002		DSNI 1+=00002	✓	✓	
3				VXX: DSNI 1+=00003		DSNI 1+=00003	✓	✓	
4				VXX: DSNI 1+=00004		DSNI 1+=00004	✓	✓	
5				VXX: DSNI 1+=00005		DSNI 1+=00005	✓	✓	
6				VXX: DSNI 1+=00006		DSNI 1+=00006	✓	✓	
7				VXX: DSNI 1+=00007		DSNI 1+=00007	✓	✓	
8				VXX: DSNI 1+=00008		DSNI 1+=00008	✓	✓	
9				VXX: DSNI 1+=00009		DSNI 1+=00009	✓	✓	
10				VXX: DSNI 1+=00010		DSNI 1+=00010	✓	✓	
11				VXX: DSNI 1+=00011		DSNI 1+=00011	✓	✓	
3D SYNC SETTING-STEREO SYNC OUTPUT DELAY		0	10 step	VXX: DSNI 2+=00000	QVX: DSNI 2	DSNI 2+=00000	✓	✓	
25000				VXX: DSNI 2+=25000		DSNI 2+=25000	✓	✓	
3D INPUT FORMAT		AUTO		VXX: DI FI 1+=00000	QVX: DI FI 1	DI FI 1+=00000	✓	✓	
NATIVE(2D)				VXX: DI FI 1+=00001		DI FI 1+=00001	✓	✓	
SIDE BY SIDE				VXX: DI FI 1+=00003		DI FI 1+=00003	✓	✓	
TOP AND BOTTOM				VXX: DI FI 1+=00004		DI FI 1+=00004	✓	✓	
FRAME SEQUENTIAL				VXX: DI FI 1+=00006		DI FI 1+=00006	✓	✓	
3D LEFT/RIGHT SWAP		NORMAL		VXX: DSWI 1+=00000	QVX: DSWI 1	DSWI 1+=00000	✓	✓	
SWAPPED				VXX: DSWI 1+=00001		DSWI 1+=00001	✓	✓	
3D COLOR MATCHING	SHARED 2D/3D		VXX: DCMI 1+=00000	QVX: DCMI 1	DCMI 1+=00000	✓	✓		
SEPARATE 2D/3D			VXX: DCMI 1+=00001		DCMI 1+=00001	✓	✓		
3D DARK TIME SETTING	0.5		VXX: DDTS1+=0. 5	QVX: DDTS1	DDTS1+=0. 5	✓	✓		
1.0			VXX: DDTS1+=1. 0		DDTS1+=1. 0	✓	✓		
1.5			VXX: DDTS1+=1. 5		DDTS1+=1. 5	✓	✓		
2.0			VXX: DDTS1+=2. 0		DDTS1+=2. 0	✓	✓		
2.5			VXX: DDTS1+=2. 5		DDTS1+=2. 5	✓	✓		
2.7			VXX: DDTS1+=2. 7		DDTS1+=2. 7	✓	✓		
3D TEST MODE	NORMAL		VXX: DTSI 1+=00000	QVX: DTSI 1	DTSI 1+=00000	✓	✓		
SIDE BY SIDE			VXX: DTSI 1+=00001		DTSI 1+=00001	✓	✓		
LEFT/LEFT			VXX: DTSI 1+=00002		DTSI 1+=00002	✓	✓		
RIGHT/RIGHT			VXX: DTSI 1+=00003		DTSI 1+=00003	✓	✓		
LEFT/BLACK			VXX: DTSI 1+=00004		DTSI 1+=00004	✓	✓		
BLACK/RIGHT			VXX: DTSI 1+=00005		DTSI 1+=00005	✓	✓		
3D SAFETY PRECAUTIONS MESSAGE	OFF		VXX: DMGI 1+=00000	QVX: DMGI 1	DMGI 1+=00000	✓	✓		
ON			VXX: DMGI 1+=00001		DMGI 1+=00001	✓	✓		
COLOR MATCHING	COLOR MATCHING	OFF		VXX: CMAI 0+=00000	QVX: CMAI 0	CMAI 0+=00000	✓	✓	
	3COLORS			VXX: CMAI 0+=00001		CMAI 0+=00001	✓	✓	
	7COLORS			VXX: CMAI 0+=00002		CMAI 0+=00002	✓	✓	
	MEASURED			VXX: CMAI 0+=00004		CMAI 0+=00004	✓	✓	
	COLOR MATCHING-RESET MODE	NATIVE		VXX: CRMI 1+=00000	QVX: CRMI 1	CRMI 1+=00000	✓	✓	
PICTURE			VXX: CRMI 1+=00001		CRMI 1+=00001	✓	✓		

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		RQ35K SERIES	RZ34K SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K SRQ35KC	RZ34K SRZ34KC	
		REC709		VXX: CRMI 1=+00002		CRMI 1=+00002	✓	✓	
	COLOR MATCHING-3COLORS-RED	0 (R,G,B) 2048,2048,2048(R,G,B)		VMR: 0000, 0000, 0000 VMR: 2048, 2048, 2048	QMR	0000, 0000, 0000 2048, 2048, 2048	✓	✓	
	COLOR MATCHING-3COLORS-GREE	0 (R,G,B) 2048,2048,2048(R,G,B)		VMG: 0000, 0000, 0000 VMG: 2048, 2048, 2048	QMG	0000, 0000, 0000 2048, 2048, 2048	✓	✓	
	COLOR MATCHING-3COLORS-BLUE	0 (R,G,B) 2048,2048,2048(R,G,B)		VMB: 0000, 0000, 0000 VMB: 2048, 2048, 2048	QMB	0000, 0000, 0000 2048, 2048, 2048	✓	✓	
	COLOR MATCHING-3COLORS-AUTO TESTPATTERN	OFF ON		VXX: CATI 0=+00000 VXX: CATI 0=+00001	QVX: CATI 0	CATI 0=+00000 CATI 0=+00001	✓	✓	
	COLOR MATCHING-3COLORS-RESE	EXECUTE		VXX: CREI 1=+00001			✓	✓	
	COLOR MATCHING-7COLORS-RED	0 (R,G,B) 2048(R,G,B)		VXX: C7CS0=0000, 0000, 0000 VXX: C7CS0=2048, 2048, 2048	QVX: C7CS0	C7CS0=0000, 0000, 0000 C7CS0=2048, 2048, 2048	✓	✓	
	COLOR MATCHING-7COLORS-GREE	0 (R,G,B) 2048(R,G,B)		VXX: C7CS1=0000, 0000, 0000 VXX: C7CS1=2048, 2048, 2048	QVX: C7CS1	C7CS1=0000, 0000, 0000 C7CS1=2048, 2048, 2048	✓	✓	
	COLOR MATCHING-7COLORS-BLUE	0 (R,G,B) 2048(R,G,B)		VXX: C7CS2=0000, 0000, 0000 VXX: C7CS2=2048, 2048, 2048	QVX: C7CS2	C7CS2=0000, 0000, 0000 C7CS2=2048, 2048, 2048	✓	✓	
	COLOR MATCHING-7COLORS-CYAN	0 (R,G,B) 2048(R,G,B)		VXX: C7CS3=0000, 0000, 0000 VXX: C7CS3=2048, 2048, 2048	QVX: C7CS3	C7CS3=0000, 0000, 0000 C7CS3=2048, 2048, 2048	✓	✓	
	COLOR MATCHING-7COLORS-MAGE	0 (R,G,B) 2048(R,G,B)		VXX: C7CS4=0000, 0000, 0000 VXX: C7CS4=2048, 2048, 2048	QVX: C7CS4	C7CS4=0000, 0000, 0000 C7CS4=2048, 2048, 2048	✓	✓	
	COLOR MATCHING-7COLORS-YELL	0 (R,G,B) 2048(R,G,B)		VXX: C7CS5=0000, 0000, 0000 VXX: C7CS5=2048, 2048, 2048	QVX: C7CS5	C7CS5=0000, 0000, 0000 C7CS5=2048, 2048, 2048	✓	✓	
	COLOR MATCHING-7COLORS-WHIT	0 (R,G,B) 2048(R,G,B)		VXX: C7CS6=0000, 0000, 0000 VXX: C7CS6=2048, 2048, 2048	QVX: C7CS6	C7CS6=0000, 0000, 0000 C7CS6=2048, 2048, 2048	✓	✓	
	COLOR MATCHING-7COLORS-AUTO TESTPATTERN	OFF ON		VXX: CATI 1=+00000 VXX: CATI 1=+00001	QVX: CATI 1	CATI 1=+00000 CATI 1=+00001	✓	✓	
	COLOR MATCHING-7COLORS-RESE	EXECUTE		VXX: CREI 2=+00001			✓	✓	
	COLOR MATCHING-MEASURED MODE-MEASURED DATA BLACK	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS0=00000, 0001, 0001 VXX: CMMS0=65535, 0999, 0999	QVX: CMMS0	CMMS0=00000, 0001, 0001 CMMS0=65535, 0999, 0999	✓	✓	
	COLOR MATCHING-MEASURED MODE-MEASURED DATA RED	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS1=00000, 0001, 0001 VXX: CMMS1=65535, 0999, 0999	QVX: CMMS1	CMMS1=00000, 0001, 0001 CMMS1=65535, 0999, 0999	✓	✓	
	COLOR MATCHING-MEASURED MODE-MEASURED DATA GREEN	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS2=00000, 0001, 0001 VXX: CMMS2=65535, 0999, 0999	QVX: CMMS2	CMMS2=00000, 0001, 0001 CMMS2=65535, 0999, 0999	✓	✓	
	COLOR MATCHING-MEASURED MODE-MEASURED DATA BLUE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS3=00000, 0001, 0001 VXX: CMMS3=65535, 0999, 0999	QVX: CMMS3	CMMS3=00000, 0001, 0001 CMMS3=65535, 0999, 0999	✓	✓	
	COLOR MATCHING-MEASURED MODE-MEASURED DATA WHITE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS4=00000, 0001, 0001 VXX: CMMS4=65535, 0999, 0999	QVX: CMMS4	CMMS4=00000, 0001, 0001 CMMS4=65535, 0999, 0999	✓	✓	
	COLOR MATCHING-MEASURED MODE-TARGET DATA RED	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS0=00000, 0001, 0001 VXX: CMMS0=65535, 0999, 0999	QVX: CMMS0	CMMS0=00000, 0001, 0001 CMMS0=65535, 0999, 0999	✓	✓	
	COLOR MATCHING-MEASURED MODE-TARGET DATA GREEN	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS1=00000, 0001, 0001 VXX: CMMS1=65535, 0999, 0999	QVX: CMMS1	CMMS1=00000, 0001, 0001 CMMS1=65535, 0999, 0999	✓	✓	
	COLOR MATCHING-MEASURED MODE-TARGET DATA BLUE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS2=00000, 0001, 0001 VXX: CMMS2=65535, 0999, 0999	QVX: CMMS2	CMMS2=00000, 0001, 0001 CMMS2=65535, 0999, 0999	✓	✓	
	COLOR MATCHING-MEASURED MODE-TARGET DATA CYAN	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS3=00000, 0001, 0001 VXX: CMMS3=65535, 0999, 0999	QVX: CMMS3	CMMS3=00000, 0001, 0001 CMMS3=65535, 0999, 0999	✓	✓	
	COLOR MATCHING-MEASURED MODE-TARGET DATA MAGENTA	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS4=00000, 0001, 0001 VXX: CMMS4=65535, 0999, 0999	QVX: CMMS4	CMMS4=00000, 0001, 0001 CMMS4=65535, 0999, 0999	✓	✓	
	COLOR MATCHING-MEASURED MODE-TARGET DATA YELLOW	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS5=00000, 0001, 0001 VXX: CMMS5=65535, 0999, 0999	QVX: CMMS5	CMMS5=00000, 0001, 0001 CMMS5=65535, 0999, 0999	✓	✓	
	COLOR MATCHING-MEASURED MODE-TARGET DATA WHITE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS6=00000, 0001, 0001 VXX: CMMS6=65535, 0999, 0999	QVX: CMMS6	CMMS6=00000, 0001, 0001 CMMS6=65535, 0999, 0999	✓	✓	
	COLOR MATCHING-MEASURED MODE-AUTO TESTPATTERN	OFF ON		VXX: CATI 3=+00000 VXX: CATI 3=+00001	QVX: CATI 3	CATI 3=+00000 CATI 3=+00001	✓	✓	
	COLOR MATCHING-MEASURED MODE-RESET AUTO SIGNAL	EXECUTE OFF ON		VXX: CREI 3=+00001 VXX: AASI 0=+00000 VXX: AASI 0=+00001	QVX: AASI 0	AASI 0=+00000 AASI 0=+00001	✓	✓	
	AUTO SETUP -POSITION ADJ.	OFF ON		VXX: APAI 0=+00000 VXX: APAI 0=+00001	QVX: APAI 0	APAI 0=+00000 APAI 0=+00001	✓	✓	
	AUTO SETUP -SIGNAL LEVEL ADJ.	OFF ON		VXX: ASLI 0=+00000 VXX: ASLI 0=+00001	QVX: ASLI 0	ASLI 0=+00000 ASLI 0=+00001	✓	✓	
	BACKUP INPUT SETTING-BACKUP INPUT	PRIMARY SECONDARY TOGGLE		VXX: BACI 1=+00001 VXX: BACI 1=+00002 VXX: BACI 1=+00010	QVX: BACI 1	BACI 1=+00001 BACI 1=+00002 BACI 1=+00010	✓	✓	
	BACKUP INPUT SETTING-BACKUP INPUT MODE	OFF 2 3 4		VXX: BACI 2=+00000 VXX: BACI 2=+00002 VXX: BACI 2=+00003 VXX: BACI 2=+00004	QVX: BACI 2	BACI 2=+00000 BACI 2=+00002 BACI 2=+00003 BACI 2=+00004	✓	✓	
	BACKUP INPUT SETTING-BACKUP INPUT MODE (OPTION SLOT)	OFF HDMI1 (SLOT1) / HDMI2 (SLOT1) DVI1 (SLOT1) / DVI2 (SLOT1) SDI1 (SLOT1) / SDI3 (SLOT1) HDMI3 (SLOT2) / HDMI4 (SLOT2) DVI3 (SLOT2) / DVI4 (SLOT2) SDI1 (SLOT2) / SDI3 (SLOT2) DisplayPort1 (SLOT1) / DisplayPort3 (SLOT2) 12G SDI OPT1 (SLOT1) / 12G SDI OPT1 (SLOT2) HDMI1-2 (SLOT1) / HDMI3-4 (SLOT2) SDI1-3 (SLOT1) / SDI1-3 (SLOT2) SDI1-2-3-4 (SLOT1) / SDI1-2-3-4 (SLOT2)		VXX: BACI 6=+00000 VXX: BACI 6=+00012 VXX: BACI 6=+00013 VXX: BACI 6=+00014 VXX: BACI 6=+00022 VXX: BACI 6=+00023 VXX: BACI 6=+00024 VXX: BACI 6=+00055 VXX: BACI 6=+00056 VXX: BACI 6=+00102 VXX: BACI 6=+00104 VXX: BACI 6=+01003	QVX: BACI 6	BACI 6=+00000 BACI 6=+00012 BACI 6=+00013 BACI 6=+00014 BACI 6=+00022 BACI 6=+00023 BACI 6=+00024 BACI 6=+00055 BACI 6=+00056 BACI 6=+00102 BACI 6=+00104 BACI 6=+01003	✓	✓	
	BACKUP INPUT SETTING-AUTOMATIC SWITCHING	DISABLE ENABLE		VXX: BACI 3=+00001 VXX: BACI 3=+00002	QVX: BACI 3	BACI 3=+00001 BACI 3=+00002	✓	✓	
	BACKUP INPUT SETTING-BACKUP INPUT STATUS	INACTIVE ACTIVE			QVX: BACI 4	BACI 4=+00000 BACI 4=+00001	✓	✓	
	SIMUL INPUT SETTING - SLOT IN (SDI In/Slot In Correspondence)	OFF AUTO (3D)		VXX: SMLI 2=+00000 VXX: SMLI 2=+00002	QVX: SMLI 2	SMLI 2=+00000 SMLI 2=+00002	✓	✓	
	DVI-D IN-EDID	EDID1 EDID2(PC) EDID3		OED: 1 OED: 2 OED: 3	QED	1 2 3	✓	✓	
	DVI-D IN-SIGNAL LEVEL	0-255 PC 15-235 AUTO		VXX: DVII 0=+00000 VXX: DVII 0=+00001 VXX: DVII 0=+00002	QVX: DVII 0	DVII 0=+00000 DVII 0=+00001 DVII 0=+00002	✓	✓	
	DVI-D IN-EDID MODE	DEFAULT SCREEN FIT USER		VXX: EDM1 2=+00000 VXX: EDM1 2=+00001 VXX: EDM1 2=+00010	QVX: EDM1 0	EDM1 2=+00000 EDM1 2=+00001 EDM1 2=+00010	✓	✓	
	DVI-D IN-EDID RESOLUTION	1024x768p 1280x720p 1280x800p 1280x1024p 1366x768p 1400x1050p 1440x900p 1600x900p 1600x1200p 1680x1050p 1920x1080p 1920x1080i 1920x1200p		VXX: EDRS2=1024: 0768: p VXX: EDRS2=1280: 0720: p VXX: EDRS2=1280: 0800: p VXX: EDRS2=1280: 1024: p VXX: EDRS2=1366: 0768: p VXX: EDRS2=1400: 1050: p VXX: EDRS2=1440: 0900: p VXX: EDRS2=1600: 0900: p VXX: EDRS2=1600: 1200: p VXX: EDRS2=1680: 1050: p VXX: EDRS2=1920: 1080: p VXX: EDRS2=1920: 1080: i VXX: EDRS2=1920: 1200: p	QVX: EDRS2	EDRS2=1024: 0768: p EDRS2=1280: 0720: p EDRS2=1280: 0800: p EDRS2=1280: 1024: p EDRS2=1366: 0768: p EDRS2=1400: 1050: p EDRS2=1440: 0900: p EDRS2=1600: 0900: p EDRS2=1600: 1200: p EDRS2=1680: 1050: p EDRS2=1920: 1080: p EDRS2=1920: 1080: i EDRS2=1920: 1200: p	✓	✓	
	DVI-D IN-EDID VERTICAL SCAN FREQUENCY	60Hz 50Hz 48Hz 30Hz 25Hz 24Hz		VXX: EDVI 2=+06000 VXX: EDVI 2=+05000 VXX: EDVI 2=+04800 VXX: EDVI 2=+03000 VXX: EDVI 2=+02500 VXX: EDVI 2=+02400	QVX: EDVI 2	EDVI 2=+06000 EDVI 2=+05000 EDVI 2=+04800 EDVI 2=+03000 EDVI 2=+02500 EDVI 2=+02400	✓	✓	
	DVI-D IN-EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER 1024x768 1280x720 1280x800 1280x1024 1366x768 1400x1050		VXX: EDSD1=*****: *: **** VXX: EDSD1=1024: 0768: *: **** VXX: EDSD1=1280: 0720: *: **** VXX: EDSD1=1280: 0800: *: **** VXX: EDSD1=1280: 1024: *: **** VXX: EDSD1=1366: 0768: *: **** VXX: EDSD1=1400: 1050: *: ****	QVX: EDSD1	EDSD1=*****: *: **** EDSD1=1024: 0768: *: **** EDSD1=1280: 0720: *: **** EDSD1=1280: 0800: *: **** EDSD1=1280: 1024: *: **** EDSD1=1366: 0768: *: **** EDSD1=1400: 1050: *: ****	✓	✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY	RQ35K SERIES	RZ34K SERIES		
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K SRQ35KC	RZ34K SRZ34KC	
		* PARAMETER1	1440x900	VXX: EDDS1=1440: 0900: *: ****		EDDS1=1440: 0900: *: ****		✓	
			1600x900	VXX: EDDS1=1600: 0900: *: ****		EDDS1=1600: 0900: *: ****		✓	
			1600x1200	VXX: EDDS1=1600: 1200: *: ****		EDDS1=1600: 1200: *: ****		✓	
			1680x1050	VXX: EDDS1=1680: 1050: *: ****		EDDS1=1680: 1050: *: ****		✓	
			1920x1080	VXX: EDDS1=1920: 1080: *: ****		EDDS1=1920: 1080: *: ****		✓	
			1920x1200	VXX: EDDS1=1920: 1200: *: ****		EDDS1=1920: 1200: *: ****		✓	
		* PARAMETER2	Progressive Interlace	VXX: EDDS1=*****: p: **** VXX: EDDS1=*****: i: ****		EDDS1=*****: p: **** EDDS1=*****: i: ****		✓	✓
			* PARAMETER3	60Hz	VXX: EDDS1=*****: *: 6000		EDDS1=*****: *: 6000		✓
		50Hz		VXX: EDDS1=*****: *: 5000		EDDS1=*****: *: 5000		✓	
		48Hz		VXX: EDDS1=*****: *: 4800		EDDS1=*****: *: 4800		✓	
		30Hz		VXX: EDDS1=*****: *: 3000		EDDS1=*****: *: 3000		✓	
		* PARAMETER3	25Hz	VXX: EDDS1=*****: *: 2500		EDDS1=*****: *: 2500		✓	
	24Hz		VXX: EDDS1=*****: *: 2400		EDDS1=*****: *: 2400		✓		
	DVI-D IN-EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER			QVX: ESDS1	ESDS1=*****: *: ****		✓	
			1024x768			ESDS1=1024: 0768: *: ****		✓	
			1280x720			ESDS1=1280: 0720: *: ****		✓	
			1280x800			ESDS1=1280: 0800: *: ****		✓	
			1280x1024			ESDS1=1280: 1024: *: ****		✓	
			1366x768			ESDS1=1366: 0768: *: ****		✓	
			1400x1050			ESDS1=1400: 1050: *: ****		✓	
			1440x900			ESDS1=1440: 0900: *: ****		✓	
			1600x900			ESDS1=1600: 0900: *: ****		✓	
			1600x1200			ESDS1=1600: 1200: *: ****		✓	
			1680x1050			ESDS1=1680: 1050: *: ****		✓	
1920x1080					ESDS1=1920: 1080: *: ****		✓		
1920x1200			ESDS1=1920: 1200: *: ****		✓				
* PARAMETER2	Progressive Interlace				ESDS1=*****: p: **** ESDS1=*****: i: ****		✓		
	* PARAMETER3	60Hz			ESDS1=*****: *: 6000		✓		
		50Hz			ESDS1=*****: *: 5000		✓		
		48Hz			ESDS1=*****: *: 4800		✓		
30Hz				ESDS1=*****: *: 3000		✓			
* PARAMETER3	25Hz				ESDS1=*****: *: 2500		✓		
	24Hz				ESDS1=*****: *: 2400		✓		
HDMI IN-SIGNAL LEVEL	0-1023		VXX: HSLI 0=+00000	QVX: HSLI 0	HSLI 0=+00000	✓	✓		
	64-940		VXX: HSLI 0=+00001		HSLI 0=+00001	✓	✓		
	AUTO		VXX: HSLI 0=+00002		HSLI 0=+00002	✓	✓		
HDMI IN-EDID MODE	DEFAULT		VXX: EDM 3=+00000	QVX: EDM 3	EDM 3=+00000	✓	✓		
	SCREEN FIT		VXX: EDM 3=+00001		EDM 3=+00001	✓	✓		
	USER		VXX: EDM 3=+00010		EDM 3=+00010	✓	✓		
HDMI IN-EDID RESOLUTION	* PARAMETER	1024x768p	VXX: EDRS3=1024: 0768: p	QVX: EDRS3	EDRS3=1024: 0768: p	✓	✓		
		1280x720p	VXX: EDRS3=1280: 0720: p		EDRS3=1280: 0720: p	✓	✓		
		1280x800p	VXX: EDRS3=1280: 0800: p		EDRS3=1280: 0800: p	✓	✓		
		1280x1024p	VXX: EDRS3=1280: 1024: p		EDRS3=1280: 1024: p	✓	✓		
		1366x768p	VXX: EDRS3=1366: 0768: p		EDRS3=1366: 0768: p	✓	✓		
		1400x1050p	VXX: EDRS3=1400: 1050: p		EDRS3=1400: 1050: p	✓	✓		
		1440x900p	VXX: EDRS3=1440: 0900: p		EDRS3=1440: 0900: p	✓	✓		
		1600x900p	VXX: EDRS3=1600: 0900: p		EDRS3=1600: 0900: p	✓	✓		
		1600x1200p	VXX: EDRS3=1600: 1200: p		EDRS3=1600: 1200: p	✓	✓		
		1680x1050p	VXX: EDRS3=1680: 1050: p		EDRS3=1680: 1050: p	✓	✓		
		1920x1080p	VXX: EDRS3=1920: 1080: p		EDRS3=1920: 1080: p	✓	✓		
		1920x1080i	VXX: EDRS3=1920: 1080: i		EDRS3=1920: 1080: i	✓	✓		
		1920x1200p	VXX: EDRS3=1920: 1200: p		EDRS3=1920: 1200: p	✓	✓		
		2048x1080p	VXX: EDRS3=2048: 1080: p		EDRS3=2048: 1080: p	✓	✓		
		2560x1600p	VXX: EDRS3=2560: 1600: p		EDRS3=2560: 1600: p	✓	✓		
		3840x2400p	VXX: EDRS3=3840: 2400: p		EDRS3=3840: 2400: p	✓	✓		
HDMI IN-EDID VERTICAL SCAN FREQUENCY	* PARAMETER	60Hz	VXX: EDVI 3=+06000	QVX: EDVI 3	EDVI 3=+06000	✓	✓		
		50Hz	VXX: EDVI 3=+05000		EDVI 3=+05000	✓	✓		
		48Hz	VXX: EDVI 3=+04800		EDVI 3=+04800	✓	✓		
		30Hz	VXX: EDVI 3=+03000		EDVI 3=+03000	✓	✓		
		25Hz	VXX: EDVI 3=+02500		EDVI 3=+02500	✓	✓		
		24Hz	VXX: EDVI 3=+02400		EDVI 3=+02400	✓	✓		
HDMI IN-HDMI1 EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER		VXX: EDHS1=*****: *: ****	QVX: EHDS1	EDHS1=*****: *: ****	✓	✓		
		1024x768	VXX: EDHS1=1024: 0768: *: ****		EDHS1=1024: 0768: *: ****	✓	✓		
		1280x720	VXX: EDHS1=1280: 0720: *: ****		EDHS1=1280: 0720: *: ****	✓	✓		
		1280x800	VXX: EDHS1=1280: 0800: *: ****		EDHS1=1280: 0800: *: ****	✓	✓		
		1280x1024	VXX: EDHS1=1280: 1024: *: ****		EDHS1=1280: 1024: *: ****	✓	✓		
		1366x768	VXX: EDHS1=1366: 0768: *: ****		EDHS1=1366: 0768: *: ****	✓	✓		
		1400x1050	VXX: EDHS1=1400: 1050: *: ****		EDHS1=1400: 1050: *: ****	✓	✓		
		1440x900	VXX: EDHS1=1440: 0900: *: ****		EDHS1=1440: 0900: *: ****	✓	✓		
		1600x900	VXX: EDHS1=1600: 0900: *: ****		EDHS1=1600: 0900: *: ****	✓	✓		
		1600x1200	VXX: EDHS1=1600: 1200: *: ****		EDHS1=1600: 1200: *: ****	✓	✓		
		1680x1050	VXX: EDHS1=1680: 1050: *: ****		EDHS1=1680: 1050: *: ****	✓	✓		
		1920x1080	VXX: EDHS1=1920: 1080: *: ****		EDHS1=1920: 1080: *: ****	✓	✓		
	1920x1200	VXX: EDHS1=1920: 1200: *: ****		EDHS1=1920: 1200: *: ****	✓	✓			
	2048x1080	VXX: EDHS1=2048: 1080: *: ****		EDHS1=2048: 1080: *: ****	✓	✓			
	2560x1600	VXX: EDHS1=2560: 1600: *: ****		EDHS1=2560: 1600: *: ****	✓	✓			
	3840x2400	VXX: EDHS1=3840: 2400: *: ****		EDHS1=3840: 2400: *: ****	✓	✓			
	* PARAMETER2	Progressive Interlace	VXX: EDHS1=*****: p: **** VXX: EDHS1=*****: i: ****			EDHS1=*****: p: **** EDHS1=*****: i: ****	✓	✓	
		* PARAMETER3	60Hz	VXX: EDHS1=*****: *: 6000		EDHS1=*****: *: 6000	✓	✓	
			50Hz	VXX: EDHS1=*****: *: 5000		EDHS1=*****: *: 5000	✓	✓	
			48Hz	VXX: EDHS1=*****: *: 4800		EDHS1=*****: *: 4800	✓	✓	
	30Hz		VXX: EDHS1=*****: *: 3000		EDHS1=*****: *: 3000	✓	✓		
	* PARAMETER3	25Hz	VXX: EDHS1=*****: *: 2500		EDHS1=*****: *: 2500	✓	✓		
		24Hz	VXX: EDHS1=*****: *: 2400		EDHS1=*****: *: 2400	✓	✓		
	HDMI IN-HDMI 1 EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER			QVX: ESHS1	ESHS1=*****: *: ****	✓	✓	
1024x768					ESHS1=1024: 0768: *: ****	✓	✓		
1280x720					ESHS1=1280: 0720: *: ****	✓	✓		
1280x800					ESHS1=1280: 0800: *: ****	✓	✓		
1280x1024					ESHS1=1280: 1024: *: ****	✓	✓		
1366x768					ESHS1=1366: 0768: *: ****	✓	✓		
1400x1050					ESHS1=1400: 1050: *: ****	✓	✓		
1440x900					ESHS1=1440: 0900: *: ****	✓	✓		
1600x900					ESHS1=1600: 0900: *: ****	✓	✓		
1600x1200					ESHS1=1600: 1200: *: ****	✓	✓		
1680x1050					ESHS1=1680: 1050: *: ****	✓	✓		
1920x1080					ESHS1=1920: 1080: *: ****	✓	✓		
1920x1200			ESHS1=1920: 1200: *: ****	✓	✓				
2048x1080			ESHS1=2048: 1080: *: ****	✓	✓				
2560x1600			ESHS1=2560: 1600: *: ****	✓	✓				
3840x2400			ESHS1=3840: 2400: *: ****	✓	✓				
* PARAMETER2	Progressive Interlace				ESHS1=*****: p: **** ESHS1=*****: i: ****	✓	✓		
	* PARAMETER3	60Hz			ESHS1=*****: *: 6000	✓	✓		
		50Hz			ESHS1=*****: *: 5000	✓	✓		
		48Hz			ESHS1=*****: *: 4800	✓	✓		
30Hz				ESHS1=*****: *: 3000	✓	✓			
* PARAMETER3	25Hz				ESHS1=*****: *: 2500	✓	✓		
	24Hz				ESHS1=*****: *: 2400	✓	✓		
HDMI IN-HDMI1 EDID SELECT	4K/60p		VXX: HESI 1=+00000	QVX: HESI 1	HESI 1=+00000	✓	✓		
	4K/30p		VXX: HESI 1=+00001		HESI 1=+00001	✓	✓		
	2K		VXX: HESI 1=+00002		HESI 1=+00002	✓	✓		
	4K/60p/HDR		VXX: HESI 1=+00010		HESI 1=+00010	✓	✓		
DIGITAL LINK-SIGNAL LEVEL	AUTO		VXX: DKLI 1=+00000	QVX: DKLI 1	DKLI 1=+00000	✓	✓		
	0-1023		VXX: DKLI 1=+00001		DKLI 1=+00001	✓	✓		
	64-940		VXX: DKLI 1=+00002		DKLI 1=+00002	✓	✓		
DIGITAL LINK-AUTO GAMMA SELECT	DISABLE		VXX: LAGI 1=+00000	QVX: LAGI 1	LAGI 1=+00000	✓	✓		
	ENABLE		VXX: LAGI 1=+00001		LAGI 1=+00001	✓	✓		
DIGITAL LINK- AUTO COLOR	DISABLE		VXX: LACI 1=+00000	QVX: LACI 1	LACI 1=+00000	✓	✓		

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ35K SERIES	RZ34K SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K SRQ35KC	RZ34K SRZ34KC
DIGITAL LINK-EDID SELECT (SINGLE LINK)	SPACE SELECT	ENABLE		VXX: LACI 1=+00001		LACI 2=+00001	✓	✓
	DIGITAL LINK-EDID SELECT (SINGLE LINK)	EDID1:4K/60p		VXX: LESI 1=+00000	QVX: LESI 1	LESI 1=+00000	✓	✓
		EDID2:4K/30p		VXX: LESI 1=+00001		LESI 1=+00001	✓	✓
		EDID3:2K		VXX: LESI 1=+00002		LESI 1=+00002	✓	✓
		EDID4:4K/30p/HDR		VXX: LESI 1=+00011		LESI 1=+00011	✓	✓
	DIGITAL LINK-EDID MODE	DEFAULT		VXX: EDM 4=+00000	QVX: EDM 4	EDM 4=+00000	✓	✓
		SCREEN FIT		VXX: EDM 4=+00001		EDM 4=+00001	✓	✓
		USER		VXX: EDM 4=+00010		EDM 4=+00010	✓	✓
	DIGITAL LINK-EDID RESOLUTION	1024x768p		VXX: EDRS4=1024: 0768: p	QVX: EDRS4	EDRS4=1024: 0768: p	✓	✓
		1280x720p		VXX: EDRS4=1280: 0720: p		EDRS4=1280: 0720: p	✓	✓
		1280x800p		VXX: EDRS4=1280: 0800: p		EDRS4=1280: 0800: p	✓	✓
		1280x1024p		VXX: EDRS4=1280: 1024: p		EDRS4=1280: 1024: p	✓	✓
		1366x768p		VXX: EDRS4=1366: 0768: p		EDRS4=1366: 0768: p	✓	✓
		1400x1050p		VXX: EDRS4=1400: 1050: p		EDRS4=1400: 1050: p	✓	✓
		1440x900p		VXX: EDRS4=1440: 0900: p		EDRS4=1440: 0900: p	✓	✓
		1600x900p		VXX: EDRS4=1600: 0900: p		EDRS4=1600: 0900: p	✓	✓
		1600x1200p		VXX: EDRS4=1600: 1200: p		EDRS4=1600: 1200: p	✓	✓
		1680x1050p		VXX: EDRS4=1680: 1050: p		EDRS4=1680: 1050: p	✓	✓
		1920x1080p		VXX: EDRS4=1920: 1080: p		EDRS4=1920: 1080: p	✓	✓
		1920x1080i		VXX: EDRS4=1920: 1080: i		EDRS4=1920: 1080: i	✓	✓
		1920x1200p		VXX: EDRS4=1920: 1200: p		EDRS4=1920: 1200: p	✓	✓
		2048x1080p		VXX: EDRS4=2048: 1080: p		EDRS4=2048: 1080: p	✓	✓
		2560x1600p		VXX: EDRS4=2560: 1600: p		EDRS4=2560: 1600: p	✓	✓
		3840x2400p		VXX: EDRS4=3840: 2400: p		EDRS4=3840: 2400: p	✓	✓
DIGITAL LINK-EDID VERTICAL SCAN FREQUENCY	60Hz		VXX: EDVI 4=+06000	QVX: EDVI 4	EDVI 4=+06000	✓	✓	
	50Hz		VXX: EDVI 4=+05000		EDVI 4=+05000	✓	✓	
	48Hz		VXX: EDVI 4=+04800		EDVI 4=+04800	✓	✓	
	30Hz		VXX: EDVI 4=+03000		EDVI 4=+03000	✓	✓	
	25Hz		VXX: EDVI 4=+02500		EDVI 4=+02500	✓	✓	
24Hz		VXX: EDVI 4=+02400		EDVI 4=+02400	✓	✓		
DIGITAL LINK-EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER		VXX: EDLS1=*****: *: ****	QVX: EDLS1	EDLS1=*****: *: ****	✓	✓	
	* PARAMETER1	1024x768		VXX: EDLS1=1024: 0768: *: ****		EDLS1=1024: 0768: *: ****	✓	✓
		1280x720		VXX: EDLS1=1280: 0720: *: ****		EDLS1=1280: 0720: *: ****	✓	✓
		1280x800		VXX: EDLS1=1280: 0800: *: ****		EDLS1=1280: 0800: *: ****	✓	✓
		1280x1024		VXX: EDLS1=1280: 1024: *: ****		EDLS1=1280: 1024: *: ****	✓	✓
		1366x768		VXX: EDLS1=1366: 0768: *: ****		EDLS1=1366: 0768: *: ****	✓	✓
		1400x1050		VXX: EDLS1=1400: 1050: *: ****		EDLS1=1400: 1050: *: ****	✓	✓
		1440x900		VXX: EDLS1=1440: 0900: *: ****		EDLS1=1440: 0900: *: ****	✓	✓
		1600x900		VXX: EDLS1=1600: 0900: *: ****		EDLS1=1600: 0900: *: ****	✓	✓
		1600x1200		VXX: EDLS1=1600: 1200: *: ****		EDLS1=1600: 1200: *: ****	✓	✓
		1680x1050		VXX: EDLS1=1680: 1050: *: ****		EDLS1=1680: 1050: *: ****	✓	✓
		1920x1080		VXX: EDLS1=1920: 1080: *: ****		EDLS1=1920: 1080: *: ****	✓	✓
		1920x1200		VXX: EDLS1=1920: 1200: *: ****		EDLS1=1920: 1200: *: ****	✓	✓
	2048x1080		VXX: EDLS1=2048: 1080: *: ****		EDLS1=2048: 1080: *: ****	✓	✓	
	2560x1600		VXX: EDLS1=2560: 1600: *: ****		EDLS1=2560: 1600: *: ****	✓	✓	
	3840x2400		VXX: EDLS1=3840: 2400: *: ****		EDLS1=3840: 2400: *: ****	✓	✓	
	* PARAMETER2	Progressive Interface		VXX: EDLS1=*****: p: ****		EDLS1=*****: p: ****	✓	✓
				VXX: EDLS1=*****: i: ****		EDLS1=*****: i: ****	✓	✓
	* PARAMETER3	60Hz		VXX: EDLS1=*****: *: 6000		EDLS1=*****: *: 6000	✓	✓
		50Hz		VXX: EDLS1=*****: *: 5000		EDLS1=*****: *: 5000	✓	✓
48Hz			VXX: EDLS1=*****: *: 4800		EDLS1=*****: *: 4800	✓	✓	
30Hz			VXX: EDLS1=*****: *: 3000		EDLS1=*****: *: 3000	✓	✓	
25Hz			VXX: EDLS1=*****: *: 2500		EDLS1=*****: *: 2500	✓	✓	
24Hz		VXX: EDLS1=*****: *: 2400		EDLS1=*****: *: 2400	✓	✓		
DIGITAL LINK-EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER			QVX: ESLS1	ESLS1=*****: *: ****	✓	✓	
	* PARAMETER1	1024x768				ESLS1=1024: 0768: *: ****	✓	✓
		1280x720				ESLS1=1280: 0720: *: ****	✓	✓
		1280x800				ESLS1=1280: 0800: *: ****	✓	✓
		1280x1024				ESLS1=1280: 1024: *: ****	✓	✓
		1366x768				ESLS1=1366: 0768: *: ****	✓	✓
		1400x1050				ESLS1=1400: 1050: *: ****	✓	✓
		1440x900				ESLS1=1440: 0900: *: ****	✓	✓
		1600x900				ESLS1=1600: 0900: *: ****	✓	✓
		1600x1200				ESLS1=1600: 1200: *: ****	✓	✓
		1680x1050				ESLS1=1680: 1050: *: ****	✓	✓
		1920x1080				ESLS1=1920: 1080: *: ****	✓	✓
		1920x1200				ESLS1=1920: 1200: *: ****	✓	✓
	2048x1080				ESLS1=2048: 1080: *: ****	✓	✓	
	2560x1600				ESLS1=2560: 1600: *: ****	✓	✓	
	3840x2400				ESLS1=3840: 2400: *: ****	✓	✓	
	* PARAMETER2	Progressive Interface				ESLS1=*****: p: ****	✓	✓
						ESLS1=*****: i: ****	✓	✓
	* PARAMETER3	60Hz				ESLS1=*****: *: 6000	✓	✓
		50Hz				ESLS1=*****: *: 5000	✓	✓
48Hz					ESLS1=*****: *: 4800	✓	✓	
30Hz					ESLS1=*****: *: 3000	✓	✓	
25Hz					ESLS1=*****: *: 2500	✓	✓	
24Hz					ESLS1=*****: *: 2400	✓	✓	
SDI IN-SIGNAL LEVEL (SDI1)	64-940		VXX: SSLI 1=+00000	QVX: SSLI 1	SSLI 1=+00000	✓	✓	
	4-1019		VXX: SSLI 1=+00001		SSLI 1=+00001	✓	✓	
SDI IN-BIT DEPTH (SDI1)	AUTO		VXX: SBTI 1=+00000	QVX: SBTI 1	SBTI 1=+00000	✓	✓	
	12-bit		VXX: SBTI 1=+00001		SBTI 1=+00001	✓	✓	
10-bit		VXX: SBTI 1=+00002		SBTI 1=+00002	✓	✓		
SDI IN-3G SDI MAPPING (SDI1)	AUTO		VXX: SGM 1=+00000	QVX: SGM 1	SGM 1=+00000	✓	✓	
	LEVEL A		VXX: SGM 1=+00001		SGM 1=+00001	✓	✓	
	LEVEL B		VXX: SGM 1=+00002		SGM 1=+00002	✓	✓	
SDI RESOLUTION	* PARAMETER		VXX: *****+*****	QVX: *****	*****+*****	✓	✓	
	* PARAMETER1	SDI1	VXX: SRSI 1=+*****		SRSI 1=+*****	✓	✓	
	* PARAMETER2	AUTO		VXX: *****+00000		*****+00000	✓	✓
		1280x720p		VXX: *****+00003		*****+00003	✓	✓
		1920x1080i		VXX: *****+00005		*****+00005	✓	✓
		1920x1080p		VXX: *****+00006		*****+00006	✓	✓
		1920x1080sF		VXX: *****+00007		*****+00007	✓	✓
2048x1080p		VXX: *****+00009		*****+00009	✓	✓		
SDI SYSTEM SELECTOR	* PARAMETER		VXX: SYSS1=*, ****: *****	QVX: SYSS1=*, ****	SYSS1=*, ****: *****	✓	✓	
	* PARAMETER1, 2	SDI1	VXX: SYSS1=1: 1		SYSS1=1: 1: *****	✓	✓	
	* PARAMETER3	AUTO		VXX: SYSS1=*, ****: 00000		SYSS1=*, ****: 00000	✓	✓
		RGB		VXX: SYSS1=*, ****: 00001		SYSS1=*, ****: 00001	✓	✓
YPbPr4:4:4			VXX: SYSS1=*, ****: 00002		SYSS1=*, ****: 00002	✓	✓	
YPbPr4:2:2		VXX: SYSS1=*, ****: 00003		SYSS1=*, ****: 00003	✓	✓		
SDI IN - SDI MODE(ET-MDN12G10)	* PARAMETER		VXX: *****=VXX: *****+*****	QVX: *****=QVX: *****	*****=*****+*****	✓	✓	
	* PARAMETER1, 2	SLOT1	VXX: SLSS1=VXX: SMOI 1=+*****		SLSS1=SMOI 1=+*****	✓	✓	
	SLOT2		VXX: SLSS2=VXX: SMOI 1=+*****		SLSS2=SMOI 1=+*****	✓	✓	
	* PARAMETER3	INPUT	VXX: *****=VXX: *****+00000		*****=*****+00000	✓	✓	
OUTPUT		VXX: *****=VXX: *****+00001		*****=*****+00001	✓	✓		
SLOT - SDI IN - SDI LINK(ET-MDN12G10)	* PARAMETER		VXX: *****=VXX: *****+00000		*****=*****+00000	✓	✓	
	* PARAMETER1, 2	SLOT1	VXX: SLSS1=VXX: SLKI 3=+*****		SLSS1=SLKI 3=+*****	✓	✓	
	SLOT2		VXX: SLSS2=VXX: SLKI 3=+*****		SLSS2=SLKI 3=+*****	✓	✓	
	* PARAMETER3	SNGLE LINK	VXX: *****=VXX: *****+00000		*****=*****+00000	✓	✓	
	DUAL LINK		VXX: *****=VXX: *****+00001		*****=*****+00001	✓	✓	
QUAD LINK		VXX: *****=VXX: *****+00002		*****=*****+00002	✓	✓		
AUTO		VXX: *****=VXX: *****+00010		*****=*****+00010	✓	✓		
SLOT - HDMI IN - HDMI LINK	SINGLE LINK		VXX: HLKI 1=+00000	QVX: HLKI 1	HLKI 1=+00000	✓	✓	
	QUAD LINK		VXX: HLKI 1=+00002		HLKI 1=+00002	✓	✓	
	AUTO		VXX: HLKI 1=+00010		HLKI 1=+00010	✓	✓	
	DUAL / DUAL		VXX: HLKI 1=+00100		HLKI 1=+00100	✓	✓	
	DUAL / SINGLE		VXX: HLKI 1=+00101		HLKI 1=+00101	✓	✓	
	SINGLE / DUAL		VXX: HLKI 1=+00102		HLKI 1=+00102	✓	✓	
SLOT - DVI IN - DVI LINK	SINGLE LINK		VXX: DLKI 1=+00000	QVX: DLKI 1	DLKI 1=+00000	✓	✓	
	QUAD LINK		VXX: DLKI 1=+00002		DLKI 1=+00002	✓	✓	
	AUTO		VXX: DLKI 1=+00010		DLKI 1=+00010	✓	✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ35K SERIES	RZ34K SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K SRQ35KC	RZ34K SRZ34KC
SLOT : SDI RESOLUTION	* PARAMETER	SLOT1:SDI1 SLOT1:SDI2 SLOT1:SDI3 SLOT1:SDI4 SLOT2:SDI1 SLOT2:SDI2 SLOT2:SDI3 SLOT2:SDI4 DUAL LINK(SLOT1:SDI1+3) DUAL LINK(SLOT2:SDI1+3) QUAD LINK(SLOT1:SDI1+2+3+4) QUAD LINK(SLOT2:SDI1+2+3+4)	VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓	
			VXX: SLSS1=VXX: SRSI 1=+*****	SLSS1=SRSI 1=+*****	✓	✓		
			VXX: SLSS1=VXX: SRSI 2=+*****	SLSS1=SRSI 2=+*****	✓	✓		
			VXX: SLSS1=VXX: SRSI 3=+*****	SLSS1=SRSI 3=+*****	✓	✓		
			VXX: SLSS1=VXX: SRSI 4=+*****	SLSS1=SRSI 4=+*****	✓	✓		
			VXX: SLSS2=VXX: SRSI 1=+*****	SLSS2=SRSI 1=+*****	✓	✓		
			VXX: SLSS2=VXX: SRSI 2=+*****	SLSS2=SRSI 2=+*****	✓	✓		
			VXX: SLSS2=VXX: SRSI 3=+*****	SLSS2=SRSI 3=+*****	✓	✓		
			VXX: SLSS2=VXX: SRSI 4=+*****	SLSS2=SRSI 4=+*****	✓	✓		
			VXX: SLSS1=VXX: SRDI 1=+*****	SLSS1=SRDI 1=+*****	✓	✓		
	VXX: SLSS2=VXX: SRDI 1=+*****	SLSS2=SRDI 1=+*****	✓	✓				
	VXX: SLSS1=VXX: SRQI 1=+*****	SLSS1=SRQI 1=+*****	✓	✓				
	VXX: SLSS2=VXX: SRQI 1=+*****	SLSS2=SRQI 1=+*****	✓	✓				
	* PARAMETER3	AUTO	VXX: *****=VXX: *****=+00000	*****=*****=+00000	✓	✓		
		1280x720p	VXX: *****=VXX: *****=+00003	*****=*****=+00003	✓	✓		
		1920x1080i	VXX: *****=VXX: *****=+00005	*****=*****=+00005	✓	✓		
		1920x1080p	VXX: *****=VXX: *****=+00006	*****=*****=+00006	✓	✓		
		1920x1080sF	VXX: *****=VXX: *****=+00007	*****=*****=+00007	✓	✓		
		2048x1080p	VXX: *****=VXX: *****=+00009	*****=*****=+00009	✓	✓		
		3840x2160p	VXX: *****=VXX: *****=+00011	*****=*****=+00011	✓	✓		
4096x2160p		VXX: *****=VXX: *****=+00013	*****=*****=+00013	✓	✓			
SLOT : SDI : SDI 4K DIVISION		* PARAMETER	VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓	
* PARAMETER1, 2 (ET-MDN12G10)		SINGLE LINK(SLOT1:SDI1)	VXX: SLSS1=VXX: SKSI 1=+*****	SLSS1=SKSI 1=+*****	✓	✓		
	SINGLE LINK(SLOT1:SDI3)	VXX: SLSS1=VXX: SKSI 3=+*****	SLSS1=SKSI 3=+*****	✓	✓			
	SINGLE LINK(SLOT2:SDI1)	VXX: SLSS2=VXX: SKSI 1=+*****	SLSS2=SKSI 1=+*****	✓	✓			
	SINGLE LINK(SLOT2:SDI3)	VXX: SLSS2=VXX: SKSI 3=+*****	SLSS2=SKSI 3=+*****	✓	✓			
	DUAL LINK(SLOT1:SDI1+3)	VXX: SLSS1=VXX: SKDI 1=+*****	SLSS1=SKDI 1=+*****	✓	✓			
	DUAL LINK(SLOT2:SDI1+3)	VXX: SLSS2=VXX: SKDI 1=+*****	SLSS2=SKDI 1=+*****	✓	✓			
	QUAD LINK(SLOT1:SDI1+2+3+4)	VXX: SLSS1=VXX: SKQI 1=+*****	SLSS1=SKQI 1=+*****	✓	✓			
	QUAD LINK(SLOT2:SDI1+2+3+4)	VXX: SLSS2=VXX: SKQI 1=+*****	SLSS2=SKQI 1=+*****	✓	✓			
	AUTO	VXX: *****=VXX: *****=+00000	*****=*****=+00000	✓	✓			
	SQUARE	VXX: *****=VXX: *****=+00001	*****=*****=+00001	✓	✓			
INTERLEAVE	VXX: *****=VXX: *****=+00002	*****=*****=+00002	✓	✓				
SLOT : SDI : SDI 3G-SDI MAPPING		* PARAMETER	VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓	
* PARAMETER1, 2 (ET-MDN12G10)	SINGLE LINK(SLOT1:SDI1)	VXX: SLSS1=VXX: SGMI 1=+*****	SLSS1=SGMI 1=+*****	✓	✓			
	SINGLE LINK(SLOT1:SDI2)	VXX: SLSS1=VXX: SGMI 2=+*****	SLSS1=SGMI 2=+*****	✓	✓			
	SINGLE LINK(SLOT1:SDI3)	VXX: SLSS1=VXX: SGMI 3=+*****	SLSS1=SGMI 3=+*****	✓	✓			
	SINGLE LINK(SLOT1:SDI4)	VXX: SLSS1=VXX: SGMI 4=+*****	SLSS1=SGMI 4=+*****	✓	✓			
	SINGLE LINK(SLOT2:SDI1)	VXX: SLSS2=VXX: SGMI 1=+*****	SLSS2=SGMI 1=+*****	✓	✓			
	SINGLE LINK(SLOT2:SDI2)	VXX: SLSS2=VXX: SGMI 2=+*****	SLSS2=SGMI 2=+*****	✓	✓			
	SINGLE LINK(SLOT2:SDI3)	VXX: SLSS2=VXX: SGMI 3=+*****	SLSS2=SGMI 3=+*****	✓	✓			
	SINGLE LINK(SLOT2:SDI4)	VXX: SLSS2=VXX: SGMI 4=+*****	SLSS2=SGMI 4=+*****	✓	✓			
	DUAL LINK(SLOT1:SDI1+3)	VXX: SLSS1=VXX: DGM 3=+*****	SLSS1=DGM 3=+*****	✓	✓			
	DUAL LINK(SLOT2:SDI1+3)	VXX: SLSS2=VXX: DGM 3=+*****	SLSS2=DGM 3=+*****	✓	✓			
QUAD LINK(SLOT1:SDI1+2+3+4)	VXX: SLSS1=VXX: QGMI 1=+*****	SLSS1=QGMI 1=+*****	✓	✓				
QUAD LINK(SLOT2:SDI1+2+3+4)	VXX: SLSS2=VXX: QGMI 1=+*****	SLSS2=QGMI 1=+*****	✓	✓				
AUTO	VXX: *****=VXX: *****=+00000	*****=*****=+00000	✓	✓				
TYPE1/LEVEL A	VXX: *****=VXX: *****=+00001	*****=*****=+00001	✓	✓				
TYPE2/LEVEL B	VXX: *****=VXX: *****=+00002	*****=*****=+00002	✓	✓				
SLOT : SDI : SDI SYSTEM SELECTOR		* PARAMETER	VXX: *****=VXX: *****=*, *****	QVX: *****=QVX: *****=*, *****	*****=*****=*, *****	✓	✓	
* PARAMETER1, 2 (ET-MDN12G10)	SINGLE LINK(SLOT1:SDI1)	VXX: SLSS1=VXX: SYSS1=1: 1: ****	QVX: SLSS1=QVX: SYSS1=1: 1	SLSS1=SYSS1=1: 1: ****	✓	✓		
	SINGLE LINK(SLOT1:SDI2)	VXX: SLSS1=VXX: SYSS1=1: 2: ****	QVX: SLSS1=QVX: SYSS1=1: 2	SLSS1=SYSS1=1: 2: ****	✓	✓		
	SINGLE LINK(SLOT1:SDI3)	VXX: SLSS1=VXX: SYSS1=1: 3: ****	QVX: SLSS1=QVX: SYSS1=1: 3	SLSS1=SYSS1=1: 3: ****	✓	✓		
	SINGLE LINK(SLOT1:SDI4)	VXX: SLSS1=VXX: SYSS1=1: 4: ****	QVX: SLSS1=QVX: SYSS1=1: 4	SLSS1=SYSS1=1: 4: ****	✓	✓		
	SINGLE LINK(SLOT2:SDI1)	VXX: SLSS2=VXX: SYSS1=1: 1: ****	QVX: SLSS2=QVX: SYSS1=1: 1	SLSS2=SYSS1=1: 1: ****	✓	✓		
	SINGLE LINK(SLOT2:SDI2)	VXX: SLSS2=VXX: SYSS1=1: 2: ****	QVX: SLSS2=QVX: SYSS1=1: 2	SLSS2=SYSS1=1: 2: ****	✓	✓		
	SINGLE LINK(SLOT2:SDI3)	VXX: SLSS2=VXX: SYSS1=1: 3: ****	QVX: SLSS2=QVX: SYSS1=1: 3	SLSS2=SYSS1=1: 3: ****	✓	✓		
	SINGLE LINK(SLOT2:SDI4)	VXX: SLSS2=VXX: SYSS1=1: 4: ****	QVX: SLSS2=QVX: SYSS1=1: 4	SLSS2=SYSS1=1: 4: ****	✓	✓		
	DUAL LINK(SLOT1:SDI1+3)	VXX: SLSS1=VXX: SYSS1=2: 13: ****	QVX: SLSS1=QVX: SYSS1=2: 13	SLSS1=SYSS1=2: 13: ****	✓	✓		
	DUAL LINK(SLOT2:SDI1+3)	VXX: SLSS2=VXX: SYSS1=2: 13: ****	QVX: SLSS2=QVX: SYSS1=2: 13	SLSS2=SYSS1=2: 13: ****	✓	✓		
QUAD LINK(SLOT1:SDI1+2+3+4)	VXX: SLSS1=VXX: SYSS1=4: 1234: ****	QVX: SLSS1=QVX: SYSS1=4: 1234	SLSS1=SYSS1=4: 1234: ****	✓	✓			
QUAD LINK(SLOT2:SDI1+2+3+4)	VXX: SLSS2=VXX: SYSS1=4: 1234: ****	QVX: SLSS2=QVX: SYSS1=4: 1234	SLSS2=SYSS1=4: 1234: ****	✓	✓			
AUTO	VXX: *****=VXX: SYSS1=*, *****: 00000	*****=SYSS1=*, *****: 00000	✓	✓				
RGB	VXX: *****=VXX: SYSS1=*, *****: 00001	*****=SYSS1=*, *****: 00001	✓	✓				
YPbPr4:4:4	VXX: *****=VXX: SYSS1=*, *****: 00002	*****=SYSS1=*, *****: 00002	✓	✓				
YPbPr4:2:2	VXX: *****=VXX: SYSS1=*, *****: 00003	*****=SYSS1=*, *****: 00003	✓	✓				
SLOT : SDI : BIT DEPTH		* PARAMETER	VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓	
* PARAMETER1, 2 (ET-MDN12G10)	SINGLE LINK(SLOT1:SDI1)	VXX: SLSS1=VXX: SBTI 1=+*****	SLSS1=SBTI 1=+*****	✓	✓			
	SINGLE LINK(SLOT1:SDI2)	VXX: SLSS1=VXX: SBTI 2=+*****	SLSS1=SBTI 2=+*****	✓	✓			
	SINGLE LINK(SLOT1:SDI3)	VXX: SLSS1=VXX: SBTI 4=+*****	SLSS1=SBTI 4=+*****	✓	✓			
	SINGLE LINK(SLOT1:SDI4)	VXX: SLSS1=VXX: SBTI 5=+*****	SLSS1=SBTI 5=+*****	✓	✓			
	SINGLE LINK(SLOT2:SDI1)	VXX: SLSS2=VXX: SBTI 1=+*****	SLSS2=SBTI 1=+*****	✓	✓			
	SINGLE LINK(SLOT2:SDI2)	VXX: SLSS2=VXX: SBTI 2=+*****	SLSS2=SBTI 2=+*****	✓	✓			
	SINGLE LINK(SLOT2:SDI3)	VXX: SLSS2=VXX: SBTI 4=+*****	SLSS2=SBTI 4=+*****	✓	✓			
	SINGLE LINK(SLOT2:SDI4)	VXX: SLSS2=VXX: SBTI 5=+*****	SLSS2=SBTI 5=+*****	✓	✓			
	DUAL LINK(SDI1+3)	VXX: SLSS1=VXX: SBTI 3=+*****	SLSS1=SBTI 3=+*****	✓	✓			
	DUAL LINK(SDI1+3)	VXX: SLSS2=VXX: SBTI 3=+*****	SLSS2=SBTI 3=+*****	✓	✓			
QUAD LINK (SDI1+2+3+4)	VXX: SLSS1=VXX: SBTI 7=+*****	SLSS1=SBTI 7=+*****	✓	✓				
QUAD LINK (SDI1+2+3+4)	VXX: SLSS2=VXX: SBTI 7=+*****	SLSS2=SBTI 7=+*****	✓	✓				
AUTO	VXX: *****=VXX: *****=+00000	*****=*****=+00000	✓	✓				
12-bit	VXX: *****=VXX: *****=+00001	*****=*****=+00001	✓	✓				
10-bit	VXX: *****=VXX: *****=+00002	*****=*****=+00002	✓	✓				
SLOT : SDI : SIGNAL LEVEL		* PARAMETER	VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓	
* PARAMETER1, 2 (ET-MDN12G10)	SINGLE LINK(SLOT1:SDI1)	VXX: SLSS1=VXX: SSLI 1=+*****	SLSS1=SSLI 1=+*****	✓	✓			
	SINGLE LINK(SLOT1:SDI2)	VXX: SLSS1=VXX: SSLI 2=+*****	SLSS1=SSLI 2=+*****	✓	✓			
	SINGLE LINK(SLOT1:SDI3)	VXX: SLSS1=VXX: SSLI 4=+*****	SLSS1=SSLI 4=+*****	✓	✓			
	SINGLE LINK(SLOT1:SDI4)	VXX: SLSS1=VXX: SSLI 5=+*****	SLSS1=SSLI 5=+*****	✓	✓			
	SINGLE LINK(SLOT2:SDI1)	VXX: SLSS2=VXX: SSLI 1=+*****	SLSS2=SSLI 1=+*****	✓	✓			
	SINGLE LINK(SLOT2:SDI2)	VXX: SLSS2=VXX: SSLI 2=+*****	SLSS2=SSLI 2=+*****	✓	✓			
	SINGLE LINK(SLOT2:SDI3)	VXX: SLSS2=VXX: SSLI 4=+*****	SLSS2=SSLI 4=+*****	✓	✓			
	SINGLE LINK(SLOT2:SDI4)	VXX: SLSS2=VXX: SSLI 5=+*****	SLSS2=SSLI 5=+*****	✓	✓			
	DUAL LINK(SDI1+3)	VXX: SLSS1=VXX: SSLI 3=+*****	SLSS1=SSLI 3=+*****	✓	✓			
	DUAL LINK(SDI1+3)	VXX: SLSS2=VXX: SSLI 3=+*****	SLSS2=SSLI 3=+*****	✓	✓			
QUAD LINK (SDI1+2+3+4)	VXX: SLSS1=VXX: SSLI 7=+*****	SLSS1=SSLI 7=+*****	✓	✓				
QUAD LINK (SDI1+2+3+4)	VXX: SLSS2=VXX: SSLI 7=+*****	SLSS2=SSLI 7=+*****	✓	✓				
64-940	VXX: *****=VXX: *****=+00000	*****=*****=+00000	✓	✓				
4-1019	VXX: *****=VXX: *****=+00001	*****=*****=+00001	✓	✓				
SLOT : HDMI : SIGNAL LEVEL		* PARAMETER	VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓	
* PARAMETER1, 2	HDMI1	VXX: SLSS1=VXX: HSLI 1=+*****	SLSS1=HSLI 1=+*****	✓	✓			
	HDMI2	VXX: SLSS1=VXX: HSLI 2=+*****	SLSS1=HSLI 2=+*****	✓	✓			
	HDMI3	VXX: SLSS2=VXX: HSLI 1=+*****	SLSS2=HSLI 1=+*****	✓	✓			
	HDMI4	VXX: SLSS2=VXX: HSLI 2=+*****	SLSS2=HSLI 2=+*****	✓	✓			
	DUAL LINK 1(HDMI1+2)	VXX: SLSS1=VXX: HSDI 1=+*****	SLSS1=HSDI 1=+*****	✓	✓			
	DUAL LINK 2(HDMI3+4)	VXX: SLSS2=VXX: HSDI 1=+*****	SLSS2=HSDI 1=+*****	✓	✓			
	QUAD LINK (HDMI1+2+3+4)	VXX: SLDS1=VXX: HSQI 1=+*****	SLDS1=HSQI 1=+*****	✓	✓			
	0-1023	VXX: *****=VXX: *****=+00000	*****=*****=+00000	✓	✓			
	64-940	VXX: *****=VXX: *****=+00001	*****=*****=+00001	✓	✓			
	AUTO	VXX: *****=VXX: *****=+00002	*****=*****=+00002	✓	✓			
SLOT : HDMI : AUTO GAMMA SELECT		* PARAMETER	VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓	
* PARAMETER1, 2	HDMI1	VXX: SLSS1=VXX: HAGI 1=+*****	SLSS1=HAGI 1=+*****	✓	✓			
	HDMI2	VXX: SLSS1=VXX: HAGI 2=+*****	SLSS1=HAGI 2=+*****	✓	✓			
	HDMI3	VXX: SLSS2=VXX: HAGI 1=+*****	SLSS2=HAGI 1=+*****	✓	✓			
	HDMI4	VXX: SLSS2=VXX: HAGI 2=+*****	SLSS2=HAGI 2=+*****	✓	✓			
* PARAMETER3	DISABLE	VXX: *****=VXX: *****=+00000	*****=*****=+00000	✓	✓			
	ENABLE	VXX: *****=VXX: *****=+00001	*****=*****=+00001	✓	✓			
SLOT : HDMI : AUTO COLOR SPACE SELECT		* PARAMETER	VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓	
* PARAMETER1, 2	HDMI1	VXX: SLSS1=VXX: HACI 1=+*****	SLSS1=HACI 1=+*****	✓	✓			
	HDMI2	VXX: SLSS1=VXX: HACI 2=+*****	SLSS1=HACI 2=+*****	✓	✓			
	HDMI3	VXX: SLSS2=VXX: HACI 1=+*****	SLSS2=HACI 1=+*****	✓	✓			
	HDMI4	VXX: SLSS2=VXX: HACI 2=+*****	SLSS2=HACI 2=+*****	✓	✓			
* PARAMETER3	DISABLE	VXX: *****=VXX: *****=+00000	*****=*****=+00000	✓	✓			

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ35K SERIES	RZ34K SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K SRQ35KC	RZ34K SRZ34KC
DISPLAY OPTION	SLOT : HDMI : EDID SELECT	* PARAMETER	ENABLE	VXX: *****=VXX: *****+00001 VXX: *****=VXX: *****+*****		*****=*****+00001 *****=*****+*****	✓	✓
		* PARAMETER1, 2	HDMI1 HDMI2 HDMI3 HDMI4	VXX: SLSS1=VXX: HESI 1=+***** VXX: SLSS1=VXX: HESI 2=+***** VXX: SLSS2=VXX: HESI 1=+***** VXX: SLSS2=VXX: HESI 2=+*****		SLSS1=HESI 1=+***** SLSS1=HESI 2=+***** SLSS2=HESI 1=+***** SLSS2=HESI 2=+*****	✓	✓
		* PARAMETER3	4K/60p/SDR 4K/30p 2K 4K/60p/HDR	VXX: *****=VXX: *****+00000 VXX: *****=VXX: *****+00001 VXX: *****=VXX: *****+00002 VXX: *****=VXX: *****+00010		*****=*****+00000 *****=*****+00001 *****=*****+00002 *****=*****+00010	✓	✓
		* PARAMETER		VXX: *****=VXX: *****+*****	QVX: *****=QVX: *****	*****=*****+*****	✓	✓
		* PARAMETER1, 2	HDMI1 HDMI2 HDMI3 HDMI4	VXX: SLSS1=VXX: EDMI 3=+***** VXX: SLSS1=VXX: EDMI 6=+***** VXX: SLSS2=VXX: EDMI 3=+***** VXX: SLSS2=VXX: EDMI 6=+*****		SLSS1=EDMI 3=+***** SLSS1=EDMI 6=+***** SLSS2=EDMI 3=+***** SLSS2=EDMI 6=+*****	✓	✓
		* PARAMETER3	DEFAULT SCREEN FIT USER	VXX: *****=VXX: *****+00000 VXX: *****=VXX: *****+00001 VXX: *****=VXX: *****+00010		*****=*****+00000 *****=*****+00001 *****=*****+00010	✓	✓
		* PARAMETER		VXX: *****=VXX: *****+*****	QVX: *****=QVX: *****	*****=*****+*****	✓	✓
		* PARAMETER1, 2	HDMI1 HDMI2 HDMI3 HDMI4	VXX: SLSS1=VXX: EDRS3=*****: * VXX: SLSS1=VXX: EDRS6=*****: * VXX: SLSS2=VXX: EDRS3=*****: * VXX: SLSS2=VXX: EDRS6=*****: *		SLSS1=EDRS3=*****: * SLSS1=EDRS6=*****: * SLSS2=EDRS3=*****: * SLSS2=EDRS6=*****: *	✓	✓
		* PARAMETER3	1024x768 1280x720 1280x800 1280x1024 1366x768 1400x1050 1440x900 1600x900 1600x1200 1680x1050 1920x1080 1920x1200 1920x2160 2048x1080 2048x2160 2560x1600 3840x2400	VXX: *****=VXX: *****=1024: 0768: * VXX: *****=VXX: *****=1280: 0720: * VXX: *****=VXX: *****=1280: 0800: * VXX: *****=VXX: *****=1280: 1024: * VXX: *****=VXX: *****=1366: 0768: * VXX: *****=VXX: *****=1400: 1050: * VXX: *****=VXX: *****=1440: 0900: * VXX: *****=VXX: *****=1600: 0900: * VXX: *****=VXX: *****=1600: 1200: * VXX: *****=VXX: *****=1680: 1050: * VXX: *****=VXX: *****=1920: 1080: * VXX: *****=VXX: *****=1920: 1200: * VXX: *****=VXX: *****=1920: 2160: * VXX: *****=VXX: *****=2048: 1080: * VXX: *****=VXX: *****=2048: 2160: * VXX: *****=VXX: *****=2560: 1600: * VXX: *****=VXX: *****=3840: 2400: *		*****=*****=1024: 0768: * *****=*****=1280: 0720: * *****=*****=1280: 0800: * *****=*****=1280: 1024: * *****=*****=1366: 0768: * *****=*****=1400: 1050: * *****=*****=1440: 0900: * *****=*****=1600: 0900: * *****=*****=1600: 1200: * *****=*****=1680: 1050: * *****=*****=1920: 1080: * *****=*****=1920: 1200: * *****=*****=1920: 2160: * *****=*****=2048: 1080: * *****=*****=2048: 2160: * *****=*****=2560: 1600: * *****=*****=3840: 2400: *	✓	✓
		* PARAMETER4	Progressive Interlace	VXX: *****=VXX: *****=*****: p VXX: *****=VXX: *****=*****: i		*****=*****=*****: p *****=*****=*****: i	✓	✓
	* PARAMETER		VXX: *****=VXX: *****+*****	QVX: *****=QVX: *****	*****=*****+*****	✓	✓	
	* PARAMETER1, 2	HDMI1 HDMI2 HDMI3 HDMI4	VXX: SLSS1=VXX: EDVI 3=+***** VXX: SLSS1=VXX: EDVI 6=+***** VXX: SLSS2=VXX: EDVI 3=+***** VXX: SLSS2=VXX: EDVI 6=+*****		SLSS1=EDVI 3=+***** SLSS1=EDVI 6=+***** SLSS2=EDVI 3=+***** SLSS2=EDVI 6=+*****	✓	✓	
	* PARAMETER3	60Hz 50Hz 48Hz 30Hz 25Hz 24Hz	VXX: *****=VXX: *****+06000 VXX: *****=VXX: *****+05000 VXX: *****=VXX: *****+04800 VXX: *****=VXX: *****+03000 VXX: *****=VXX: *****+02500 VXX: *****=VXX: *****+02400		*****=*****+06000 *****=*****+05000 *****=*****+04800 *****=*****+03000 *****=*****+02500 *****=*****+02400	✓	✓	
	* PARAMETER		VXX: *****=VXX: *****+*****	QVX: *****=QVX: *****	*****=*****+*****	✓	✓	
	* PARAMETER1, 2	HDMI1 HDMI2 HDMI3 HDMI4	VXX: SLSS1=VXX: EDHS1=*****: * VXX: SLSS1=VXX: EDHS2=*****: * VXX: SLSS2=VXX: EDHS1=*****: * VXX: SLSS2=VXX: EDHS2=*****: *		SLSS1=EDHS1=*****: * SLSS1=EDHS2=*****: * SLSS2=EDHS1=*****: * SLSS2=EDHS2=*****: *	✓	✓	
	* PARAMETER3	1024x768 1280x720 1280x800 1280x1024 1366x768 1400x1050 1440x900 1600x900 1600x1200 1680x1050 1920x1080 1920x1200 1920x2160 2048x1080 2048x2160 2560x1600 3840x2400	VXX: *****=VXX: *****=1024: 0768: * VXX: *****=VXX: *****=1280: 0720: * VXX: *****=VXX: *****=1280: 0800: * VXX: *****=VXX: *****=1280: 1024: * VXX: *****=VXX: *****=1366: 0768: * VXX: *****=VXX: *****=1400: 1050: * VXX: *****=VXX: *****=1440: 0900: * VXX: *****=VXX: *****=1600: 0900: * VXX: *****=VXX: *****=1600: 1200: * VXX: *****=VXX: *****=1680: 1050: * VXX: *****=VXX: *****=1920: 1080: * VXX: *****=VXX: *****=1920: 1200: * VXX: *****=VXX: *****=1920: 2160: * VXX: *****=VXX: *****=2048: 1080: * VXX: *****=VXX: *****=2048: 2160: * VXX: *****=VXX: *****=2560: 1600: * VXX: *****=VXX: *****=3840: 2400: *		*****=*****=1024: 0768: * *****=*****=1280: 0720: * *****=*****=1280: 0800: * *****=*****=1280: 1024: * *****=*****=1366: 0768: * *****=*****=1400: 1050: * *****=*****=1440: 0900: * *****=*****=1600: 0900: * *****=*****=1600: 1200: * *****=*****=1680: 1050: * *****=*****=1920: 1080: * *****=*****=1920: 1200: * *****=*****=1920: 2160: * *****=*****=2048: 1080: * *****=*****=2048: 2160: * *****=*****=2560: 1600: * *****=*****=3840: 2400: *	✓	✓	
	* PARAMETER4	Progressive Interlace	VXX: *****=VXX: *****=*****: p VXX: *****=VXX: *****=*****: i		*****=*****=*****: p *****=*****=*****: i	✓	✓	
	* PARAMETER5	60Hz 50Hz 48Hz 30Hz 25Hz 24Hz	VXX: *****=VXX: *****=*****: * 6000 VXX: *****=VXX: *****=*****: * 5000 VXX: *****=VXX: *****=*****: * 4800 VXX: *****=VXX: *****=*****: * 3000 VXX: *****=VXX: *****=*****: * 2500 VXX: *****=VXX: *****=*****: * 2400		*****=*****=*****: * 6000 *****=*****=*****: * 5000 *****=*****=*****: * 4800 *****=*****=*****: * 3000 *****=*****=*****: * 2500 *****=*****=*****: * 2400	✓	✓	
	* PARAMETER		VXX: *****=VXX: *****+*****	QVX: *****=QVX: *****	*****=*****+*****	✓	✓	
	* PARAMETER1, 2	HDMI1 HDMI2 HDMI3 HDMI4			SLSS1=ESH1=*****: * SLSS1=ESH2=*****: * SLSS2=ESH1=*****: * SLSS2=ESH2=*****: *	✓	✓	
	* PARAMETER3	1024x768 1280x720 1280x800 1280x1024 1366x768 1400x1050 1440x900 1600x900 1600x1200 1680x1050 1920x1080 1920x1200 1920x2160 2048x1080 2048x2160 2560x1600 3840x2400			*****=*****=1024: 0768: * *****=*****=1280: 0720: * *****=*****=1280: 0800: * *****=*****=1280: 1024: * *****=*****=1366: 0768: * *****=*****=1400: 1050: * *****=*****=1440: 0900: * *****=*****=1600: 0900: * *****=*****=1600: 1200: * *****=*****=1680: 1050: * *****=*****=1920: 1080: * *****=*****=1920: 1200: * *****=*****=1920: 2160: * *****=*****=2048: 1080: * *****=*****=2048: 2160: * *****=*****=2560: 1600: * *****=*****=3840: 2400: *	✓	✓	
	* PARAMETER4	Progressive Interlace			*****=*****=*****: p *****=*****=*****: i	✓	✓	
	* PARAMETER5	60Hz 50Hz 48Hz 30Hz 25Hz 24Hz			*****=*****=*****: * 6000 *****=*****=*****: * 5000 *****=*****=*****: * 4800 *****=*****=*****: * 3000 *****=*****=*****: * 2500 *****=*****=*****: * 2400	✓	✓	
	* PARAMETER		VXX: *****=VXX: *****+*****	QVX: *****=QVX: *****	*****=*****+*****	✓	✓	
	* PARAMETER1, 2	DVI1 DVI2 DVI3 DVI4 QUAD LINK (DVI1+2+3+4)	VXX: SLSS1=VXX: DVII 0=+***** VXX: SLSS1=VXX: DVII 2=+***** VXX: SLSS2=VXX: DVII 0=+***** VXX: SLSS2=VXX: DVII 2=+***** VXX: SLDS1=VXX: DVQI 1=+*****		SLSS1=DVII 0=+***** SLSS1=DVII 2=+***** SLSS2=DVII 0=+***** SLSS2=DVII 2=+***** SLDS1=DVQI 1=+*****	✓	✓	
	* PARAMETER3	0-25(PC) 16-235	VXX: *****=VXX: *****+00000 VXX: *****=VXX: *****+00001		*****=*****+00000 *****=*****+00001	✓	✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ35K SERIES	RZ34K SERIES	
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K SRQ35KC	RZ34K SRZ34KC	
SLOT : DVI : EDID SELECT	* PARAMETER		AUTO	VXX: *****=VXX: *****=+00002 VXX: *****=VXX: *****=+*****		*****=*****=+00002 *****=*****=+*****	✓	✓	
	* PARAMETER1, 2	DVI1 DVI2 DVI3 DVI4		VXX: SLSS1=VXX: DSLI 1=+***** VXX: SLSS1=VXX: DSLI 2=+***** VXX: SLSS2=VXX: DSLI 1=+***** VXX: SLSS2=VXX: DSLI 2=+*****		SLSS1=DSLI 1=+***** SLSS1=DSLI 2=+***** SLSS2=DSLI 1=+***** SLSS2=DSLI 2=+*****	✓	✓	
	* PARAMETER3	EDID1:4K/60p EDID2:4K/30p EDID3:2K		VXX: *****=VXX: *****=+00000 VXX: *****=VXX: *****=+00001 VXX: *****=VXX: *****=+00002		*****=*****=+00000 *****=*****=+00001 *****=*****=+00002	✓	✓	
	* PARAMETER			VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓	
	* PARAMETER1, 2	DVI1 DVI2 DVI3 DVI4		VXX: SLSS1=VXX: EDMI 2=+***** VXX: SLSS1=VXX: EDMI 5=+***** VXX: SLSS2=VXX: EDMI 2=+***** VXX: SLSS2=VXX: EDMI 5=+*****		SLSS1=EDMI 2=+***** SLSS1=EDMI 5=+***** SLSS2=EDMI 2=+***** SLSS2=EDMI 5=+*****	✓	✓	
	* PARAMETER3	DEFAULT SCREEN FIT USER		VXX: *****=VXX: *****=+00000 VXX: *****=VXX: *****=+00001 VXX: *****=VXX: *****=+00010		*****=*****=+00000 *****=*****=+00001 *****=*****=+00010	✓	✓	
	* PARAMETER			VXX: *****=VXX: *****=*****: *	QVX: *****=QVX: *****	*****=*****=*****: *	✓	✓	
	* PARAMETER1, 2	DVI1 DVI2 DVI3 DVI4		VXX: SLSS1=VXX: EDRS2=*****: * VXX: SLSS1=VXX: EDRS5=*****: * VXX: SLSS2=VXX: EDRS2=*****: * VXX: SLSS2=VXX: EDRS5=*****: *		SLSS1=EDRS2=*****: * SLSS1=EDRS5=*****: * SLSS2=EDRS2=*****: * SLSS2=EDRS5=*****: *	✓	✓	
	* PARAMETER3	1024x768 1280x720 1280x800 1280x1024 1366x768 1400x1050 1440x900 1600x900 1600x1200 1680x1050 1920x1080 1920x1200 2048x1080		VXX: *****=VXX: *****=1024: 0768: * VXX: *****=VXX: *****=1280: 0720: * VXX: *****=VXX: *****=1280: 0800: * VXX: *****=VXX: *****=1280: 1024: * VXX: *****=VXX: *****=1366: 0768: * VXX: *****=VXX: *****=1400: 1050: * VXX: *****=VXX: *****=1440: 0900: * VXX: *****=VXX: *****=1600: 0900: * VXX: *****=VXX: *****=1600: 1200: * VXX: *****=VXX: *****=1680: 1050: * VXX: *****=VXX: *****=1920: 1080: * VXX: *****=VXX: *****=1920: 1200: * VXX: *****=VXX: *****=2048: 1080: *		*****=*****=1024: 0768: * *****=*****=1280: 0720: * *****=*****=1280: 0800: * *****=*****=1280: 1024: * *****=*****=1366: 0768: * *****=*****=1400: 1050: * *****=*****=1440: 0900: * *****=*****=1600: 0900: * *****=*****=1600: 1200: * *****=*****=1680: 1050: * *****=*****=1920: 1080: * *****=*****=1920: 1200: * *****=*****=2048: 1080: *	✓	✓	
	* PARAMETER4	Progressive Interlace		VXX: *****=VXX: *****=*****: p VXX: *****=VXX: *****=*****: i		*****=*****=*****: p *****=*****=*****: i	✓	✓	
	* PARAMETER			VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓	
	SLOT : DVI : EDID VERTICAL SCAN FREQUENCY	* PARAMETER1, 2	DVI1 DVI2 DVI3 DVI4		VXX: SLSS1=VXX: EDVI 2=+***** VXX: SLSS1=VXX: EDVI 5=+***** VXX: SLSS2=VXX: EDVI 2=+***** VXX: SLSS2=VXX: EDVI 5=+*****		SLSS1=EDVI 2=+***** SLSS1=EDVI 5=+***** SLSS2=EDVI 2=+***** SLSS2=EDVI 5=+*****	✓	✓
* PARAMETER3		60Hz 50Hz 48Hz 30Hz 25Hz 24Hz		VXX: *****=VXX: *****=+06000 VXX: *****=VXX: *****=+05000 VXX: *****=VXX: *****=+04800 VXX: *****=VXX: *****=+03000 VXX: *****=VXX: *****=+02500 VXX: *****=VXX: *****=+02400		*****=*****=+06000 *****=*****=+05000 *****=*****=+04800 *****=*****=+03000 *****=*****=+02500 *****=*****=+02400	✓	✓	
* PARAMETER4		Progressive Interlace		VXX: *****=VXX: *****=*****: p VXX: *****=VXX: *****=*****: i		*****=*****=*****: p *****=*****=*****: i	✓	✓	
* PARAMETER				VXX: *****=VXX: *****=*****: *, *****	QVX: *****=QVX: *****	*****=*****=*****: *, *****	✓	✓	
* PARAMETER1, 2		DVI1 DVI2 DVI3 DVI4		VXX: SLSS1=VXX: EDDS1=*****: *, ***** VXX: SLSS1=VXX: EDDS2=*****: *, ***** VXX: SLSS2=VXX: EDDS1=*****: *, ***** VXX: SLSS2=VXX: EDDS2=*****: *, *****		SLSS1=EDDS1=*****: *, ***** SLSS1=EDDS2=*****: *, ***** SLSS2=EDDS1=*****: *, ***** SLSS2=EDDS2=*****: *, *****	✓	✓	
* PARAMETER3		1024x768 1280x720 1280x800 1280x1024 1366x768 1400x1050 1440x900 1600x900 1600x1200 1680x1050 1920x1080 1920x1200 2048x1080		VXX: *****=VXX: *****=1024: 0768: *, ***** VXX: *****=VXX: *****=1280: 0720: *, ***** VXX: *****=VXX: *****=1280: 0800: *, ***** VXX: *****=VXX: *****=1280: 1024: *, ***** VXX: *****=VXX: *****=1366: 0768: *, ***** VXX: *****=VXX: *****=1400: 1050: *, ***** VXX: *****=VXX: *****=1440: 0900: *, ***** VXX: *****=VXX: *****=1600: 0900: *, ***** VXX: *****=VXX: *****=1600: 1200: *, ***** VXX: *****=VXX: *****=1680: 1050: *, ***** VXX: *****=VXX: *****=1920: 1080: *, ***** VXX: *****=VXX: *****=1920: 1200: *, ***** VXX: *****=VXX: *****=2048: 1080: *, *****		*****=*****=1024: 0768: *, ***** *****=*****=1280: 0720: *, ***** *****=*****=1280: 0800: *, ***** *****=*****=1280: 1024: *, ***** *****=*****=1366: 0768: *, ***** *****=*****=1400: 1050: *, ***** *****=*****=1440: 0900: *, ***** *****=*****=1600: 0900: *, ***** *****=*****=1600: 1200: *, ***** *****=*****=1680: 1050: *, ***** *****=*****=1920: 1080: *, ***** *****=*****=1920: 1200: *, ***** *****=*****=2048: 1080: *, *****	✓	✓	
* PARAMETER4		Progressive Interlace		VXX: *****=VXX: *****=*****: p VXX: *****=VXX: *****=*****: i		*****=*****=*****: p *****=*****=*****: i	✓	✓	
* PARAMETER5		60Hz 50Hz 48Hz 30Hz 25Hz 24Hz		VXX: *****=VXX: *****=*****: *, 6000 VXX: *****=VXX: *****=*****: *, 5000 VXX: *****=VXX: *****=*****: *, 4800 VXX: *****=VXX: *****=*****: *, 3000 VXX: *****=VXX: *****=*****: *, 2500 VXX: *****=VXX: *****=*****: *, 2400		*****=*****=*****: *, 6000 *****=*****=*****: *, 5000 *****=*****=*****: *, 4800 *****=*****=*****: *, 3000 *****=*****=*****: *, 2500 *****=*****=*****: *, 2400	✓	✓	
* PARAMETER				VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓	
SLOT : DVI : EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY		* PARAMETER1, 2	DVI1 DVI2 DVI3 DVI4				SLSS1=ESDS1=*****: *, ***** SLSS1=ESDS2=*****: *, ***** SLSS2=ESDS1=*****: *, ***** SLSS2=ESDS2=*****: *, *****	✓	✓
		* PARAMETER3	1024x768 1280x720 1280x800 1280x1024 1366x768 1400x1050 1440x900 1600x900 1600x1200 1680x1050 1920x1080 1920x1200 2048x1080				*****=*****=1024: 0768: *, ***** *****=*****=1280: 0720: *, ***** *****=*****=1280: 0800: *, ***** *****=*****=1280: 1024: *, ***** *****=*****=1366: 0768: *, ***** *****=*****=1400: 1050: *, ***** *****=*****=1440: 0900: *, ***** *****=*****=1600: 0900: *, ***** *****=*****=1600: 1200: *, ***** *****=*****=1680: 1050: *, ***** *****=*****=1920: 1080: *, ***** *****=*****=1920: 1200: *, ***** *****=*****=2048: 1080: *, *****	✓	✓
		* PARAMETER4	Progressive Interlace				*****=*****=*****: p *****=*****=*****: i	✓	✓
	* PARAMETER5	60Hz 50Hz 48Hz 30Hz 25Hz 24Hz				*****=*****=*****: *, 6000 *****=*****=*****: *, 5000 *****=*****=*****: *, 4800 *****=*****=*****: *, 3000 *****=*****=*****: *, 2500 *****=*****=*****: *, 2400	✓	✓	
	* PARAMETER			VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓	
	* PARAMETER1, 2	DisplayPort1 DisplayPort2 DisplayPort3 DisplayPort4		VXX: SLSS1=VXX: DPLI 1=+***** VXX: SLSS1=VXX: DPLI 2=+***** VXX: SLSS2=VXX: DPLI 1=+***** VXX: SLSS2=VXX: DPLI 2=+*****		SLSS1=DPLI 1=+***** SLSS1=DPLI 2=+***** SLSS2=DPLI 1=+***** SLSS2=DPLI 2=+*****	✓	✓	
	* PARAMETER3	0-1023 64-940 AUTO		VXX: *****=VXX: *****=+00000 VXX: *****=VXX: *****=+00001 VXX: *****=VXX: *****=+00002		*****=*****=+00000 *****=*****=+00001 *****=*****=+00002	✓	✓	
	* PARAMETER			VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓	
	* PARAMETER1, 2	DisplayPort1 DisplayPort2 DisplayPort3 DisplayPort4		VXX: SLSS1=VXX: DAGI 1=+***** VXX: SLSS1=VXX: DAGI 2=+***** VXX: SLSS2=VXX: DAGI 1=+***** VXX: SLSS2=VXX: DAGI 2=+*****		SLSS1=DAGI 1=+***** SLSS1=DAGI 2=+***** SLSS2=DAGI 1=+***** SLSS2=DAGI 2=+*****	✓	✓	
	* PARAMETER3	DISABLE ENABLE		VXX: *****=VXX: *****=+00000 VXX: *****=VXX: *****=+00001		*****=*****=+00000 *****=*****=+00001	✓	✓	
	* PARAMETER			VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓	
	* PARAMETER1, 2	DisplayPort1 DisplayPort2 DisplayPort3		VXX: SLSS1=VXX: DACI 1=+***** VXX: SLSS1=VXX: DACI 2=+***** VXX: SLSS2=VXX: DACI 1=+*****		SLSS1=DACI 1=+***** SLSS1=DACI 2=+***** SLSS2=DACI 1=+*****	✓	✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY	RQ35K SERIES	RZ34K SERIES	
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K SRQ35KC	RZ34K SRZ34KC
SLOT : DisplayPort : EDID SELECT	* PARAMETER3	DISABLE	DisplayPort4	VXX: SLSS2=VXX: DACI 2=+*****		SLSS2=DACI 2=+*****	✓	✓
			ENABLE	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓	✓
	* PARAMETER		DisplayPort1	VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓
			DisplayPort2	VXX: SLSS1=VXX: DESI 1=+*****		SLSS1=DESI 1=+*****	✓	✓
			DisplayPort3	VXX: SLSS1=VXX: DESI 2=+*****		SLSS1=DESI 2=+*****	✓	✓
			DisplayPort4	VXX: SLSS2=VXX: DESI 1=+*****		SLSS2=DESI 1=+*****	✓	✓
	* PARAMETER3		4K/60p	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓	✓
			4K/30p	VXX: *****=VXX: *****=+00001		*****=*****=+00001	✓	✓
			2K	VXX: *****=VXX: *****=+00002		*****=*****=+00002	✓	✓
			4K/60p/HDR	VXX: *****=VXX: *****=+00010		*****=*****=+00010	✓	✓
	SLOT : DisplayPort : EDID MODE	* PARAMETER		VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓
		* PARAMETER1, 2	DisplayPort1	VXX: SLSS1=VXX: EDMI 8=+*****		SLSS1=EDMI 8=+*****	✓	✓
DisplayPort2			VXX: SLSS1=VXX: EDMI 9=+*****		SLSS1=EDMI 9=+*****	✓	✓	
DisplayPort3			VXX: SLSS2=VXX: EDMI 8=+*****		SLSS2=EDMI 8=+*****	✓	✓	
DisplayPort4			VXX: SLSS2=VXX: EDMI 9=+*****		SLSS2=EDMI 9=+*****	✓	✓	
* PARAMETER3	DEFAULT	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓	✓		
USER	VXX: *****=VXX: *****=+00010		*****=*****=+00010	✓	✓			
SLOT : DisplayPort : EDID RESOLUTION	* PARAMETER		VXX: *****=VXX: *****=*****: *	QVX: *****=QVX: *****	*****=*****=*****: *	✓	✓	
	* PARAMETER1, 2	DisplayPort1	VXX: SLSS1=VXX: EDRS8=*****: *		SLSS1=EDRS8=*****: *	✓	✓	
		DisplayPort2	VXX: SLSS1=VXX: EDRS9=*****: *		SLSS1=EDRS9=*****: *	✓	✓	
		DisplayPort3	VXX: SLSS2=VXX: EDRS8=*****: *		SLSS2=EDRS8=*****: *	✓	✓	
		DisplayPort4	VXX: SLSS2=VXX: EDRS9=*****: *		SLSS2=EDRS9=*****: *	✓	✓	
	* PARAMETER3	1024x768	VXX: *****=VXX: *****=1024: 0768: *		*****=*****=1024: 0768: *	✓	✓	
		1280x720	VXX: *****=VXX: *****=1280: 0720: *		*****=*****=1280: 0720: *	✓	✓	
		1280x800	VXX: *****=VXX: *****=1280: 0800: *		*****=*****=1280: 0800: *	✓	✓	
		1400x1050	VXX: *****=VXX: *****=1400: 1050: *		*****=*****=1400: 1050: *	✓	✓	
		1600x900	VXX: *****=VXX: *****=1600: 0900: *		*****=*****=1600: 0900: *	✓	✓	
		1600x1200	VXX: *****=VXX: *****=1600: 1200: *		*****=*****=1600: 1200: *	✓	✓	
		1920x1080	VXX: *****=VXX: *****=1920: 1080: *		*****=*****=1920: 1080: *	✓	✓	
		1920x1200	VXX: *****=VXX: *****=1920: 1200: *		*****=*****=1920: 1200: *	✓	✓	
		2048x1080	VXX: *****=VXX: *****=2048: 1080: *		*****=*****=2048: 1080: *	✓	✓	
		2560x1600	VXX: *****=VXX: *****=2560: 1600: *		*****=*****=2560: 1600: *	✓	✓	
3840x2400	VXX: *****=VXX: *****=3840: 2400: *		*****=*****=3840: 2400: *	✓	✓			
* PARAMETER4	Progressive Interlace	VXX: *****=VXX: *****=*****: p		*****=*****=*****: p	✓	✓		
		VXX: *****=VXX: *****=*****: i		*****=*****=*****: i	✓	✓		
SLOT : DisplayPort : EDID VERTICAL SCAN FREQUENCY	* PARAMETER		VXX: *****=VXX: *****=*****	QVX: *****=QVX: *****	*****=*****=*****	✓	✓	
	* PARAMETER1, 2	DisplayPort1	VXX: SLSS1=VXX: EDVI 8=+*****		SLSS1=EDVI 8=+*****	✓	✓	
		DisplayPort2	VXX: SLSS1=VXX: EDVI 9=+*****		SLSS1=EDVI 9=+*****	✓	✓	
		DisplayPort3	VXX: SLSS2=VXX: EDVI 8=+*****		SLSS2=EDVI 8=+*****	✓	✓	
		DisplayPort4	VXX: SLSS2=VXX: EDVI 9=+*****		SLSS2=EDVI 9=+*****	✓	✓	
	* PARAMETER3	60Hz	VXX: *****=VXX: *****=+06000		*****=*****=+06000	✓	✓	
		50Hz	VXX: *****=VXX: *****=+05000		*****=*****=+05000	✓	✓	
		48Hz	VXX: *****=VXX: *****=+04800		*****=*****=+04800	✓	✓	
		30Hz	VXX: *****=VXX: *****=+03000		*****=*****=+03000	✓	✓	
		25Hz	VXX: *****=VXX: *****=+02500		*****=*****=+02500	✓	✓	
		24Hz	VXX: *****=VXX: *****=+02400		*****=*****=+02400	✓	✓	
		* PARAMETER4	Progressive	VXX: *****=VXX: *****=*****: *		*****=*****=*****: *	✓	✓
Interlace			VXX: *****=VXX: *****=*****: i		*****=*****=*****: i	✓	✓	
SLOT : DisplayPort : EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER		VXX: *****=VXX: *****=*****: *, ****	QVX: *****=QVX: *****	*****=*****=*****: *, ****	✓	✓	
	* PARAMETER1, 2	DisplayPort1	VXX: SLSS1=VXX: EDPS1=*****: *, ****		SLSS1=EDPS1=*****: *, ****	✓	✓	
		DisplayPort2	VXX: SLSS1=VXX: EDPS2=*****: *, ****		SLSS1=EDPS2=*****: *, ****	✓	✓	
		DisplayPort3	VXX: SLSS2=VXX: EDPS1=*****: *, ****		SLSS2=EDPS1=*****: *, ****	✓	✓	
		DisplayPort4	VXX: SLSS2=VXX: EDPS2=*****: *, ****		SLSS2=EDPS2=*****: *, ****	✓	✓	
	* PARAMETER3	1024x768	VXX: *****=VXX: *****=1024: 0768: *, ****		*****=*****=1024: 0768: *, ****	✓	✓	
		1280x720	VXX: *****=VXX: *****=1280: 0720: *, ****		*****=*****=1280: 0720: *, ****	✓	✓	
		1280x800	VXX: *****=VXX: *****=1280: 0800: *, ****		*****=*****=1280: 0800: *, ****	✓	✓	
		1400x1050	VXX: *****=VXX: *****=1400: 1050: *, ****		*****=*****=1400: 1050: *, ****	✓	✓	
		1600x900	VXX: *****=VXX: *****=1600: 0900: *, ****		*****=*****=1600: 0900: *, ****	✓	✓	
1600x1200		VXX: *****=VXX: *****=1600: 1200: *, ****		*****=*****=1600: 1200: *, ****	✓	✓		
1920x1080		VXX: *****=VXX: *****=1920: 1080: *, ****		*****=*****=1920: 1080: *, ****	✓	✓		
1920x1200		VXX: *****=VXX: *****=1920: 1200: *, ****		*****=*****=1920: 1200: *, ****	✓	✓		
2048x1080		VXX: *****=VXX: *****=2048: 1080: *, ****		*****=*****=2048: 1080: *, ****	✓	✓		
2560x1600		VXX: *****=VXX: *****=2560: 1600: *, ****		*****=*****=2560: 1600: *, ****	✓	✓		
3840x2400	VXX: *****=VXX: *****=3840: 2400: *, ****		*****=*****=3840: 2400: *, ****	✓	✓			
* PARAMETER4	Progressive Interlace	VXX: *****=VXX: *****=*****: p		*****=*****=*****: p	✓	✓		
		VXX: *****=VXX: *****=*****: i		*****=*****=*****: i	✓	✓		
* PARAMETER5	60Hz	VXX: *****=VXX: *****=*****: *, 6000		*****=*****=*****: *, 6000	✓	✓		
	50Hz	VXX: *****=VXX: *****=*****: *, 5000		*****=*****=*****: *, 5000	✓	✓		
	48Hz	VXX: *****=VXX: *****=*****: *, 4800		*****=*****=*****: *, 4800	✓	✓		
	30Hz	VXX: *****=VXX: *****=*****: *, 3000		*****=*****=*****: *, 3000	✓	✓		
	25Hz	VXX: *****=VXX: *****=*****: *, 2500		*****=*****=*****: *, 2500	✓	✓		
24Hz	VXX: *****=VXX: *****=*****: *, 2400		*****=*****=*****: *, 2400	✓	✓			
SLOT : DisplayPort : EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER		VXX: *****=VXX: *****=*****	QVX: *****=QVX: *****	*****=*****=*****	✓	✓	
	* PARAMETER1, 2	DisplayPort1	VXX: SLSS1=VXX: ESPS1=*****: *, ****		SLSS1=ESPS1=*****: *, ****	✓	✓	
		DisplayPort2	VXX: SLSS1=VXX: ESPS2=*****: *, ****		SLSS1=ESPS2=*****: *, ****	✓	✓	
		DisplayPort3	VXX: SLSS2=VXX: ESPS1=*****: *, ****		SLSS2=ESPS1=*****: *, ****	✓	✓	
		DisplayPort4	VXX: SLSS2=VXX: ESPS2=*****: *, ****		SLSS2=ESPS2=*****: *, ****	✓	✓	
	* PARAMETER3	1024x768	VXX: *****=VXX: *****=1024: 0768: *, ****		*****=*****=1024: 0768: *, ****	✓	✓	
		1280x720	VXX: *****=VXX: *****=1280: 0720: *, ****		*****=*****=1280: 0720: *, ****	✓	✓	
		1280x800	VXX: *****=VXX: *****=1280: 0800: *, ****		*****=*****=1280: 0800: *, ****	✓	✓	
		1400x1050	VXX: *****=VXX: *****=1400: 1050: *, ****		*****=*****=1400: 1050: *, ****	✓	✓	
		1600x900	VXX: *****=VXX: *****=1600: 0900: *, ****		*****=*****=1600: 0900: *, ****	✓	✓	
		1600x1200	VXX: *****=VXX: *****=1600: 1200: *, ****		*****=*****=1600: 1200: *, ****	✓	✓	
		1920x1080	VXX: *****=VXX: *****=1920: 1080: *, ****		*****=*****=1920: 1080: *, ****	✓	✓	
1920x1200		VXX: *****=VXX: *****=1920: 1200: *, ****		*****=*****=1920: 1200: *, ****	✓	✓		
2048x1080		VXX: *****=VXX: *****=2048: 1080: *, ****		*****=*****=2048: 1080: *, ****	✓	✓		
2560x1600		VXX: *****=VXX: *****=2560: 1600: *, ****		*****=*****=2560: 1600: *, ****	✓	✓		
3840x2400	VXX: *****=VXX: *****=3840: 2400: *, ****		*****=*****=3840: 2400: *, ****	✓	✓			
* PARAMETER4	Progressive Interlace	VXX: *****=VXX: *****=*****: p		*****=*****=*****: p	✓	✓		
		VXX: *****=VXX: *****=*****: i		*****=*****=*****: i	✓	✓		
* PARAMETER5	60Hz	VXX: *****=VXX: *****=*****: *, 6000		*****=*****=*****: *, 6000	✓	✓		
	50Hz	VXX: *****=VXX: *****=*****: *, 5000		*****=*****=*****: *, 5000	✓	✓		
	48Hz	VXX: *****=VXX: *****=*****: *, 4800		*****=*****=*****: *, 4800	✓	✓		
	30Hz	VXX: *****=VXX: *****=*****: *, 3000		*****=*****=*****: *, 3000	✓	✓		
	25Hz	VXX: *****=VXX: *****=*****: *, 2500		*****=*****=*****: *, 2500	✓	✓		
24Hz	VXX: *****=VXX: *****=*****: *, 2400		*****=*****=*****: *, 2400	✓	✓			
SLOT : 12G SDI OPT : RESOLUTION	* PARAMETER		VXX: *****=VXX: *****=*****	QVX: *****=QVX: *****	*****=*****=*****	✓	✓	
	* PARAMETER1, 2	12G SDI OPT1	VXX: SLSS1=VXX: OREI 1=*****		SLSS1=OREI 1=*****	✓	✓	
		12G SDI OPT2	VXX: SLSS1=VXX: OREI 2=*****		SLSS1=OREI 2=*****	✓	✓	
		12G SDI OPT1	VXX: SLSS2=VXX: OREI 1=*****		SLSS2=OREI 1=*****	✓	✓	
		12G SDI OPT2	VXX: SLSS2=VXX: OREI 2=*****		SLSS2=OREI 2=*****	✓	✓	
	* PARAMETER3	AUTO	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓	✓	
		1280x720p	VXX: *****=VXX: *****=+00003		*****=*****=+00003	✓	✓	
		1920x1080i	VXX: *****=VXX: *****=+00005		*****=*****=+00005	✓	✓	
		1920x1080p	VXX: *****=VXX: *****=+00006		*****=*****=+00006	✓	✓	
		1920x1080sF	VXX: *****=VXX: *****=+00007		*****=*****=+00007	✓	✓	
		2048x1080p	VXX: *****=VXX: *****=+00009		*****=*****=+00009	✓	✓	
		3840x2160p	VXX: *****=VXX: *****=+00011		*****=*****=+00011	✓	✓	
4096x2160p		VXX: *****=VXX: *****=+00013		*****=*****=+00013	✓	✓		
* PARAMETER		VXX: *****=VXX: *****=*****	QVX: *****=QVX: *****	*****=*****=*****	✓	✓		
* PARAMETER1, 2	12G SDI OPT1	VXX: SLSS1=VXX: OGMI 1=*****		SLSS1=OGMI 1=*****	✓	✓		
	12G SDI OPT2	VXX: SLSS1=VXX: OGMI 2=*****		SLSS1=OGMI 2=*****	✓	✓		
	12G SDI OPT1	VXX: SLSS2=VXX: OGMI 1=*****		SLSS2=OGMI 1=*****	✓	✓		
	12G SDI OPT2	VXX: SLSS2=VXX: OGMI 2=*****		SLSS2=OGMI 2=*****	✓	✓		
* PARAMETER3	AUTO	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓	✓		
TYPE1 / LEVEL A	VXX: *****=VXX: *****=+00001		*****=*****=+00001	✓	✓			
TYPE2 / LEVEL B	VXX: *****=VXX: *****=+00002		*****=*****=+00002	✓	✓			
* PARAMETER		VXX: *****=VXX: *****=*****	QVX: *****=QVX: *****	*****=*****=*****	✓	✓		
SLOT : 12G SDI OPT : SYSTEM SELECTOR	* PARAMETER		VXX: *****=VXX: *****=*****	QVX: *****=QVX: *****	*****=*****=*****	✓	✓	
	* PARAMETER1, 2	12G SDI OPT1	VXX: SLSS1=VXX: OSYI 1=*****		SLSS1=OSYI 1=*****	✓	✓	
		12G SDI OPT2	VXX: SLSS1=VXX: OSYI 2=*****		SLSS1=OSYI 2=*****	✓	✓	
12G SDI OPT1		VXX: SLSS2=VXX: OSYI 1=*****		SLSS2=OSYI 1=*****	✓	✓		

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ35K SERIES	RZ34K SERIES	
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K SRQ35KC	RZ34K SRZ34KC	
CONTROL	* PARAMETER3	12G SDI OPT2		VXX: SLSS2=VXX: 0SYI 2=*****		SLSS2=0SYI 2=*****	✓		
		AUTO		VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓	✓	
		RGB		VXX: *****=VXX: *****=+00001		*****=*****=+00001	✓	✓	
		YPbPr 4:4:4		VXX: *****=VXX: *****=+00002		*****=*****=+00002	✓	✓	
	SLOT : 12G SDI OPT : BIT DEPTH	* PARAMETER	YPbPr 4:2:2		VXX: *****=VXX: *****=+00003		*****=*****=+00003	✓	✓
					VXX: *****=VXX: *****=*****	QVX: *****=QVX: *****	*****=*****=*****	✓	✓
			12G SDI OPT1		VXX: SLSS1=VXX: 0BTI 1=*****		SLSS1=0BTI 1=*****	✓	✓
			12G SDI OPT2		VXX: SLSS1=VXX: 0BTI 2=*****		SLSS1=0BTI 2=*****	✓	✓
	* PARAMETER1, 2	* PARAMETER	12G SDI OPT1		VXX: SLSS2=VXX: 0BTI 1=*****		SLSS2=0BTI 1=*****	✓	
			12G SDI OPT2		VXX: SLSS2=VXX: 0BTI 2=*****		SLSS2=0BTI 2=*****	✓	
			AUTO		VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓	✓
			12-bit		VXX: *****=VXX: *****=+00001		*****=*****=+00001	✓	✓
	SLOT : 12G SDI OPT : SIGNAL LEVEL	* PARAMETER	10-bit		VXX: *****=VXX: *****=+00002		*****=*****=+00002	✓	✓
					VXX: *****=VXX: *****=*****	QVX: *****=QVX: *****	*****=*****=*****	✓	✓
			12G SDI OPT1		VXX: SLSS1=VXX: 0SLI 1=*****		SLSS1=0SLI 1=*****	✓	✓
			12G SDI OPT2		VXX: SLSS1=VXX: 0SLI 2=*****		SLSS1=0SLI 2=*****	✓	✓
	* PARAMETER1, 2	* PARAMETER	12G SDI OPT1		VXX: SLSS2=VXX: 0SLI 1=*****		SLSS2=0SLI 1=*****	✓	
			12G SDI OPT2		VXX: SLSS2=VXX: 0SLI 2=*****		SLSS2=0SLI 2=*****	✓	
			64-940		VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓	✓
			4-1019		VXX: *****=VXX: *****=+00001		*****=*****=+00001	✓	✓
	SLOT : 12G SDI OPT : SDI OPT OUT	* PARAMETER			VXX: 00MS1=*, *: *****	QVX: 00MS1=*, *	00MS1=*, *: *****	✓	✓
			SLOT1		VXX: 00MS1=1: *, *****		00MS1=1: *, *****	✓	✓
			SLOT2		VXX: 00MS1=2: *, *****		00MS1=2: *, *****	✓	✓
			SFP2		VXX: 00MS1=*, 2: *****		00MS1=*, 2: *****	✓	✓
* PARAMETER3	DISABLE		VXX: 00MS1=*, *: 00000		00MS1=*, *: 00000	✓	✓		
	ENABLE		VXX: 00MS1=*, *: 00001		00MS1=*, *: 00001	✓	✓		
MULTI PROJECTOR SYNC - MODE	OFF		VXX: MPSI 1=+00000	QVX: MPSI 1	MPSI 1=+00000	✓	✓		
	MASTER		VXX: MPSI 1=+00001		MPSI 1=+00001	✓	✓		
FRAME SYNC SETTING(MULTI PROJECTOR SYNC) - CONTRAST	SLAVE		VXX: MPSI 1=+00002		MPSI 1=+00002	✓	✓		
	OFF		VXX: CSYI 1=+00000	QVX: CSYI 1	CSYI 1=+00000	✓	✓		
MULTI PROJECTOR SYNC - SHUTTER SYNC.	ON		VXX: CSYI 1=+00001		CSYI 1=+00001	✓	✓		
	OFF		VXX: SSYI 1=+00000	QVX: SSYI 1	SSYI 1=+00000	✓	✓		
INPUT GUIDE	ON		VXX: SSYI 1=+00001		SSYI 1=+00001	✓	✓		
	OFF		OID: 0	QDI	0	✓	✓		
OSD POSITION	ON (SIMPLE)		OID: 1		1	✓	✓		
	UPPER LEFT		ODP: 1	QDP	1	✓	✓		
	CETRE LEFT		ODP: 2		2	✓	✓		
	LOWER LEFT		ODP: 3		3	✓	✓		
	TOP CENTER		ODP: 4		4	✓	✓		
	CENTER		ODP: 5		5	✓	✓		
	LOEER CENTER		ODP: 6		6	✓	✓		
	UPPER RIGHT		ODP: 7		7	✓	✓		
	CENTER RIGHT		ODP: 8		8	✓	✓		
	LOWER RIGHT		ODP: 9		9	✓	✓		
OSD ROTATION	OFF		VXX: OSRI 1=+00000	QVX: OSRI 1	OSRI 1=+00000	✓	✓		
	CLOCKWISE		VXX: OSRI 1=+00001		OSRI 1=+00001	✓	✓		
	COUNTER CLOCKWISE		VXX: OSRI 1=+00002		OSRI 1=+00002	✓	✓		
OSD MEMORY	OFF		VXX: OMYI 0=+00000	QVX: OMYI 0	OMYI 0=+00000	✓	✓		
	ON		VXX: OMYI 0=+00001		OMYI 0=+00001	✓	✓		
ON SCREEN	OFF		OOS: 0	QOS	0	✓	✓		
	ON		OOS: 1		1	✓	✓		
WARNING MESSAGE	OFF		VXX: WMDI 0=+00000	QVX: WMDI 0	WMDI 0=+00000	✓	✓		
	ON		VXX: WMDI 0=+00001		WMDI 0=+00001	✓	✓		
OSD DESIGN	1(YELLOW)		MOD: 0	QOD	0	✓	✓		
	2(BLUE)		MOD: 1		1	✓	✓		
	3(WHITE)		MOD: 2		2	✓	✓		
	4(GREEN)		MOD: 3		3	✓	✓		
	5(PEACH)		MOD: 4		4	✓	✓		
	6(BROWN)		MOD: 5		5	✓	✓		
MENU MODE	NORMAL		VXX: MMDI 1=+00000	QVX: MMDI 1	MMDI 1=+00000	✓	✓		
	SIMPLE		VXX: MMDI 1=+00001		MMDI 1=+00001	✓	✓		
SCREEN SETTING	16:10		VSF: 0	QSF	0	✓	✓		
	16:9		VSF: 1		1	✓	✓		
	4:3		VSF: 2		2	✓	✓		
SCREEN POSITION-VERTICAL	min.		VXX: VSPI 0=- 00120	QVX: VSPI 0	VSPI 0=- 00120	-120	-60		
	max.		VXX: VSPI 0=+00120		VSPI 0=+00120	120	60		
SCREEN POSITION-HORZONTAL	min.		VXX: HSPI 0=- 00320	QVX: HSPI 0	HSPI 0=- 00320	-320	-160		
	max.		VXX: HSPI 0=+00320		HSPI 0=+00320	320	160		
SCREEN MARKER	OFF		VXX: SSMI 1=+00000	QVX: SSMI 1	SSMI 1=+00000	✓	✓		
	ON		VXX: SSMI 1=+00001		SSMI 1=+00001	✓	✓		
SCREEN MARKER - UPPER	min.		VXX: SCMI 1=+00000	QVX: SCMI 1	SCMI 1=+00000	0	0		
	max.		VXX: SCMI 1=+02399		SCMI 1=+02399	2399	1199		
SCREEN MARKER - LOWER	min.		VXX: SCMI 2=+00000	QVX: SCMI 2	SCMI 2=+00000	0	0		
	max.		VXX: SCMI 2=+02399		SCMI 2=+02399	2399	1199		
SCREEN MARKER - LEFT	min.		VXX: SCMI 3=+00000	QVX: SCMI 3	SCMI 3=+00000	0	0		
	max.		VXX: SCMI 3=+03839		SCMI 3=+03839	3839	1919		
SCREEN MARKER - RIGHT	min.		VXX: SCMI 4=+00000	QVX: SCMI 4	SCMI 4=+00000	0	0		
	max.		VXX: SCMI 4=+03839		SCMI 4=+03839	3839	1919		
STARTUP LOGO	OFF		ML0: 0	QLO	0	✓	✓		
	USER LOGO		ML0: 1		1	✓	✓		
	DEFAULT LOGO		ML0: 2		2	✓	✓		
UNIFORMITY-FLEXIBLE CORRECTION *	OFF		VXX: UFMI 1=+00000	QVX: UFMI 1	UFMI 1=+00000	✓	✓		
	ON(PRE)		VXX: UFMI 1=+00011		UFMI 1=+00011	✓	✓		
	ON(POST)		VXX: UFMI 1=+00021		UFMI 1=+00021	✓	✓		
UNIFORMITY-INITILIZE	EXECUTE		VXX: UFMI 2=+00001		UFMI 2=+00001	✓	✓		
	CHROMA ONLY		VXX: UFMI 3=+00001	QVX: UFMI 3	UFMI 3=+00001	✓	✓		
UNIFORMITY-MODE	LUMINACE/CHROMA		VXX: UFMI 3=+00011		UFMI 3=+00011	✓	✓		
	* PARAMETER		ESW: *, ***, ****	ESR: *	*, ***, ****	✓	✓		
UNIFORMITY-WHITE/RED/GREEN/RED	* PARAMETER 1	WHITE		ESW: W, ***, ****	ESR: W	*, ***, ****	✓	✓	
		RED		ESW: R, ***, ****	ESR: R	*, ***, ****	✓	✓	
		GREEN		ESW: G, ***, ****	ESR: G	*, ***, ****	✓	✓	
		BLUE		ESW: B, ***, ****	ESR: B	*, ***, ****	✓	✓	
	* PARAMETER 2	VERTICAL(-127)		ESW: *, - 127, ****		*, - 127, ****	✓	✓	
		VERTICAL(+127)		ESW: *, +127, ****		*, +127, ****	✓	✓	
	* PARAMETER 3	HORIZONTAL(-127)		ESW: *, ***, - 127		*, ***, - 127	✓	✓	
		HORZONTAL(+127)		ESW: *, ***, +127		*, ***, +127	✓	✓	
		L1(ON)				1*, ***, ****	✓	✓	
		L2(OFF)				*0, ***, ****	✓	✓	
SHUTTER SETTING-FADE IN	0.0s(OFF)		VXX: SEFS1=0. 0	QVX: SEFS1	SEFS1=0. 0	✓	✓		
	0.5s		VXX: SEFS1=0. 5		SEFS1=0. 5	✓	✓		
	1.0s		VXX: SEFS1=1. 0		SEFS1=1. 0	✓	✓		
	1.5s		VXX: SEFS1=1. 5		SEFS1=1. 5	✓	✓		
	2.0s		VXX: SEFS1=2. 0		SEFS1=2. 0	✓	✓		
	2.5s		VXX: SEFS1=2. 5		SEFS1=2. 5	✓	✓		
	3.0s		VXX: SEFS1=3. 0		SEFS1=3. 0	✓	✓		
	3.5s		VXX: SEFS1=3. 5		SEFS1=3. 5	✓	✓		
	4.0s		VXX: SEFS1=4. 0		SEFS1=4. 0	✓	✓		
	5.0s		VXX: SEFS1=5. 0		SEFS1=5. 0	✓	✓		
	7.0s		VXX: SEFS1=7. 0		SEFS1=7. 0	✓	✓		
	10.0s		VXX: SEFS1=10. 0		SEFS1=10. 0	✓	✓		
SHUTTER SETTING-FADE OUT	0.0s(OFF)		VXX: SEFS2=0. 0	QVX: SEFS2	SEFS2=0. 0	✓	✓		
	0.5s		VXX: SEFS2=0. 5		SEFS2=0. 5	✓	✓		
	1.0s		VXX: SEFS2=1. 0		SEFS2=1. 0	✓	✓		
	1.5s		VXX: SEFS2=1. 5		SEFS2=1. 5	✓	✓		
	2.0s		VXX: SEFS2=2. 0		SEFS2=2. 0	✓	✓		
	2.5s		VXX: SEFS2=2. 5		SEFS2=2. 5	✓	✓		
	3.0s		VXX: SEFS2=3. 0		SEFS2=3. 0	✓	✓		
	3.5s		VXX: SEFS2=3. 5		SEFS2=3. 5	✓	✓		
	4.0s		VXX: SEFS2=4. 0		SEFS2=4. 0	✓	✓		
	5.0s		VXX: SEFS2=5. 0		SEFS2=5. 0	✓	✓		
	7.0s		VXX: SEFS2=7. 0		SEFS2=7. 0	✓	✓		

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		RQ35K SERIES	RZ34K SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K SRQ35KC	RZ34K SRZ34KC	
CONTROL	SHUTTER SETTING	10.0s		VXX: SEFS2=10.0		SEFS2=10.0		✓	✓
	DISABLE			VXX: SEFI 5=+00000	QVX: SEFI 5	SEFS5=+00000		✓	✓
	-MECHANICAL SHUTTER	ENABLE		VXX: SEFI 5=+00001		SEFS5=+00001		✓	✓
	SHUTTER SETTING-STARTUP	OPEN		VXX: SEFI 3=+00000	QVX: SEFI 3	SEFI 3=+00000		✓	✓
		CLOSE		VXX: SEFI 3=+00001		SEFI 3=+00001		✓	✓
	SHUTTER SETTING-SHUT OFF	OPEN		VXX: SEFI 4=+00000	QVX: SEFI 4	SEFI 4=+00000		✓	✓
		CLOSE		VXX: SEFI 4=+00001		SEFI 4=+00001		✓	✓
		KEEP CURRENT STATE		VXX: SEFI 4=+00002		SEFI 4=+00002		✓	✓
	BACK COLOR	BLUE		OBC: 0	QBC	0		✓	✓
		BLACK		OBC: 1		1		✓	✓
		USER LOGO		OBC: 2		2		✓	✓
		DEFAULT LOGO		OBC: 3		3		✓	✓
	WAVEFORM MONITOR	OFF		OWM: 0	QWM	0		✓	✓
		LUMINANCE		OWM: 5		5		✓	✓
		RED		OWM: 6		6		✓	✓
		GREEN		OWM: 7		7		✓	✓
		BLUE		OWM: 8		8		✓	✓
	WAVEFORM MONITOR-LINE ADJ.	0		VXX: WMLI 0=+00000	QVX: WMLI 0	WMLI 0=+00000		✓	✓
		+2159		VXX: WMLI 0=+02159		WMLI 0=+02159		✓	✓
	AC VOLTAGE				QVX: VMOI 2	VMOI 2=+00000		✓	✓
						VMOI 2=+99999		✓	✓
	CUT OFF-RED	OFF		VXX: CUTI 1=+00000	QVX: CUTI 1	CUTI 1=+00000		✓	✓
		ON		VXX: CUTI 1=+00001		CUTI 1=+00001		✓	✓
	CUT OFF-GREEN	OFF		VXX: CUTI 2=+00000	QVX: CUTI 2	CUTI 2=+00000		✓	✓
		ON		VXX: CUTI 2=+00001		CUTI 2=+00001		✓	✓
	CUT OFF-BLUE	OFF		VXX: CUTI 3=+00000	QVX: CUTI 3	CUTI 3=+00000		✓	✓
		ON		VXX: CUTI 3=+00001		CUTI 3=+00001		✓	✓
PROJECTOR ID	0(ALL)		RIS: 00				✓	✓	
	64		RIS: 64				✓	✓	
ID ALL	OFF		RVS: 0	QVY	0		✓	✓	
	ON		RVS: 1		1		✓	✓	
PROJECTION METHOD	FRONT/DESK		OIL: 0	QSP	0		✓	✓	
INSTALLATION	REAR/DESK		OIL: 1		1		✓	✓	
	FRONT/CEILING		OIL: 2		2		✓	✓	
	REAR/CEILING		OIL: 3		3		✓	✓	
	FRONT/AUTO		OIL: 4		4		✓	✓	
	REAR/AUTO		OIL: 5		5		✓	✓	
AUTO COOLING CONDITION-STATUS	FLOOR			QVX: ADRI 1	ADRI 1=+00000		✓	✓	
	CEILING				ADRI 1=+00001		✓	✓	
	VERTICAL UP				ADRI 1=+00002		✓	✓	
	VERTICAL DOWN				ADRI 1=+00003		✓	✓	
	PORTRAIT				ADRI 1=+00004		✓	✓	
OPERATING MODE	NORMAL		VXX: OPEI 1=+00000	QVX: OPEI 1	OPEI 1=+00000		✓	✓	
	ECO		VXX: OPEI 1=+00001		OPEI 1=+00001		✓	✓	
	QUIET1(QUIET)		VXX: OPEI 1=+00021		OPEI 1=+00021		✓	✓	
	USER1(USER)		VXX: OPEI 1=+00101		OPEI 1=+00101		✓	✓	
	USER2		VXX: OPEI 1=+00102		OPEI 1=+00102		✓	✓	
	USER3		VXX: OPEI 1=+00103		OPEI 1=+00103		✓	✓	
LIGHT OUTPUT	min.		VXX: LOPI 2=+00050	QVX: LOPI 2	LOPI 2=+00050	8%	8%		
	max.		VXX: LOPI 2=+01000		LOPI 2=+01000	100%	100%		
MAX LIGHT OUTPUT	min.		VXX: LOPI 3=+00050	QVX: LOPI 3	LOPI 3=+00050	8%	8%		
	max.		VXX: LOPI 3=+01000		LOPI 3=+01000	100%	100%		
BRIGHTNESS CONTROL-SETUP-CONSTANT MODE	OFF		VXX: BCMI 0=+00000	QVX: BCMI 0	BCMI 0=+00000		✓	✓	
	AUTO		VXX: BCMI 0=+00001		BCMI 0=+00001		✓	✓	
	PC		VXX: BCMI 0=+00002		BCMI 0=+00002		✓	✓	
BRIGHTNESS CONTROL-SETUP-LINK	OFF		VXX: BCLI 0=+00000	QVX: BCLI 0	BCLI 0=+00000		✓	✓	
	GROUP A		VXX: BCLI 0=+00001		BCLI 0=+00001		✓	✓	
	GROUP B		VXX: BCLI 0=+00002		BCLI 0=+00002		✓	✓	
	GROUP C		VXX: BCLI 0=+00003		BCLI 0=+00003		✓	✓	
	GROUP D		VXX: BCLI 0=+00004		BCLI 0=+00004		✓	✓	
BRIGHTNESS CONTROL-SETUP APPLY SCHEDULE	APPLY		VXX: BCSI 0=+00001				✓	✓	
	OFF		VXX: SCHI 0=+00000	QVX: SCHI 0	SCHI 0=+00000		✓	✓	
	ON		VXX: SCHI 0=+00001		SCHI 0=+00001		✓	✓	
SCHEDULE-PROGRAM ASSIGN	OFF		VXX: SPGI *=+00000	QVX: SPGI *	SPGI *=+00000		✓	✓	
	PROGRAM1		VXX: SPGI *=+00001		SPGI *=+00001		✓	✓	
	PROGRAM2		VXX: SPGI *=+00002		SPGI *=+00002		✓	✓	
	PROGRAM3		VXX: SPGI *=+00003		SPGI *=+00003		✓	✓	
	PROGRAM4		VXX: SPGI *=+00004		SPGI *=+00004		✓	✓	
	PROGRAM5		VXX: SPGI *=+00005		SPGI *=+00005		✓	✓	
	PROGRAM6		VXX: SPGI *=+00006		SPGI *=+00006		✓	✓	
	PROGRAM7		VXX: SPGI *=+00007		SPGI *=+00007		✓	✓	
	* PARAMETER	SUN	VXX: SPGI 0=+0000*	QVX: SPGI 0	SPGI 0=+0000*		✓	✓	
		MON	VXX: SPGI 1=+0000*	QVX: SPGI 1	SPGI 1=+0000*		✓	✓	
		TUE	VXX: SPGI 2=+0000*	QVX: SPGI 2	SPGI 2=+0000*		✓	✓	
		WED	VXX: SPGI 3=+0000*	QVX: SPGI 3	SPGI 3=+0000*		✓	✓	
		THU	VXX: SPGI 4=+0000*	QVX: SPGI 4	SPGI 4=+0000*		✓	✓	
		FRI	VXX: SPGI 5=+0000*	QVX: SPGI 5	SPGI 5=+0000*		✓	✓	
		SAT	VXX: SPGI 6=+0000*	QVX: SPGI 6	SPGI 6=+0000*		✓	✓	
SCHEDULE-COMMAND SETTING	COMMAND Del		VXX: SCCS *=**00****	QVX: SCCS *=**	SCCS *=**00****		✓	✓	
	STANDBY		VXX: SCCS *=**10****		SCCS *=**10****		✓	✓	
	POWER ON		VXX: SCCS *=**11****		SCCS *=**11****		✓	✓	
	SHUTTER OPEN		VXX: SCCS *=**20****		SCCS *=**20****		✓	✓	
	SHUTTER CLOSE		VXX: SCCS *=**21****		SCCS *=**21****		✓	✓	
	DVI-D INPUT		VXX: SCCS *=**51****		SCCS *=**51****		✓	✓	
	SDI1 INPUT		VXX: SCCS *=**52****		SCCS *=**52****		✓	✓	
	HDMI1 INPUT		VXX: SCCS *=**53****		SCCS *=**53****		✓	✓	
	SLOT1-1 INPUT		VXX: SCCS *=**68****		SCCS *=**68****		✓	✓	
	SLOT1-2 INPUT		VXX: SCCS *=**69****		SCCS *=**69****		✓	✓	
	SLOT2-3 INPUT		VXX: SCCS *=**6A****		SCCS *=**6A****		✓	✓	
	SLOT2-4 INPUT		VXX: SCCS *=**6B****		SCCS *=**6B****		✓	✓	
	SLOT1-3 INPUT		VXX: SCCS *=**6C****		SCCS *=**6C****		✓	✓	
	SLOT1-4 INPUT		VXX: SCCS *=**6D****		SCCS *=**6D****		✓	✓	
	SLOT2-1 INPUT		VXX: SCCS *=**6E****		SCCS *=**6E****		✓	✓	
	SLOT2-2 INPUT		VXX: SCCS *=**6F****		SCCS *=**6F****		✓	✓	
	NORMAL		VXX: SCCS *=**70****		SCCS *=**70****		✓	✓	
	ECO		VXX: SCCS *=**71****		SCCS *=**71****		✓	✓	
	USER1(USER)		VXX: SCCS *=**75****		SCCS *=**75****		✓	✓	
	USER2		VXX: SCCS *=**76****		SCCS *=**76****		✓	✓	
	USER3		VXX: SCCS *=**77****		SCCS *=**77****		✓	✓	
	SILENT1(QUIET1/QUIET)		VXX: SCCS *=**7A****		SCCS *=**7A****		✓	✓	
	DIGITAL LINK		VXX: SCCS *=**B0****		SCCS *=**B0****		✓	✓	
	INPUT 1		VXX: SCCS *=**B1****		SCCS *=**B1****		✓	✓	
	INPUT 2		VXX: SCCS *=**B2****		SCCS *=**B2****		✓	✓	
	INPUT 3		VXX: SCCS *=**B3****		SCCS *=**B3****		✓	✓	
	INPUT 4		VXX: SCCS *=**B4****		SCCS *=**B4****		✓	✓	
	INPUT 5		VXX: SCCS *=**B5****		SCCS *=**B5****		✓	✓	
	INPUT 6		VXX: SCCS *=**B6****		SCCS *=**B6****		✓	✓	
	INPUT 7		VXX: SCCS *=**B7****		SCCS *=**B7****		✓	✓	
	INPUT 8		VXX: SCCS *=**B8****		SCCS *=**B8****		✓	✓	
	INPUT 9		VXX: SCCS *=**B9****		SCCS *=**B9****		✓	✓	
	INPUT 10		VXX: SCCS *=**BA****		SCCS *=**BA****		✓	✓	
	* PARAMETER1	PROGRAM1	VXX: SCCS1=*****	QVX: SCCS1=**	SCCS1=*****		✓	✓	
		PROGRAM2	VXX: SCCS2=*****	QVX: SCCS2=**	SCCS2=*****		✓	✓	
		PROGRAM3	VXX: SCCS3=*****	QVX: SCCS3=**	SCCS3=*****		✓	✓	
		PROGRAM4	VXX: SCCS4=*****	QVX: SCCS4=**	SCCS4=*****		✓	✓	
		PROGRAM5	VXX: SCCS5=*****	QVX: SCCS5=**	SCCS5=*****		✓	✓	
		PROGRAM6	VXX: SCCS6=*****	QVX: SCCS6=**	SCCS6=*****		✓	✓	
		PROGRAM7	VXX: SCCS7=*****	QVX: SCCS7=**	SCCS7=*****		✓	✓	
	* PARAMETER2	COMMAND 1	VXX: SCCS*=01*****	QVX: SCCS*=01	SCCS*=01*****		✓	✓	
		COMMAND 16	VXX: SCCS*=16*****	QVX: SCCS*=16	SCCS*=16*****		✓	✓	
	* PARAMETER3	00:00	VXX: SCCS*=***0000		SCCS*=***0000		✓	✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY	RQ35K SERIES	RZ34K SERIES	
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K SRQ35KC	RZ34K SRZ34KC
PROJECTOR SETUP	STARTUP INPUT SELECT	* PARAMETER	23:59	VXX: SCCS*=***2359		SCCS*=***2359	✓	✓
		DVI-D		VXX: S1SS1=DVI	QVX: S1SS1	S1SS1=DVI	✓	✓
		HDMI1		VXX: S1SS1=HD1		S1SS1=HD1	✓	✓
		DIGITAL LINK		VXX: S1SS1=DL1		S1SS1=DL1	✓	✓
		SDI1		VXX: S1SS1=SD1		S1SS1=SD1	✓	✓
		SLOT1 : SDI1		VXX: S1SS1=AU1, SD1		S1SS1=AU1, SD1	✓	✓
		SLOT1 : SDI2		VXX: S1SS1=AU1, SD2		S1SS1=AU1, SD2	✓	✓
		SLOT1 : SDI3		VXX: S1SS1=AU1, SD3		S1SS1=AU1, SD3	✓	✓
		SLOT1 : SDI4		VXX: S1SS1=AU1, SD4		S1SS1=AU1, SD4	✓	✓
		SLOT2 : SDI1		VXX: S1SS1=AU2, SD1		S1SS1=AU2, SD1	✓	✓
		SLOT2 : SDI2		VXX: S1SS1=AU2, SD2		S1SS1=AU2, SD2	✓	✓
		SLOT2 : SDI3		VXX: S1SS1=AU2, SD3		S1SS1=AU2, SD3	✓	✓
		SLOT2 : SDI4		VXX: S1SS1=AU2, SD4		S1SS1=AU2, SD4	✓	✓
		SLOT1 : HDMI1		VXX: S1SS1=AU1, HD1		S1SS1=AU1, HD1	✓	✓
		SLOT1 : HDMI2		VXX: S1SS1=AU1, HD2		S1SS1=AU1, HD2	✓	✓
		SLOT2 : HDMI3		VXX: S1SS1=AU2, HD3		S1SS1=AU2, HD3	✓	✓
		SLOT2 : HDMI4		VXX: S1SS1=AU2, HD4		S1SS1=AU2, HD4	✓	✓
		SLOT1 : DVI1		VXX: S1SS1=AU1, DV1		S1SS1=AU1, DV1	✓	✓
		SLOT1 : DVI2		VXX: S1SS1=AU1, DV2		S1SS1=AU1, DV2	✓	✓
		SLOT2 : DVI3		VXX: S1SS1=AU2, DV3		S1SS1=AU2, DV3	✓	✓
		SLOT2 : DVI4		VXX: S1SS1=AU2, DV4		S1SS1=AU2, DV4	✓	✓
		SLOT1 : DisplayPort1		VXX: S1SS1=AU1, DP1		S1SS1=AU1, DP1	✓	✓
		SLOT1 : DisplayPort2		VXX: S1SS1=AU1, DP2		S1SS1=AU1, DP2	✓	✓
		SLOT2 : DisplayPort3		VXX: S1SS1=AU2, DP3		S1SS1=AU2, DP3	✓	✓
		SLOT2 : DisplayPort4		VXX: S1SS1=AU2, DP4		S1SS1=AU2, DP4	✓	✓
		SLOT1 : 12G SDI OPT1		VXX: S1SS1=AU1, OP1		S1SS1=AU1, OP1	✓	✓
		SLOT1 : 12G SDI OPT2		VXX: S1SS1=AU1, OP2		S1SS1=AU1, OP2	✓	✓
		SLOT2 : 12G SDI OPT1		VXX: S1SS1=AU2, OP1		S1SS1=AU2, OP1	✓	✓
	SLOT2 : 12G SDI OPT2		VXX: S1SS1=AU2, OP2		S1SS1=AU2, OP2	✓	✓	
	LAST USED		VXX: S1SS1=LSU		S1SS1=LSU	✓	✓	
	STARTUP INPUT SELECT (DIGITAL LINK)	LAST USED		VXX: S1SI2=+00000	QVX: S1SI2	S1SI2=+00000	✓	✓
		INPUT1		VXX: S1SI2=+00001		S1SI2=+00001	✓	✓
		INPUT2		VXX: S1SI2=+00002		S1SI2=+00002	✓	✓
		INPUT3		VXX: S1SI2=+00003		S1SI2=+00003	✓	✓
		INPUT4		VXX: S1SI2=+00004		S1SI2=+00004	✓	✓
		INPUT5		VXX: S1SI2=+00005		S1SI2=+00005	✓	✓
		INPUT6		VXX: S1SI2=+00006		S1SI2=+00006	✓	✓
		INPUT7		VXX: S1SI2=+00007		S1SI2=+00007	✓	✓
		INPUT8		VXX: S1SI2=+00008		S1SI2=+00008	✓	✓
		INPUT9		VXX: S1SI2=+00009		S1SI2=+00009	✓	✓
	NO SIGNAL SHUT-OFF	DISABLE		OAF: 00	QAF	00	✓	✓
		10min		OAF: 10		10	✓	✓
		20min		OAF: 20		20	✓	✓
		30min		OAF: 30		30	✓	✓
		40min		OAF: 40		40	✓	✓
		50min		OAF: 50		50	✓	✓
		60min		OAF: 60		60	✓	✓
		70min		OAF: 70		70	✓	✓
		80min		OAF: 80		80	✓	✓
		90min		ODR: 90		90	✓	✓
	NO SIGNAL LIGHTS-OUT	DISABLE		VXX: SLOI1=+00000	QVX: SLOI1	SLOI1=+00000	✓	✓
		10SEC.		VXX: SLOI1=+00010		SLOI1=+00010	✓	✓
		20SEC.		VXX: SLOI1=+00020		SLOI1=+00020	✓	✓
		30SEC.		VXX: SLOI1=+00030		SLOI1=+00030	✓	✓
		1MIN.		VXX: SLOI1=+00060		SLOI1=+00060	✓	✓
		2MIN.		VXX: SLOI1=+00120		SLOI1=+00120	✓	✓
		3MIN.		VXX: SLOI1=+00180		SLOI1=+00180	✓	✓
		5MIN.		VXX: SLOI1=+00300		SLOI1=+00300	✓	✓
	NO SIGNAL SETTING - SECONDARY INPUT	OFF		VXX: S1NS1=OFF	QVX: S1NS1	S1NS1=OFF	✓	✓
		DVI		VXX: S1NS1=DVI		S1NS1=DVI	✓	✓
		HDMI1		VXX: S1NS1=HD1		S1NS1=HD1	✓	✓
		SDI		VXX: S1NS1=SDI		S1NS1=SDI	✓	✓
		SDI1		VXX: S1NS1=SD1		S1NS1=SD1	✓	✓
		DIGITAL LINK		VXX: S1NS1=DL1		S1NS1=DL1	✓	✓
		SLOT1 : SDI1		VXX: S1NS1=AU1, SD1		S1NS1=AU1, SD1	✓	✓
		SLOT1 : SDI2		VXX: S1NS1=AU1, SD2		S1NS1=AU1, SD2	✓	✓
		SLOT1 : SDI3		VXX: S1NS1=AU1, SD3		S1NS1=AU1, SD3	✓	✓
		SLOT1 : SDI4		VXX: S1NS1=AU1, SD4		S1NS1=AU1, SD4	✓	✓
		SLOT2 : SDI1		VXX: S1NS1=AU2, SD1		S1NS1=AU2, SD1	✓	✓
		SLOT2 : SDI2		VXX: S1NS1=AU2, SD2		S1NS1=AU2, SD2	✓	✓
		SLOT2 : SDI3		VXX: S1NS1=AU2, SD3		S1NS1=AU2, SD3	✓	✓
		SLOT2 : SDI4		VXX: S1NS1=AU2, SD4		S1NS1=AU2, SD4	✓	✓
		SLOT1 : HDMI1		VXX: S1NS1=AU1, HD1		S1NS1=AU1, HD1	✓	✓
		SLOT1 : HDMI2		VXX: S1NS1=AU1, HD2		S1NS1=AU1, HD2	✓	✓
		SLOT2 : HDMI3		VXX: S1NS1=AU2, HD3		S1NS1=AU2, HD3	✓	✓
		SLOT2 : HDMI4		VXX: S1NS1=AU2, HD4		S1NS1=AU2, HD4	✓	✓
		SLOT1 : DVI-D1		VXX: S1NS1=AU1, DV1		S1NS1=AU1, DV1	✓	✓
		SLOT1 : DVI-D2		VXX: S1NS1=AU1, DV2		S1NS1=AU1, DV2	✓	✓
		SLOT2 : DVI-D3		VXX: S1NS1=AU2, DV3		S1NS1=AU2, DV3	✓	✓
		SLOT2 : DVI-D4		VXX: S1NS1=AU2, DV4		S1NS1=AU2, DV4	✓	✓
		SLOT1 : DisplayPort1		VXX: S1NS1=AU1, DP1		S1NS1=AU1, DP1	✓	✓
		SLOT1 : DisplayPort2		VXX: S1NS1=AU1, DP2		S1NS1=AU1, DP2	✓	✓
		SLOT2 : DisplayPort3		VXX: S1NS1=AU2, DP3		S1NS1=AU2, DP3	✓	✓
		SLOT2 : DisplayPort4		VXX: S1NS1=AU2, DP4		S1NS1=AU2, DP4	✓	✓
		SLOT1 : 12G SDI OPT1		VXX: S1NS1=AU1, OP1		S1NS1=AU1, OP1	✓	✓
		SLOT1 : 12G SDI OPT2		VXX: S1NS1=AU1, OP2		S1NS1=AU1, OP2	✓	✓
		SLOT2 : 12G SDI OPT1		VXX: S1NS1=AU2, OP1		S1NS1=AU2, OP1	✓	✓
		SLOT2 : 12G SDI OPT2		VXX: S1NS1=AU2, OP2		S1NS1=AU2, OP2	✓	✓
	REMOTE2 - MODE	DEFAULT		VXX: RMPIO=+00000	QVX: RMPIO	RMPIO=+00000	✓	✓
		USER		VXX: RMPIO=+00001		RMPIO=+00001	✓	✓
	REMOTE2 - PIN2	NONE		VXX: RMPS1=P2<NONE	QVX: RMPS1=P2	RMPS1=P2<NONE	✓	✓
		POWER		VXX: RMPS1=P2<POWER		RMPS1=P2<POWER	✓	✓
	REMOTE2 - PIN3 - 7	* PARAMETER		VXX: RMPS1=P*<*****	QVX: RMPS1=P*		✓	✓
		* PARAMETER1	PIN3	VXX: RMPS1=P3<*****		RMPS1=P3<*****	✓	✓
			PIN4	VXX: RMPS1=P4<*****		RMPS1=P4<*****	✓	✓
			PIN5	VXX: RMPS1=P5<*****		RMPS1=P5<*****	✓	✓
			PIN6	VXX: RMPS1=P6<*****		RMPS1=P6<*****	✓	✓
			PIN7	VXX: RMPS1=P7<*****		RMPS1=P7<*****	✓	✓
			NONE	VXX: RMPS1=P*<NONE		RMPS1=P*<NONE	✓	✓
			DVI	VXX: RMPS1=P*<DVI		RMPS1=P*<DVI	✓	✓
		HDMI	VXX: RMPS1=P*<HDMI		RMPS1=P*<HDMI	✓	✓	
		HDMI1	VXX: RMPS1=P*<HDMI 1		RMPS1=P*<HDMI 1	✓	✓	
		SDI1	VXX: RMPS1=P*<SDI		RMPS1=P*<SDI	✓	✓	
		DIGITAL LINK	VXX: RMPS1=P*<DLINK		RMPS1=P*<DLINK	✓	✓	
		SLOT1 : SDI1	VXX: RMPS1=P*<AU1, SD1		RMPS1=P*<AU1, SD1	✓	✓	
		SLOT1 : SDI2	VXX: RMPS1=P*<AU1, SD2		RMPS1=P*<AU1, SD2	✓	✓	
		SLOT1 : SDI3	VXX: RMPS1=P*<AU1, SD3		RMPS1=P*<AU1, SD3	✓	✓	
		SLOT1 : SDI4	VXX: RMPS1=P*<AU1, SD4		RMPS1=P*<AU1, SD4	✓	✓	
		SLOT2 : SDI1	VXX: RMPS1=P*<AU2, SD1		RMPS1=P*<AU2, SD1	✓	✓	
		SLOT2 : SDI2	VXX: RMPS1=P*<AU2, SD2		RMPS1=P*<AU2, SD2	✓	✓	
		SLOT2 : SDI3	VXX: RMPS1=P*<AU2, SD3		RMPS1=P*<AU2, SD3	✓	✓	
		SLOT2 : SDI4	VXX: RMPS1=P*<AU2, SD4		RMPS1=P*<AU2, SD4	✓	✓	
	SLOT1 : HDMI1	VXX: RMPS1=P*<AU1, HD1		RMPS1=P*<AU1, HD1	✓	✓		
	SLOT1 : HDMI2	VXX: RMPS1=P*<AU1, HD2		RMPS1=P*<AU1, HD2	✓	✓		
	SLOT2 : HDMI3	VXX: RMPS1=P*<AU2, HD3		RMPS1=P*<AU2, HD3	✓	✓		
	SLOT2 : HDMI4	VXX: RMPS1=P*<AU2, HD4		RMPS1=P*<AU2, HD4	✓	✓		
	SLOT1 : DVI1	VXX: RMPS1=P*<AU1, DV1		RMPS1=P*<AU1, DV1	✓	✓		
	SLOT1 : DVI2	VXX: RMPS1=P*<AU1, DV2		RMPS1=P*<AU1, DV2	✓	✓		
	SLOT2 : DVI3	VXX: RMPS1=P*<AU2, DV3		RMPS1=P*<AU2, DV3	✓	✓		
	SLOT2 : DVI4	VXX: RMPS1=P*<AU2, DV4		RMPS1=P*<AU2, DV4	✓	✓		

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ35K SERIES	RZ34K SERIES		
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K SRQ35KC	RZ34K SRZ34KC		
			SLOT1 : DisplayPort1	VXX: RMPS1=P*<AU1, DP1		RMPS1=P*<AU1, DP1	✓	✓		
			SLOT1 : DisplayPort2	VXX: RMPS1=P*<AU1, DP2		RMPS1=P*<AU1, DP2	✓	✓		
			SLOT2 : DisplayPort3	VXX: RMPS1=P*<AU2, DP3		RMPS1=P*<AU2, DP3	✓	✓		
			SLOT2 : DisplayPort4	VXX: RMPS1=P*<AU2, DP4		RMPS1=P*<AU2, DP4	✓	✓		
			SLOT1 : 12G SDI OPT1	VXX: RMPS1=P*<AU1, OP1		RMPS1=P*<AU1, OP1	✓	✓		
			SLOT1 : 12G SDI OPT2	VXX: RMPS1=P*<AU1, OP2		RMPS1=P*<AU1, OP2	✓	✓		
			SLOT2 : 12G SDI OPT1	VXX: RMPS1=P*<AU2, OP1		RMPS1=P*<AU2, OP1	✓	✓		
			SLOT2 : 12G SDI OPT2	VXX: RMPS1=P*<AU2, OP2		RMPS1=P*<AU2, OP2	✓	✓		
			REMOTE2 - PIN8	NONE	NONE	VXX: RMPS1=P8<NONE	QVX: RMPS1=P8	RMPS1=P8<NONE	✓	✓
				SHUTTER	SHUTTER	VXX: RMPS1=P8<SHUTTER		RMPS1=P8<SHUTTER	✓	✓
FUNCTION BUTTON			DISABLE	OFC: 0	QFC	0	✓	✓		
			SYSTEM SELECTOR	OFC: 1		1	✓	✓		
			SYSTEM DAYLIGHT VIEW	OFC: 2		2	✓	✓		
			SUB MEMORY	OFC: 3		3	✓	✓		
			FREEZE	OFC: 4		4	✓	✓		
			WAVEFORM MONITOR	OFC: 6		6	✓	✓		
			LENS MEMORY LOAD	OFC: 7		7	✓	✓		
			LEFT/RIGHT SWAP	OFC: 8		8	✓	✓		
			PROJECTION METHOD	OFC: 10		10	✓	✓		
			GEOMETRY	OFC: 13		13	✓	✓		
			OSD POSITION	OFC: 14		14	✓	✓		
			DATE AND TIME-DATE SETTING	Year: yyyy		TSD: 201506151	QGD	201506161	✓	✓
				Month: mm		TSD: <i>yyyymmddw</i>		<i>yyyymmddw</i>	✓	✓
				Date: dd					✓	✓
	Day:w(1~7:Mon~Sun)					✓	✓			
DATE AND TIME-TIME SETTING	Hour: hh		TST: 154503	QGT	154503	✓	✓			
	Minute: mm		TST: <i>hhmmss</i>		<i>hhmmss</i>	✓	✓			
	Second: ss					✓	✓			
DATE AND TIME-NTP SYNCHRONIZATION	OFF		VXX: NTPI 0=+00000	QVX: NTPI 0	NTPI 0=+00000	✓	✓			
	ON		VXX: NTPI 0=+00001		NTPI 0=+00001	✓	✓			
LENS TYPE	ET-D75LE6		VXX: LNEI 1=+00001	QVX: LNEI 1	LNEI 1=+00001	✓	✓			
	ET-D75LE10		VXX: LNEI 1=+00002		LNEI 1=+00002	✓	✓			
	ET-D75LE20		VXX: LNEI 1=+00003		LNEI 1=+00003	✓	✓			
	ET-D75LE30		VXX: LNEI 1=+00004		LNEI 1=+00004	✓	✓			
	ET-D75LE40		VXX: LNEI 1=+00005		LNEI 1=+00005	✓	✓			
	ET-D75LE8		VXX: LNEI 1=+00006		LNEI 1=+00006	✓	✓			
	ET-D75LE95		VXX: LNEI 1=+00007		LNEI 1=+00007	✓	✓			
	ET-D75LE90		VXX: LNEI 1=+00008		LNEI 1=+00008	✓	✓			
	ET-D75LE50		VXX: LNEI 1=+00009		LNEI 1=+00009	✓	✓			
LENS ID	All		VXX: LNEI 4=+00000	QVX: LNEI 4	LNEI 4=+00000	✓	✓			
	1		VXX: LNEI 4=+00001		LNEI 4=+00001	✓	✓			
	255		VXX: LNEI 4=+00255		LNEI 4=+00255	✓	✓			
LENS NAME			VXX: LNES5=LENSNAME	QVX: LNES5	LNES5=LENSNAME	✓	✓			
LENS CALIBRATION	EXECUTE (ALL)		VXX: LNSI 0=+00001			✓	✓			
	EXECUTE (SHIFT)		VXX: LNSI 0=+00011			✓	✓			
	EXECUTE (FOCUS)		VXX: LNSI 0=+00012			✓	✓			
	EXECUTE (ZOOM)		VXX: LNSI 0=+00013			✓	✓			
	EXECUTE (SHIFT/FOCUS)		VXX: LNSI 0=+00021			✓	✓			
	EXECUTE (SHIFT/ZOOM)		VXX: LNSI 0=+00022			✓	✓			
	EXECUTE (FOCUS/ZOOM)		VXX: LNSI 0=+00023			✓	✓			
LENS MEMORY1 NAME CHANGE	LENSMEMORY1		VXX: NCGS5=LENSMEMORY1	QVX: NCGS5	NCGS5=LENSMEMORY1	✓	✓			
LENS MEMORY2 NAME CHANGE	LENSMEMORY2		VXX: NCGS6=LENSMEMORY2	QVX: NCGS6	NCGS6=LENSMEMORY2	✓	✓			
LENS MEMORY3 NAME CHANGE	LENSMEMORY3		VXX: NCGS7=LENSMEMORY3	QVX: NCGS7	NCGS7=LENSMEMORY3	✓	✓			
LENS MEMORY4 NAME CHANGE	LENSMEMORY4		VXX: NCGS9=LENSMEMORY4	QVX: NCGS9	NCGS9=LENSMEMORY4	✓	✓			
LENS MEMORY5 NAME CHANGE	LENSMEMORY5		VXX: NCGSA=LENSMEMORY5	QVX: NCGSA	NCGSA=LENSMEMORY5	✓	✓			
LENS MEMORY6 NAME CHANGE	LENSMEMORY6		VXX: NCGSB=LENSMEMORY6	QVX: NCGSB	NCGSB=LENSMEMORY6	✓	✓			
LENS MEMORY7 NAME CHANGE	LENSMEMORY7		VXX: NCGSC=LENSMEMORY7	QVX: NCGSC	NCGSC=LENSMEMORY7	✓	✓			
LENS MEMORY8 NAME CHANGE	LENSMEMORY8		VXX: NCGSD=LENSMEMORY8	QVX: NCGSD	NCGSD=LENSMEMORY8	✓	✓			
LENS MEMORY9 NAME CHANGE	LENSMEMORY9		VXX: NCGSE=LENSMEMORY9	QVX: NCGSE	NCGSE=LENSMEMORY9	✓	✓			
LENS MEMORY10 NAME CHANGE	LENSMEMORY10		VXX: NCGSF=LENSMEMORY10	QVX: NCGSF	NCGSF=LENSMEMORY10	✓	✓			
LENS MEMORY-LOAD	LENS MEMORY1		VXX: LNMI 1=+00000			✓	✓			
	LENS MEMORY2		VXX: LNMI 1=+00001			✓	✓			
	LENS MEMORY3		VXX: LNMI 1=+00002			✓	✓			
	LENS MEMORY4		VXX: LNMI 1=+00003			✓	✓			
	LENS MEMORY5		VXX: LNMI 1=+00004			✓	✓			
	LENS MEMORY6		VXX: LNMI 1=+00005			✓	✓			
	LENS MEMORY7		VXX: LNMI 1=+00006			✓	✓			
	LENS MEMORY8		VXX: LNMI 1=+00007			✓	✓			
	LENS MEMORY9		VXX: LNMI 1=+00008			✓	✓			
	LENS MEMORY10		VXX: LNMI 1=+00009			✓	✓			
LENS MEMORY-SAVE	LENS MEMORY1		VXX: LNMI 2=+00000			✓	✓			
	LENS MEMORY2		VXX: LNMI 2=+00001			✓	✓			
	LENS MEMORY3		VXX: LNMI 2=+00002			✓	✓			
	LENS MEMORY4		VXX: LNMI 2=+00003			✓	✓			
	LENS MEMORY5		VXX: LNMI 2=+00004			✓	✓			
	LENS MEMORY6		VXX: LNMI 2=+00005			✓	✓			
	LENS MEMORY7		VXX: LNMI 2=+00006			✓	✓			
	LENS MEMORY8		VXX: LNMI 2=+00007			✓	✓			
	LENS MEMORY9		VXX: LNMI 2=+00008			✓	✓			
	LENS MEMORY10		VXX: LNMI 2=+00009			✓	✓			
LENS MEMORY-DELETE	LENS MEMORY1		VXX: LNMI 3=+00000			✓	✓			
	LENS MEMORY2		VXX: LNMI 3=+00001			✓	✓			
	LENS MEMORY3		VXX: LNMI 3=+00002			✓	✓			
	LENS MEMORY4		VXX: LNMI 3=+00003			✓	✓			
	LENS MEMORY5		VXX: LNMI 3=+00004			✓	✓			
	LENS MEMORY6		VXX: LNMI 3=+00005			✓	✓			
	LENS MEMORY7		VXX: LNMI 3=+00006			✓	✓			
	LENS MEMORY8		VXX: LNMI 3=+00007			✓	✓			
	LENS MEMORY9		VXX: LNMI 3=+00008			✓	✓			
	LENS MEMORY10		VXX: LNMI 3=+00009			✓	✓			
LENS MEMORY1-DEFAULT NAME	LENSMEMORY1		VXX: NCLI 5=+00000			✓	✓			
LENS MEMORY2-DEFAULT NAME	LENSMEMORY2		VXX: NCLI 6=+00000			✓	✓			
LENS MEMORY3-DEFAULT NAME	LENSMEMORY3		VXX: NCLI 7=+00000			✓	✓			
LENS MEMORY4-DEFAULT NAME	LENSMEMORY4		VXX: NCLI 9=+00000			✓	✓			
LENS MEMORY5-DEFAULT NAME	LENSMEMORY5		VXX: NCLI A=+00000			✓	✓			
LENS MEMORY6-DEFAULT NAME	LENSMEMORY6		VXX: NCLI B=+00000			✓	✓			
LENS MEMORY7-DEFAULT NAME	LENSMEMORY7		VXX: NCLI C=+00000			✓	✓			
LENS MEMORY8-DEFAULT NAME	LENSMEMORY8		VXX: NCLI D=+00000			✓	✓			
LENS MEMORY9-DEFAULT NAME	LENSMEMORY9		VXX: NCLI E=+00000			✓	✓			
LENS MEMORY10-DEFAULT NAME	LENSMEMORY10		VXX: NCLI F=+00000			✓	✓			
INITIALIZE-ALL USER DATA	USER INITIALIZE		VXX: RSTS1=0password			✓	✓			
	USER RESTORE		VXX: RSTS1=1password			✓	✓			
INITIAL START UP	STANDBY		OPY: 0	QPY	0	✓	✓			
	ON		OPY: 1		1	✓	✓			
	LAST MEMORY		OPY: 2		2	✓	✓			
MODEL NAME	MODEL NAME			QID	MODELNAME	✓	✓			
SERIAL NUMBER	SW0101234			QSN	SW0101234	✓	✓			
PROJECTOR RUNTIME	7864320H			QVX: RTMS1	RTMS1=7864320	✓	✓			
LAMP1(LIGHT1) RUNTIME	9999H			QSL: 1	9999	✓	✓			
LIGHT1 RUNTIME	7864320H			QVX: LRTS3=00	LRTS3=00: 7864320	✓	✓			
LIGHT STATUS	ALL OFF			QLS	0	✓	✓			
	1:ON, 2:OFF				1	✓	✓			
CONTINUOUS LIGHTING TIME	7864320H00M			QVX: CLTS1	CLTS1=7864320: 00	✓	✓			
CONSOLIDATED RUNTIME	7864320H			QVX: CRTS1	CRTS1=7864320	✓	✓			
LAMP(LIGHT) CONTROL STATUS	LAMP OFF			QSS	0	✓	✓			
	In turning ON				1	✓	✓			
	LAMP ON				2	✓	✓			
	LAMP Cooling				3	✓	✓			
POWER STATUS	POWER OFF			QVX: POWI 1	POWI 1=+00001	✓	✓			
	In turning ON				POWI 1=+00002	✓	✓			
	POWER ON				POWI 1=+00003	✓	✓			

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		RQ35K SERIES	RZ34K SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ35K SRQ35KC	RZ34K SRZ34KC	
CONTROL	MAC ADDRESS	AB0102030405				QMA	POWI 1=+00004 AB0102030405	✓	✓
	MAIN FIRMWARE VERSION	V1.00.01				QVX: SVRS0	SVRS0=1. 00. 01	✓	✓
	NETWORK FIRMWARE VERSION	V1.00				QVX: SVRS1	SVRS1=1. 00	✓	✓
	SUB FIRMWARE VERSION	V1.00.01				QVX: SVRS2	SVRS2=1. 00. 01	✓	✓
	INPUT SIGNAL NAME	CHANNEL1 (MAIN CH)				QVX: NSGS1	NSGS1=*****.....	✓	✓
	TEMPERATURE (INTAKE)	0030/0080				QTM: 0	0030/0080	✓	✓
	TEMPERATURE (EXHAUST AIR)	0030/0080				QTM: 1	0030/0080	✓	✓
	LAN data Cloning Write protect	OFF		LCL: WRP0		QCL: WRP	QCL: WRP0	✓	✓
		ON		LCL: WRP1			QCL: WRP1	✓	✓
	MECH. SHUTTER COUNT					QVX: MSCIO	MSCIO=+*****	✓	✓
	INFO MONITOR SETTING -	OFF		VXX: INFI 1=+00000		QVX: INFI 1	INFI 1=+00000	✓	✓
	USER VIEW			VXX: INFI 1=+00001			INFI 1=+00001	✓	✓
	INFO MONITOR SETTING - USER	INPUT SIGNAL		VXX: INFS2=01: *****		QVX: INFS2=01	INFS2=01: *****	✓	✓
		AC VOLTAGE		VXX: INFS2=02: *****		QVX: INFS2=02	INFS2=02: *****	✓	✓
		INTAKE AIR TEMP.		VXX: INFS2=03: *****		QVX: INFS2=03	INFS2=03: *****	✓	✓
		EXHAUST AIR TEMP.		VXX: INFS2=04: *****		QVX: INFS2=04	INFS2=04: *****	✓	✓
		SHUTTER		VXX: INFS2=05: *****		QVX: INFS2=05	INFS2=05: *****	✓	✓
		OSD		VXX: INFS2=06: *****		QVX: INFS2=06	INFS2=06: *****	✓	✓
		IP ADDRESS		VXX: INFS2=07: *****		QVX: INFS2=07	INFS2=07: *****	✓	✓
		OFF		VXX: INFS2=08: *****		QVX: INFS2=08	INFS2=08: *****	✓	✓
	ON		VXX: INFS2=** : 00000				✓	✓	
			VXX: INFS2=** : 00001				✓	✓	
INFO MONITOR SETTING -	AUTO		VXX: INFI 3=+00000		QVX: INFI 3	INFI 3=+00000	✓	✓	
	NORMAL		VXX: INFI 3=+00001			INFI 3=+00001	✓	✓	
	FLIPPED		VXX: INFI 3=+00002			INFI 3=+00002	✓	✓	
INFO MONITOR SETTING -	30%		VXX: INFI 4=+00030		QVX: INFI 4	INFI 4=+00030	✓	✓	
	100%		VXX: INFI 4=+00100			INFI 4=+00100	✓	✓	
TEST PATTERN	TEST PATTERN	Off		OTS: 00		QTS	00	✓	✓
		White		OTS: 01			01	✓	✓
		Black		OTS: 02			02	✓	✓
		Window		OTS: 05			05	✓	✓
		Reversed Window		OTS: 06			06	✓	✓
		Cross Hatch		OTS: 07			07	✓	✓
		Color Bar V		OTS: 08			08	✓	✓
		Focus (Level 0%)		OTS: 32			32	✓	✓
		Focus (Level 50%)		OTS: 33			33	✓	✓
		Focus (Level 100%)		OTS: 34			34	✓	✓
		Color Bar Side		OTS: 51			51	✓	✓
		16:9/4:3		OTS: 59			59	✓	✓
		Focus Red		OTS: 70			70	✓	✓
		Focus Green		OTS: 71			71	✓	✓
		Focus Blue		OTS: 72			72	✓	✓
		Focus Cyan		OTS: 73			73	✓	✓
		Focus Magenta		OTS: 74			74	✓	✓
		Focus Yellow		OTS: 75			75	✓	✓
		Focus		OTS: 78			78	✓	✓
		3D-1		OTS: 80			80	✓	✓
	3D-2		OTS: 81			81	✓	✓	
	3D-3		OTS: 82			82	✓	✓	
	3D-4		OTS: 83			83	✓	✓	
	CIRCLE		OTS: 87			87	✓	✓	
SIGNAL LIST	SIGNAL LIST-REGISTRATION			OEM				✓	✓
	SIGNAL LIST-DELETE	A1		ODM: A1				✓	✓
		A2		ODM: A2				✓	✓
		A7		ODM: A7				✓	✓
		A8		ODM: A8				✓	✓
		L1		ODM: L1				✓	✓
		L2		ODM: L2				✓	✓
		L7		ODM: L7				✓	✓
		L8		ODM: L8				✓	✓
		SUB MEMORY LIST-CHANGEVER	01		OCS: 01				✓
		96		OCS: 96				✓	✓
	SUB MEMORY LIST-CHANGEVER (EXTENDED)	01		OCS: 01-01				✓	✓
		96		OCS: 95-96				✓	✓
	SUB MEMORY LIST-REGISTRATION			OES				✓	✓
	SUB MEMORY LIST-DELETE	01		ODS: 01-01				✓	✓
		96		ODS: 95-96				✓	✓
	SUB MEMORY USAGE STATE	01				QSB	01	✓	✓
		96					96	✓	✓
SECURITY	SECURITY SETTING	OFF				QVX: SPWI 1	SPWI 1=+00000	✓	✓
		ON					SPWI 1=+00001	✓	✓
	CONTROL DEVICE SETUP-CONTROL PANEL	DISABLE		VXX: CDSI 1=+00000		QVX: CDSI 1	CDSI 1=+00000	✓	✓
		ENABLE		VXX: CDSI 1=+00001			CDSI 1=+00001	✓	✓
		USER		VXX: CDSI 1=+00002			CDSI 1=+00002	✓	✓
	CONTROL DEVICE SETUP-REMOTE CONTROL	DISABLE		VXX: CDSI 2=+00000		QVX: CDSI 2	CDSI 2=+00000	✓	✓
	ENABLE		VXX: CDSI 2=+00001			CDSI 2=+00001	✓	✓	
	USER		VXX: CDSI 2=+00002			CDSI 2=+00002	✓	✓	
NETWORK	WIRELESS LAN	OFF(DISABLE)		ONS: 0		QVX: WLSI 1	WLSI 1=+00000	✓	✓
		ON(ENABLE)		ONS: 14			WLSI 1=+00014	✓	✓
	DIGITAL LINK MODE	AUTO		VXX: DKMI 1=+00001		QVX: DKMI 1	DKMI 1=+00001	✓	✓
		DIGITAL LINK		VXX: DKMI 1=+00002			DKMI 1=+00002	✓	✓
		ETHERNET		VXX: DKMI 1=+00003			DKMI 1=+00003	✓	✓
		LONG REACH MODE		VXX: DKMI 1=+00004			DKMI 1=+00004	✓	✓
	DIGITAL LINK STATUS-LINK	NO LINK				QVX: DKSI 1	DKSI 1=+00000	✓	✓
		DIGITAL LINK					DKSI 1=+00001	✓	✓
		LPM					DKSI 1=+00002	✓	✓
		ETHERNET					DKSI 1=+00003	✓	✓
	DIGITAL LINK STATUS-HDCP STATUS	NO SIGNAL				QVX: DKSI 2	DKSI 2=+00000	✓	✓
		OFF					DKSI 2=+00001	✓	✓
		ON					DKSI 2=+00002	✓	✓
	DIGITAL LINK STATUS-SIGNAL QUALITY (MIN)	-255				QVX: DKSI 3	DKSI 3=- 00255	✓	✓
		0					DKSI 3=+00000	✓	✓
	DIGITAL LINK STATUS-SIGNAL QUALITY (MAX)	-255				QVX: DKSI 4	DKSI 4=- 00255	✓	✓
		0					DKSI 4=+00000	✓	✓
	DIGITAL LINK INPUT CH LIST	HD1:HDMI1,HD2:HDMI2...				QVX: DLIS1	DLIS1=HD1: HDMI 1, ****, ***	✓	✓
PROJECTOR NAME SETTING	PROJECTOR1			VXX: NCGS8=PROJECTOR1		QVX: NCGS8	NCGS8=PROJECTOR1	✓	✓
NFC SETTING	OFF			VXX: NFCI 1=+00000		QVX: NFCI 1	NFCI 1=+00000	✓	✓
	READ ONLY			VXX: NFCI 1=+00001			NFCI 1=+00001	✓	✓
	READ/WRITE			VXX: NFCI 1=+00003			NFCI 1=+00003	✓	✓
Art-Net SETUP	OFF			VXX: DANI 1=+00000		QVX: DANI 1	DANI 1=+00000	✓	✓
	ON(2.*.*)			VXX: DANI 1=+00002			DANI 1=+00002	✓	✓
	ON(10.*.*)			VXX: DANI 1=+00003			DANI 1=+00003	✓	✓
	ON(MANUAL)			VXX: DANI 1=+00004			DANI 1=+00004	✓	✓
Art-Net SETUP-START ADDRESS	1			VXX: DANI 3=+00001		QVX: DANI 3	DANI 3=+00001	✓	✓
	501			VXX: DANI 3=+00501			DANI 3=+00501	✓	✓
Art-Net SETUP-NET	0			VXX: DANI 4=+00000		QVX: DANI 4	DANI 4=+00000	✓	✓
	127			VXX: DANI 4=+00127			DANI 4=+00127	✓	✓
Art-Net SETUP-SUB NET	0			VXX: DANI 5=+00000		QVX: DANI 5	DANI 5=+00000	✓	✓
	15			VXX: DANI 5=+00015			DANI 5=+00015	✓	✓
Art-Net SETUP-UNIVERS	0			VXX: DANI 6=+00000		QVX: DANI 6	DANI 6=+00000	✓	✓
	15			VXX: DANI 6=+00015			DANI 6=+00015	✓	✓
Art-Net SETUP-CHANNEL SETTING	DEFAULT			VXX: DANI 8=+00000		QVX: DANI 8	DANI 8=+00000	✓	✓
	1			VXX: DANI 8=+00001			DANI 8=+00001	✓	✓
	2			VXX: DANI 8=+00002			DANI 8=+00002	✓	✓
	USER			VXX: DANI 8=+00100			DANI 8=+00100	✓	✓
PRESHOW MODE	OFF					QVX: PSMI 1	PSMI 1=+00000	✓	✓
	ON						PSMI 1=+00001	✓	✓

Note: The commands or parameters with "*" shows available commands or parameters for the projector which has been activated by the Upgrade Kit.